

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1	0	2SC3603	Nec	CX	SOT173	Npn RF FT 7GHz
2	-28	PDTA114WU	Phi	N	SOT323	pnp dtr
3	-24	PDTC114TU	Phi	N	SOT323	npn dtr R1 10k
4	-23	PDTA114TU	Phi	N	SOT323	pnp dtr R1 10k
5	-20	PDTC114WU	Phi	N	SOT323	npn dtr
6	1	2SC3587	Nec	CX		npn RF FT10GHz
7	1	BA277	Phi	I	SOD523	VHF Tuner band switch diode
8	2	BAT62-02W	Sie	I	SCD80	BAT16 schottky diode
9	2	BB182	Phi	I	SOD523	varicap 2.5-23pF
10	2	2SC3604	Nec	CX		npn RF FT8GHz 12dB@2GHz
11	3	BAT62-02W	Sie	I	SCD80	
12	4	BB664	Sie	I	SCD80	Varicap 42-2.5pF
13	8	BB178	Phi	I	SOD523	VHF varicap 2.5-16pf
14	9	DTC115TKA	Roh	N	SC59	npn dtr R2 100k 50V 100mA
15	9	BC849	Mot	N	SOT23	BC 549B
16	9	BB179	Phi	I	SOD523	UHF varicap 2-11.5pf
17	10	MRF9411L	Mot	X	SOT143	npn Rf 8GHz MRF941
18	11	MRF9511L	Mot	X	SOT143	npn RF 8GHz MRF951
19	11	MUN5311DW1	Mot	DP	SOT363	npn/pnp dtr 10k+10k
20	11	PDTA114EU	Phi	N	SOT416	pnp dtr
21	12	MUN5312DW1	Mot	DP	SOT363	npn/pnp dtr 22k+22k
22	12	DTA123EUA	Rho	N	SC70	pnp dtr 2k2+2k2 50V 100ma
23	12	DTA123EKA	Rho	N	SC59	pnp dtr 2k2+2k2 res 50V 100ma
24	13	DTA143EUA	Rho	N	SC70	pnp dtr 4k7+4k7 50V 100ma
25	13	DTA143EKA	Rho	N	SC59	pnp dtr 4k7+4k7 50V 100ma
26	13	DTA143ECA	Rho	N	SOT23	pnp dtr 4k7+4k7 50V 100ma
27	13	MA4CS103A	M/A	C	SOT23	Schottky RF 20V 100mA
28	13	MUN5313DW1	Mot	DP	SOT363	npn/pnp dtr 47k+47k
29	14	BAT114-099R	Sie	DQ		Quad Schottky crossover ring
30	14	DTA114EUA	Roh	N	SC70	pnp dtr 10k + 10k
31	14	DTA114EKA	Roh	N	SC59	pnp dtr 10k + 10k
32	14	MUN5314DW1	Mot	DP	SOT363	npn/pnp dtr 10k R1
33	14	DTA114ECA	Roh	N	SOT23	pnp dtr 10k + 10k
34	15	DTA124EUA	Roh	N	SC70	pnp dtr 30V 50mA 22k+22k
35	15	DTA124EKA	Roh	N	SC59	pnp dtr 30V 50mA 22k+22k
36	15	DTA124ECA	Roh	N	SOT23	pnp dtr 30V 50mA 22k+22k
37	15	MUN5315DW1	Mot	DP	SOT363	npn/pnp dtr 10k R1
38	15	MMBT3960	Mot	N		2N3960
39	16	MUN5316DW1	Mot	DP	SOT363	npn/pnp dtr 4k7 R1
40	16	DTA144EUA	Roh	N	SC70	pnp dtr 30V 50mA 47k+47k
41	16	DTA144EKA	Roh	N	SC59	pnp dtr 30V 50mA 47k+47k
42	18	BFP181T	Tfk	X		npn Rf FT 7.8GHz 10V 20mA
43	18	PDTC143ZK	Phi	N	SOT346	npn dtr 4k7+47k
44	19	PDTA143ZK	Phi	N	SOT346	pnp dtr 4k7+47k
45	19	DTA115EUA	Rho	N	SC70	pnp dtr 100k+100k 50V 100ma
46	19	DTA115EKA	Rho	N	SC59	pnp dtr 100k+100k 50V 100ma
47	20	MRF5811	Mot	X	SOT143	npn Rf FT 5GHz 0.2A
48	21	Gali-21	MC	AZ	SOT89	DC-8GHz MMIC amp 14 dB gain
49	22	MMBT4209	Nat	N	SOT23	pnp sw 850MHz 2N4209

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
50	22	DTC123EUA	Rho	N	SC70	npn dtr 2k2+2k2 50V 100ma
51	22	DTC123EKA	Rho	N	SC59	npn dtr 2k2+2k2 50V 100ma
52	23	MMBT3646	Nat	N	SOT23	npn sw 350MHz 2N3646
53	23	DTC143EUA	Roh	N	SC70	pnp dtr 50V 100mA 4k7+ 4k7
54	23	DTC143EKA	Roh	N	SC59	pnp dtr 50V 100mA 4k7+ 4k7
55	24	MMBD2101	Nat	C	SOT23	Si diode 100V 200mA
56	24	DTC114ECA	Roh	N	SOT23	npn dtr 50V 100mA 10k + 10k
57	24	DTC114EUA	Roh	N	SC70	npn dtr 50V 100mA 10k + 10k
58	24	DTC114EKA	Roh	N	SC59	npn dtr 50V 100mA 10k + 10k
59	24	2SC5006	Nec	N		npn RF FT 4.5GHz @3V 7mA
60	25	MMBD2102	Nat	K	SOT23	Si diode 100V 200mA
61	25	DTC124ECA	Roh	N	SOT23	npn dtr 50V 100mA 22k + 22k
62	25	DTC124EKA	Roh	N	SC59	npn dtr 50V 100mA 22k + 22k
63	25	DTC124EUA	Roh	N	SC70	npn dtr 50V 100mA 22k + 22k
64	26	MMBD2103	Nat	D	SOT23	dual MMBD1201
65	26	DTC144EKA	Roh	N	SC59	npn dtr 50V 30mA 47k + 47k
66	26	DTC144EUA	Roh	N	SC70	npn dtr 50V 30mA 47k + 47k
67	27	MMBD2104	Nat	B	SOT23	dual cc MMBD1201
68	28	BFP280T	Tfk	W		npn RF FT 7GHz 8V 10mA
69	28	MMBD2105	Nat	A	SOT23	dual ca MMBD1201
70	29	MMBD1401	Nat	C	SOT23	Si diode 200V 100mA
71	29	DTC115EE	Roh	N	EMT3	npn dtr 100k +100k 50V 20mA
72	29	DTC115EUA	Roh	N	SC70	npn dtr 100k +100k 50V 20mA
73	29	DTC115EKA	Roh	N	SC59	npn dtr 100k +100k 50V 20mA
74	30	MUN5330DW1	Mot	DP	SOT363	npn/pnp dtr 1k0+1k0
75	31	MUN5331DW1	Mot	DP	SOT363	npn/pnp dtr 2k2+2k2
76	31	MMBD1402	Nat	K	SOT23	Si diode 200V 100mA
77	32	MUN5332DW1	Mot	DP	SOT363	npn/pnp dtr 4k7+4k7
78	32	MMBD1403	Nat	D	SOT23	dual Si diode 200V 100mA
79	32	BAT32	Sie	CS		18GHz zero-bias schottky
80	33	MUN5333DW1	Mot	DP	SOT363	npn/pnp dtr 4k7+47k
81	33	DTA143XE	Roh	N	EMT3	pnp dtr 4k7+10k 50V 100mA
82	33	DTA143XUA	Roh	N	SC70	pnp sw 4k7+10k bias res 50V 100mA
83	33	DTA143XKA	Roh	N	SC59	pnp sw 4k7+10k bias res 50V 100mA
84	33	MMBD1404	Nat	B	SOT23	dual cc Si diode 200V 100mA
85	33	Gali-33	MC	AZ	SOT89	DC-4GHz MMIC amp 19dB gain
86	34	MUN5334DW1	Mot	DP	SOT363	npn/pnp dtr 22k+47k
87	34	MMBD1405	Nat	A	SOT23	dual ca Si diode 200V 100mA
88	34	2SC5007	Nec	N		npn RF FT 7GHz @3V 7mA
89	35	MUN5335DW1	Mot	DP	SOT363	npn/pnp dtr 2k2+47k
90	35	DTA124XE	Roh	N	EMT3	pnp dtr 22k+47k 50V 50mA
91	35	DTA124XUA	Roh	N	SC70	pnp dtr 22k+47k 50V 50mA
92	35	DTA124XKA	Roh	N	SC59	pnp dtr 22k+47k 50V 50mA
93	41	BAT14-115S	Sie	CS	SOT173	40GHz schottky diode
94	41	BAT14-115R	Sie	CZ	SOT173	40GHz schottky ring quad
95	42	BAT14-025S	Sie	CS	SOT173	4GHz schottky diode
96	42	BAT14-025R	Sie	CZ	SOT173	4GHz schottky ring quad
97	43	BAS40	Sie	C	SOT23	schottky diode 40V 100mA
98	43	DTA143EE	Mot	N	SOT416	pnp dtr 4k7 + 4k7

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
99	43	DTC143XE	Roh	N	EMT3	npn dtr 4k7+10k 50V 100mA
100	43	DTC143XUA	Roh	N	SC70	npn dtr 4k7+10k 50V 100mA
101	43	DTC143XKA	Roh	N	SC59	npn dtr 4k7+10k 50V 100mA
102	44	BAS40-04	Sie	D	SOT23	dual series BAS40
103	44	BAS40-04W	Sie	D	SOT323	dual series BAS40
104	44	2SC5009	Nec	N		npn RF FT 12GHz @3V 5mA
105	45	BAS40-05	Sie	A	SOT23	dual ca BAS40
106	45	BAS40-05W	Sie	A	SOT323	dual ca BAS40
107	45	BAT14-055S	Sie	CS	SOT173	8GHz schottky diode
108	45	BAT14-055R	Sie	CZ	SOT173	8GHz schottky ring quad
109	45	DTC124XE	Roh	N	EMT3	npn dtr 22k+47k 50V 50mA
110	45	DTC124XUA	Roh	N	SC70	npn dtr 22k+47k 50V 50mA
111	45	DTC124XKA	Roh	N	SC59	npn dtr 22k+47k 50V 50mA
112	46	BAS40-06	Sie	B	SOT23	dual cc BAS40
113	46	BAS40-06W	Sie	B	SOT323	dual cc BAS40
114	46	MBT3946DW	Mot	DP		2N3904/2N3906 pair
115	47	BAS40-07	Sie	S	SOT143	dual BAS40
116	47	BAS40-07W	Sie	S	SOT343	dual BAS40
117	49	BAT14-095S	Sie	CS	SOT173	18GHz schottky diode
118	49	BAT14-095R	Sie	CZ	SOT173	18GHz schottky ring quad
119	51	BAT15-115S	Sie	CS	SOT173	40GHz schottky diode
120	51	BAT15-115R	Sie	CZ	SOT173	40GHz schottky ring quad
121	52	BAT15-025S	Sie	CS	SOT173	4GHz schottky diode
122	52	BAT15-025R	Sie	CZ	SOT173	4GHz schottky ring quad
123	52	Gali-52	MC	AZ	SOT89	DC-2GHz MMIC amp 23 dB gain
124	52	BAS52-02V	Inf	I	SC79	Schottky diode 45V 750mA
125	52	DTA123YE	Roh	N	EMT3	pnp dtr 2k2 +10k 50V 100mA
126	52	DTA123YUA	Roh	N	SC70	pnp dtr 2k2 +10k 50V 100mA
127	52	DTA123YKA	Roh	N	SC59	pnp dtr 2k2 +10k 50V 100mA
128	54	DTA114YE	Roh	N	EMT3	pnp dtr 10k + 47k 50V 100mA
129	54	DTA114YUA	Roh	N	SC70	pnp dtr 10k + 47k 50V 100mA
130	54	DTA114YKA	Roh	N	SC59	pnp dtr 10k + 47k 50V 100mA
131	55	BAT15-055S	Sie	CS	SOT173	8GHz schottky diode
132	55	BAT15-055R	Sie	CZ	SOT173	8GHz schottky ring quad
133	55	Gali-55	MC	AZ	SOT89	DC-4GHz MMIC amp 21 dB gain
134	57	BFQ57	Sie	CX	SOT173	npn 6.5GHz 16V/35mA
135	58	BFQ58	Sie	CX	SOT173	npn 6.5GHz 16V/30mA
136	59	BAT15-095S	Sie	CS	SOT173	18GHz schottky diode
137	59	BAT15-095R	Sie	CZ	SOT173	18GHz schottky ring quad
138	62	DTC123YE	Roh	N	EMT3	npn dtr 2k2 +10k 50V 100mA
139	62	DTC123YUA	Roh	N	SC70	npn dtr 2k2 +10k 50V 100mA
140	62	DTC123YKA	Roh	N	SC59	npn dtr 2k2 +10k 50V 100mA
141	64	DTC114YE	Roh	N	EMT3	npn dtr 10k + 47k 50V 100mA
142	64	DTC114YUA	Roh	N	SC70	npn dtr 10k + 47k 50V 100mA
143	64	DTC114YKA	Roh	N	SC59	npn dtr 10k + 47k 50V 100mA
144	67	BFP67	Tfk	X		npn Rf FT 7.5GHz 10V 50mA
145	69	DTA114YE	Mot	N	SOT416	pnp dtr 10k +47k
146	69	DTC115EE	Roh	N	EMT3	npn dtr 100k+100k 50V 20mA
147	69	DTC115EUA	Roh	N	SC70	npn dtr 100k+100k 50V 20mA

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
148	69	DTC115EKA	Roh	N	SC59	nnp dtr 100k+100k 50V 20mA
149	70	BFQ70	Sie	CX	SOT173	nnp fT 5.2GHz 15V 35mA
150	71	BFQ71	Sie	CX	SOT173	nnp fT 5.2GHz 15V 30mA
151	72	BFQ72	Sie	CX	SOT173	nnp fT 5.1GHz 15V 50mA
152	72	2N7002	Sil	M	SOT23	n-ch mosfet 60V 170mA
153	73	MA4CS101A	M/A	C	SOT23	schottky diode 70V 50mA
154	73	BFQ73	Sie	CX	SOT173	nnp fT 4.9GHz 15V 75mA
155	73	2SC5004	Nec	N		nnp RF 5GHz @5V 5mA
156	74	BFQ74	Sie	CX	SOT173	nnp fT 6GHz 16V 35mA
157	74	MA4CS101B	M/A	D	SOT23	dual series MA4CS101A (73)
158	74	DTA114WE	Rho	N	EMT3	pnp dtr 10k + 4k7 50V 100mA
159	74	DTA114WUA	Rho	N	SC70	pnp dtr 10k + 4k7 50V 100mA
160	74	DTA114WKA	Rho	N	SC59	pnp dtr 10k + 4k7 50V 100mA
161	74	2SC5005	Nec	N		nnp RF 5.5GHz @5V 5mA
162	75	BFQ75	Sie	CX	SOT173	pnp fT 5GHz 12V 50mA
163	76	BFQ76	Sie	CX	SOT173	pnp fT 5GHz 15V 30mA
164	76	DTA144WE	Rho	N	EMT3	pnp dtr 47k + 22k 50V 30mA
165	76	DTA144WUA	Rho	N	SC70	pnp dtr 47k + 22k 50V 30mA
166	76	DTA144WKA	Rho	N	SC59	pnp dtr 47k + 22k 50V 30mA
167	77	MA4CS101E	M/A	S	SOT143	dual MA4CS101A (73)
168	77	BFQ77	Sie	CX	SOT173	nnp fT 7GHz 15V 20mA
169	78	MMBT4258	Nat	N	SOT23	pnp sw fT 700MHz
170	81	ZMV831BV2	Zet	I	SOD523	28V hyperabrupt varicap 15pF @2V
171	82	2SC5009	Nec	N		nnp RF fT 12GHz @ 3V 5mA
172	82	ZMV832BV2	Zet	I	SOD523	28V hyperabrupt varicap 22pF @2V
173	83	MMBT4400	Nat	N		nnp 2N4400
174	83	2SC5010	Nec	N		nnp RF fT 12GHz 3V 10mA
175	83	MA4CS102A	M/A	C	SOT23	schottky diode 8V 30mA
176	84	MA4CS102B	M/A	D	SOT23	dual ser schottky diode 8V 30mA
177	84	DTC114WE	Rho	N	EMT3	nnp dtr 10k + 4k7 50V 100mA
178	84	DTC114WUA	Rho	N	SC70	nnp dtr 10k + 4k7 50V 100mA
179	84	DTC114WKA	Rho	N	SC59	nnp dtr 10k + 4k7 50V 100mA
180	85	MMBD1701	Nat	C		Fast Si diode 30V 50mA
181	85	MA4CS102A	M/A	B	SOT23	dual cc schottky diode 8V 30mA
182	86	MMBD1702	Nat	K		Fast Si diode 30V 50mA
183	86	DTC144WE	Rho	N	EMT3	nnp dtr 47k + 22k 50V 30mA
184	86	DTC144WUA	Rho	N	SC70	nnp dtr 47k + 22k 50V 30mA
185	86	DTC144WKA	Rho	N	SC59	nnp dtr 47k + 22k 50V 30mA
186	87	MMBD1703	Nat	D		dual ser MMBD1701
187	87	MA4CS102A	M/A	S	SOT143	dual schottky diode 8V 30mA
188	88	MMBD1704	Nat	B		dual cc MMBD1701
189	89	MMBD1705	Nat	A		dual ca MMBD1701
190	91	ZV931V2	Zet	I	SOD523	4-13.5pF hyperabrupt varicap
191	91	DTA113TKA	Roh	N	SC59	pnp dtr R11k0 50V 100mA
192	92	ZV932V2	Zet	I	SOD523	5.5-17pF hyperabrupt varicap
193	93	ZV933V2	Zet	I	SOD523	12-42pF hyperabrupt varicap
194	93	DTA143TE	Roh	N	EMT3	pnp dtr R1 4k7 50V 100mA
195	93	DTA143TUA	Roh	N	SC70	pnp dtr R1 4k7 50V 100mA
196	93	DTA143TKA	Roh	N	SC59	pnp dtr R1 4k7 50V 100mA

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
197	94	DTA114TE	Roh	N	EMT3	pn p dtr R1 10k 50V 100mA
198	94	DTA114TUA	Roh	N	SC70	pn p dtr R1 10k 50V 100mA
199	94	DTA114TKA	Roh	N	SC59	pn p dtr R1 10k 50V 100mA
200	95	DTA124TE	Roh	N	EMT3	pn p dtr R1 22k 50V 100mA
201	95	DTA124TCA	Roh	N	SOT23	pn p dtr R1 22k 50V 100mA
202	95	DTA124TKA	Roh	N	SC59	pn p dtr R1 22k 50V 100mA
203	96	DTA144TE	Roh	N	EMT3	pn p dtr R1 47k 50V 100mA
204	96	DTA144TUA	Roh	N	SC70	pn p dtr R1 47k 50V 100mA
205	96	DTA144TKA	Roh	N	SC59	pn p dtr R1 47k 50V 100mA
206	99	DTA115TE	Roh	N	EMT3	pn p dtr R1 100k 50V 100mA
207	99	DTA115TUA	Roh	N	SC70	pn p dtr R1 100k 50V 100mA
208	99	DTA115TKA	Roh	N	SC59	pn p dtr R1 100k 50V 100mA
209	100	SSTPAD100	Sil	J	SOT23	PAD-100 100pA leakage diode
210	101	PZM10NB1	Phi	C	SOT346	10V 0.3W zener
211	102	PZM10NB2	Phi	C	SOT346	10V 0.3W zener
212	103	PZM10NB3	Phi	C	SOT346	10V 0.3W zener
213	111	PZM11NB1	Phi	C	SOT346	11V 0.3W zener
214	111	DTA113ZUA	Roh	N	SC70	pn p dtr 1k+10k 50V 100mA
215	112	PZM11NB2	Phi	C	SOT346	11V 0.3W zener
216	113	PZM11NB3	Phi	C	SOT346	11V 0.3W zener
217	113	DTA143ZUA	Roh	N	SC70	pn p dtr 4k7+47k 50V 100mA
218	121	PZM12NB1	Phi	C	SOT346	12V 0.3W zener
219	121	DTC113ZUA	Roh	N	SC70	npn dtr 1k+10k 50V 100mA
220	122	PZM12NB2	Phi	C	SOT346	12V 0.3W zener
221	123	PZM12NB3	Phi	C	SOT346	12V 0.3W zener
222	123	DTC143ZUA	Roh	N	SC70	npn dtr 4k7+47k 50V 100mA
223	131	PZM13NB1	Phi	C	SOT346	13V 0.3W zener
224	132	PZM13NB2	Phi	C	SOT346	13V 0.3W zener
225	132	DTA123JUA	Roh	N	SC70	pn p dtr 2k2+47k 50V 100mA
226	133	PZM13NB3	Phi	C	SOT346	13V 0.3W zener
227	142	DTA123JUA	Roh	N	SC70	npn dtr 2k2+47k 50V 100mA
228	151	PZM15NB1	Phi	C	SOT346	15V 0.3W zener
229	152	PZM15NB2	Phi	C	SOT346	15V 0.3W zener
230	153	PZM15NB3	Phi	C	SOT346	15V 0.3W zener
231	156	DTA144VUA	Roh	N	SC70	pn p dtr 47k+10k 50V 100mA
232	161	PZM16NB1	Phi	C	SOT346	16V 0.3W zener
233	162	PZM16NB2	Phi	C	SOT346	16V 0.3W zener
234	163	PZM16NB3	Phi	C	SOT346	16V 0.3W zener
235	166	DTC144VUA	Roh	N	SC70	npn dtr 47k+10k 50V 100mA
236	179	FMMT5179	Zet	N		2N5179
237	181	PZM18NB1	Phi	C	SOT346	18V 0.3W zener
238	182	PZM18NB2	Phi	C	SOT346	18V 0.3W zener
239	183	PZM18NB3	Phi	C	SOT346	18V 0.3W zener
240	200	SSTPAD200	Sil	J		PAD-200 200pA leakage diode
241	201	PZM20NB1	Phi	C	SOT346	20V 300mW Zener
242	202	PZM20NB2	Phi	C	SOT346	20V 300mW Zener
243	203	PZM20NB3	Phi	C	SOT346	20V 300mW Zener
244	221	PZM22NB1	Phi	C	SOT346	22V 300mW Zener
245	222	PZM22NB2	Phi	C	SOT346	22V 300mW Zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
246	223	PZM22NB3	Phi	C	SOT346	22V 300mW Zener
247	241	PZM24NB	Phi	C	SOT346	24V 300mW Zener
248	242	PZM24NB	Phi	C	SOT346	24V 300mW Zener
249	243	PZM20NB	Phi	C	SOT346	24V 300mW Zener
250	271	PZM2.7NB1	Phi	C	SOT346	2.7V 300mW Zener
251	272	PZM2.7NB2	Phi	C	SOT346	2.7V 300mW Zener
252	301	FDV301N	Fch	M	SOT23	n-ch 'digital' fet 25V 0.22A
253	302	FDV302P	Fch	M	SOT23	p-ch 'digital' fet 25V 0.13A
254	303	FDV303N	Fch	M	SOT23	n-ch 'digital' fet 25V 0.68A
255	304	FDV304P	Fch	M	SOT23	p-ch 'digital' fet 25V 0.46A
256	331	NDS331N	Fch	M	SOT23	n-ch mosfet 1.3A 20V
257	331	PZM3.3NB1	Phi	C	SOT346	3.3V 300mW zener
258	332	PZM3.3NB2	Phi	C	SOT346	3.3V 300mW zener
259	332	NDS332N	Fch	M	SOT23	p-ch mosfet 0.4A, 1A pk, 20V
260	335	NDS335N	Fch	M	SOT23	n-ch mosfet 70 mA, 1.7A pk, 20V
261	336	NDS336N	Fch	M	SOT23	p-ch mosfet 0.27A, 1.2A pk, 20V
262	337	NDS337N	Fch	M	SOT23	n-ch mosfet 50 mA, 2.5A pk 20V
263	338	NDS338N	Fch	M	SOT23	p-ch mosfet 0.13A, 1.6Apk 20V
264	340	FDV340P	Fch	M	SOT23	p-ch mosfet 20V 70 mA
265	351	NDS351N	Fch	M	SOT23	n-ch mosfet 1.1A 30V
266	352	NDS352N	Fch	M	SOT23	p-ch mosfet 0.5A 20V
267	355	NDS355N	Fch	M	SOT23	n-ch mosfet 0.1A, 1.6A pk 30V
268	356	NDS356N	Fch	M	SOT23	p-ch mosfet 0.3A, 1.1A pk 20V
269	357	NDS357N	Fch	M	SOT23	n-ch mosfet 2.5Apk 30V
270	358	NDS358N	Fch	M	SOT23	p-ch mosfet 0.2A, 1.6A pk 30V
271	358	FDN358N	Fch	M	SOT23	p-ch mosfet 0.2A 1.6A pk 30V
272	360	FDN360P	Fch	M	SOT23	p-ch mosfet 80mA, 2a PK, 30V
273	361	PZM3.6NB1	Phi	C	SOT346	3.6V 300mW Zener
274	362	PZM3.3NB2	Phi	C	SOT346	3.6V 300mW Zener
275	391	PZM3.9NB1	Phi	C	SOT346	3.9V 300mW Zener
276	392	PZM3.9NB2	Phi	C	SOT346	3.9V 300mW Zener
277	413	FMMT413	Zet	N	SOT23	nnp avalanche 150v 0.1A
278	415	FMMT415	Zet	N	SOT23	nnp avalanche 260v 0.1A
279	417	FMMT417	Zet	N	SOT23	nnp avalanche 320v 0.1A
280	431	PZM4.3NB1	Phi	C	SOT346	4.3V 0.3W zener
281	432	PZM4.3NB2	Phi	C	SOT346	4.3V 0.3W zener
282	433	PZM4.3NB3	Phi	C	SOT346	4.3V 0.3W zener
283	449	FMMT449	Zet	N	SOT23	nnp 50V 1A low Vce sat
284	451	FMMT451	Zet	N	SOT23	nnp 60V 1A
285	455	FMMT455	Zet	N	SOT23	NPN 140V 1A
286	458	FMMT458	Zet	N	SOT23	nnp 400V 0.4A
287	471	PZM4.7NB1	Phi	C	SOT346	4.7V 0.3W zener
288	472	PZM4.7NB2	Phi	C	SOT346	4.7V 0.3W zener
289	473	PZM4.7NB3	Phi	C	SOT346	4.7V 0.3W zener
290	491	FMMT491	Zet	N	SOT23	ZTX 450/451
291	493	FMMT493	Zet	N	SOT23	ZTX 453
292	494	FMMT494	Zet	N	SOT23	nnp 120V 1A
293	495	FMMT495	Zet	N	SOT23	nnp 170V 1A
294	497	FMMT497	Zet	N	SOT23	nnp 300V 0.5A

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
295	500	SSTPAD500	Sil	J		PAD-500 500pA leakage diode
296	511	PZM5.1NB1	Phi	C	SOT346	5.1V 0.3W zener
297	512	PZM5.1NB2	Phi	C	SOT346	5.1V 0.3W zener
298	513	PZM5.1NB3	Phi	C	SOT346	5.1V 0.3W zener
299	558	FMMT558	Zet	N	SOT23	pnnp 400V 0.15A
300	561	PZM5.1NB1	Phi	C	SOT346	5.6V 0.3W zener
301	562	PZM5.1NB2	Phi	C	SOT346	5.6V 0.3W zener
302	563	PZM5.1NB3	Phi	C	SOT346	5.6V 0.3W zener
303	589	FMMT589	Zet	N	SOT23	pnnp 30V 1A
304	591	FMMT591	Zet	N	SOT23	ZTX550/551
305	593	FMMT593	Zet	N	SOT23	ZTX 553
306	605	NDS0605	Fch	M	SOT23	P-ch mosfet 60V 180mA
307	605	NDS0605	Fch	M		p-ch sw mosfet 60V
308	610	NDS0610	Fch	M		p-ch sw mosfet 60V
309	614	FMMT614	Zet	N	SOT23	sw
310	617	FMMT617	Zet	N	SOT23	npn sw 15V 3A
311	618	FMMT618	Zet	N	SOT23	npn sw 20V 2.5A
312	619	FMMT619	Zet	N	SOT23	npn sw 50V 2A
313	621	PZM6.2NB1	Phi	C	SOT346	6.2V 0.3W zener
314	622	PZM6.2NB2	Phi	C	SOT346	6.2V 0.3W zener
315	623	PZM6.2NB3	Phi	C	SOT346	6.2V 0.3W zener
316	624	FMMT624	Zet	N	SOT23	
317	625	FMMT625	Zet	N	SOT23	
318	634	FMMT634	Zet	N	SOT23	100V 0.9A darlington npn
319	651	PZT651	Mot	N	SOT223	npn 60V 1A
320	681	PZM6.8NB1	Phi	C	SOT346	6.8V 0.3W zener
321	682	PZM6.8NB2	Phi	C	SOT346	6.8V 0.3W zener
322	683	PZM6.8NB1	Phi	C	SOT346	6.8V 0.3W zener
323	701	2N7001	Mot	M	SOT23	n-ch mosfet
324	702	2N7002	Mot	M	SOT23	n-ch mosfet 60V 0.11A
325	703	2N7003	Mot	M	SOT23	n-ch mosfet
326	712	NDS7002A	Nat	M	SOT23	n-ch mosfet 60V 0.28A
327	717	FMMT717	Zet	N	SOT23	pnnp sw 0.625W 2.5A 12V
328	718	FMMT718	Zet	N	SOT23	pnnp sw 0.625W 1.5A 20V
329	720	FMMT720	Zet	N	SOT23	pnnp sw 0.625W 1.5A
330	722	FMMT722	Zet	N	SOT23	pnnp sw
331	723	FMMT723	Zet	N	SOT23	pnnp sw
332	751	PZM7.5NB1	Phi	C	SOT346	7.5V 0.3W zener
333	752	PZM7.5NB2	Phi	C	SOT346	7.5V 0.3W zener
334	753	PZM7.5NB3	Phi	C	SOT346	7.5V 0.3W zener
335	821	PZM8.2NB1	Phi	C	SOT23	8.2V 0.3W zener
336	822	PZM8.2NB2	Phi	C	SOT23	8.2V 0.3W zener
337	822	S822T	Tfk	X		npn RF ft 5.2GHz 6V 8mA
338	823	PZM8.2NB3	Phi	C	SOT23	8.2V 0.3W zener
339	852	S852T	Tfk	N	SOT23	npn RF ft 5.2GHz 6V 8mA
340	887	S887T	Tfk	W	SOT143	n-ch dg uhf mosfet
341	888	S888T	Tfk	W	SOT142	n-ch dg uhf mosfet
342	911	PZM9.1NB1	Phi	C	SOT346	9.1V 0.3W zener
343	912	PZM9.1NB2	Phi	C	SOT346	9.1V 0.3W zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
344	913	PZM9.1NB3	Phi	C	SOT346	9.1V 0.3W zener
345	005	SSTPAD5	Sil	J		PAD-5 5pA leakage diode
346	01	Gali-1	MC	AZ	SOT89	DC-8GHz MMIC amp 12dB gain
347	010	SSTPAD10	Sil	J		PAD-10 10pA leakage diode
348	011	SO2369R	SGS	R	SOT23R	2N2369
349	02	BST82	Phi	M		n-ch mosfet 80V 175mA
350	02	MRF5711L	Mot	X	SOT143	npn RF MRF571
351	02	DTCC114T	Roh	N		50V 100mA npn sw + 10k base res
352	02	Gali-2	MC	AZ	SOT89	DC-8GHz MMIC amp 16dB gain
353	020	SSTPAD20	Sil	J		PAD-20 20pA leakage diode
354	03	Gali-3	MC	AZ	SOT89	DC-3GHz MMIC amp 22dB gain
355	03	DTC143TE	Roh	N	EMT3	npn dtr R1 4k7 50V 100mA
356	03	DTC143TUA	Roh	N	SC70	npn dtr R1 4k7 50V 100mA
357	03	DTC143TKA	Roh	N	SC59	npn dtr R1 4k7 50V 100mA
358	04	DTC114TCA	Roh	N	SOT23	npn dtr R1 10k 50V 100mA
359	04	DTC114TE	Roh	N	EMT3	npn dtr R1 10k 50V 100mA
360	04	DTC114TUA	Roh	N	SC70	npn dtr R1 10k 50V 100mA
361	04	DTC114TKA	Roh	N	SC59	npn dtr R1 10k 50V 100mA
362	04	MRF5211L	Mot	X	SOT143	pnp RF MRF521
363	04	Gali-4	MC	AZ	SOT89	DC-4GHz MMIC amp 17.5 dBm
364	-04	PMSS3904	Phi	N	SOT323	2N3904
365	05	Gali-4	MC	AZ	SOT89	DC-4GHz MMIC amp 18 dBm o/p
366	05	DTC124TE	Roh	N	EMT3	npn dtr R1 22k 50V 100mA
367	05	DTC124TUA	Roh	N	SC70	npn dtr R1 22k 50V 100mA
368	05	DTC124TKA	Roh	N	SC59	npn dtr R1 22k 50V 100mA
369	050	SSTPAD50	Sil	J		PAD-50 50pA leakage diode
370	05F	TSDF1205R	Trk	WQ		FT12GHz npn 4V 5mA
371	06	Gali-6	MC	AZ	SOT89	DC-4GHz MMIC amp 115 dBm o/p
372	06	DTC144TE	Roh	N	EMT3	npn dtr R1 47k 50V 100mA
373	06	DTC144TUA	Roh	N	SC70	npn dtr R1 47k 50V 100mA
374	06	DTC144TKA	Roh	N	SC59	npn dtr R1 47k 50V 100mA
375	-06	PMSS3906	Phi	N	SOT323	2N3906
376	081	SO2369AR	SGS	R	SOT23R	2N2369A
377	09	DTC115TUA	Roh	N	SC70	npn dtr R2 100k 50V 100mA
378	0A	MUN5111DW1	Mot	DO	SOT363	dual pnp dtr 10k+10k
379	0A	DTC125TUA	Roh	N	SC70	npn dtr R2 100k 50V 100mA
380	0A	DTC125TKA	Roh	N	SC59	npn dtr R2 100k 50V 100mA
381	0B	MUN5112DW1	Mot	DO	SOT363	dual pnp dtr 22k+22k
382	0C	MUN5113DW1	Mot	DO	SOT363	dual pnp dtr 47k+47k
383	0D	MUN5114DW1	Mot	DO	SOT363	dual pnp dtr 10k+47k
384	0E	MUN5115DW1	Mot	DO	SOT363	dual pnp dtr R1 10k
385	0F	MUN5116DW1	Mot	DO	SOT363	dual pnp dtr R1 4k7
386	0G	MUN5130DW1	Mot	DO	SOT363	dual pnp dtr 1k0+1k0
387	0H	MUN5131DW1	Mot	DO	SOT363	dual pnp dtr 2k2+2k2
388	0J	MUN5132DW1	Mot	DO	SOT363	dual pnp dtr 4k7+4k7
389	0K	MUN5133DW1	Mot	DO	SOT363	dual pnp dtr 4k7+47k
390	0L	MUN5134DW1	Mot	DO	SOT363	dual pnp dtr 22k+47k
391	0M	MUN5135DW1	Mot	DO	SOT363	dual pnp dtr 2k2+47k
392	1 (red)	BB669	Sie	I	SOD323	56-2.7 pF varicap

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
393	10A	PZM10NB2A	Phi	A	SOT346	dual ca 10V 0.3W zener
394	10V	PZM10NB	Phi	C	SOT346	10V 0.3W zener
395	10Y	BZV49-C10	Phi	O	SOT89	10V 1W zener
396	11A	PZM11NB2A	Phi	A	SOT346	dual ca 11V 0.3W zener
397	11A	MMBD1501A	Nat	C	SOT23	Si diode 200V 100mA
398	11V	PZM11NB	Phi	C	SOT346	11V 0.3W zener
399	11Y	BZV49-C11	Phi	O	SOT89	11V 1W zener
400	12A	MMBD1502A	Nat	K	SOT23	Si diode 200V 100mA
401	12A	PZM12NB2A	Phi	A	SOT346	dual ca 12V 0.3W zener
402	12E	ZC2812E	Zet	D	SOT23	dual series RF schottky15V 20mA
403	12V	PZM12NB	Phi	C	SOT346	12V 0.3W zener
404	12Y	BZV49-C12	Phi	O	SOT89	12V 1W zener
405	13A	MMBD1503A	Nat	D	SOT23	dual Si diode 200V 100mA
406	13A	PZM13NB2A	Phi	A	SOT346	dual ca 13V 0.3W zener
407	13E	ZC2813E	Zet	A	SOT23	dual ca RF schottky15V 20mA
408	13s	BAS125	Sie	C	SOT23	Schottky sw 24V 100mA
409	13s	BAS125W	Sie	C	SOT323	Schottky sw 24V 100mA
410	13t	BC846BPN	Phi	N	SOT363	BC546B
411	13V	PZM13NB	Phi	C	SOT346	13V 0.3W zener
412	13Y	BZV49-C13	Phi	O	SOT89	13V 1W zener
413	14A	MMBD1504A	Nat	B		dual cc Si diode 200V 100mA
414	14s	BAS125-04	Sie	D	SOT23	Dual series Schottky 25V 100mA
415	14s	BAS125-04W	Sie	D	SOT323	Dual series Schottky 25V 100mA
416	15A	MMBD1505A	Nat	A		dual ca Si diode 200V 100mA
417	15A	PZM15NB2A	Phi	A	SOT346	dual ca 15V 0.3W zener
418	15s	BAS125-05	Sie	B	SOT23	dual cc Schottky 25V 100mA
419	15s	BAS125-05W	Sie	B	SOT323	dual cc Schottky 25V 100mA
420	15V	PZM15NB	Phi	C	SOT346	15V 0.3W zener
421	15Y	BZV49-C15	Phi	O	SOT89	15V 1W zener
422	16s	BAS125-06	Sie	A	SOT23	dual ca Schottky 25V 100mA
423	16s	BAS125-06W	Sie	A	SOT323	dual ca Schottky 25V 100mA
424	16V	PZM16NB	Phi	C	SOT346	16V 0.3W zener
425	16Y	BZV49-C16	Phi	O	SOT89	16V 1W zener
426	17s	BAS125-07	Sie	S	SOT143	dual Schottky 25V 100mA
427	17s	BAS125-07W	Sie	S	SOT343	dual Schottky 25V 100mA
428	18V	PZM18NB	Phi	C	SOT346	18V 0.3W zener
429	18Y	BZV49-C18	Phi	O	SOT89	18V 1W zener
430	1A	BC846A	Phi	N	SOT23	BC546A
431	1A	BC846AT	Phi	N	SOT416	BC546A
432	1A	FMMT3904	Zet	N	SOT23	2N3904
433	1A	MMBT3904	Mot	N	SOT23	2N3904
434	1A	IRLML2402	IR	F	SOT23	n-ch mosfet 20V 0.9A
435	-1A	PMST3904	Phi	N	SOT323	2N3904
436	1A-	BC846AW	Phi	N	SOT323	BC546A
437	1AM	MMBT3904L	Mot	N	SOT23	2N3904
438	1Ap	BC846A	Phi	N	SOT23	BC546A
439	1At	BC846A	Phi	N	SOT23	BC546A
440	1At	BC846AW	Phi	N	SOT323	BC546A
441	1B	BC846B	Phi	N	SOT23	BC546B

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
442	1B	BC846BT	Phi	N	SOT416	BC546B
443	1B	FMMT2222	Zet	N	SOT23	2N2222
444	1B	MMBT2222	Mot	N	SOT23	2N2222
445	1B	IRLML2803	IR	F	SOT23	n-ch mosfet 30V 0.9A
446	-1B	PMST2222	Phi	N	SOT323	2N2222
447	1B-	BC846BW	Phi	N	SOT323	BC546B
448	1Bp	BC846B	Phi	N	SOT23	BC546B
449	1Bs	BC817UPN	Sie	N	SC74	
450	1Bt	BC846B	Phi	N	SOT23	BC546B
451	1Bt	BC846BW	Phi	N	SOT323	BC546B
452	1C	FMMT-A20	Zet	N	SOT23	MPSA20
453	1C	MMBTA20L	Mot	N	SOT23	MPS3904
454	1C	IRLML6302	IR	F	SOT23	p-ch mosfet 20V 0.6A
455	1Cp	BAP50-05	Phi	B	SOT23	dual cc GP RF pin diode
456	1Cs	BC847S	Sie		SOT363	BC457
457	1D	MMBTA42	Mot	N	SOT23	MPSA42 300V npn
458	1D	IRLML5103	IR	F	SOT23	p-ch mosfet 30V 0.6A
459	1D-	BC846W	Phi	N	SOT323	BC456
460	1DN	2SC4083	Roh	N		nnp 11V 3.2GHz TV tuners
461	1Dp	BC846	Phi	N	SOT23	BC456
462	1DR	MSD1328R	Mot	N	SOT346	nnp gp 25V 500mA
463	1Ds	BC846U	Sie	N	SC74	BC456
464	1Ds	BC846U	Sie		SOT363	BC456
465	1Dt	BC846	Phi	N	SOT23	BC456
466	1Dt	BC846W	Phi	N	SOT323	BC456
467	1E	BC847A	Phi	N	SOT23	BC547A
468	1E	BC847AT	Phi	N	SOT416	BC547A
469	1E	BC847AT	Dio	N	SOT523	BC547A
470	1E	FMMT-A43	Zet	N		MPSA43
471	1E	MMBTA43	Mot	N	SOT23	MPSA43 200V npn
472	1E-	BC847A	Phi	N	SOT323	BC547A
473	1EN	2SC4084	Roh	N		nnp 20V 2.0GHz TV tuners
474	1Ep	BC847A	Phi	N	SOT23	BC547A
475	1ER	BC847AR	Phi	R	SOT23R	BC547A
476	1Es	BC847A	Sie	N	SOT23	BC457
477	1Es	BC847AW	Sie	N	SOT323	BC457
478	1Et	BC847A	Phi	N	SOT23	BC547A
479	1Et	BC847A	Phi	N	SOT323	BC547A
480	1F	BC847B	Phi	N	SOT23	BC547B
481	1F	BC847BT	Phi	N	SOT416	BC547B
482	1F	BC847BT	Dio	N	SOT523	BC547B
483	1F	MMBT5550	Mot	N	SOT23	2N5550 140V npn
484	1F-	BC847BW	Phi	N	SOT323	BC547B
485	1Fp	BC847B	Phi	N	SOT23	BC547B
486	1FR	BC847BR	Phi	R	SOT23R	BC547B
487	1Fs	BC847B	Sie	N	SOT23	BC547B
488	1Fs	BC847BT	Sie	N	SC75	BC547B
489	1Fs	BC847BW	Sie	N	SOT323	BC547B
490	1Ft	BC847B	Phi	N	SOT23	BC547B

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
491	1Ft	BC847BW	Phi	N	SOT323	BC547B
492	1FZ	FMBT5550	Zet	N	SOT23	2N5550 140V npn
493	1G	BC847C	Phi	N	SOT23	BC547C
494	1G	BC847CT	Phi	N	SOT416	BC547C
495	1G	FMMT-A06	Zet	N	SOT23	MPSA06
496	1G	MMBTA06	Mot	N	SOT23	MPSA06
497	1G-	BC847CW	Phi	N	SOT323	BC547C
498	1GM	MMBTA06	Mot	N	SOT23	MPSA06
499	1Gp	BC847C	Phi	N	SOT23	BC547C
500	1GR	BC847CR	Phi	R	SOT23R	BC547C
501	1Gs	BC847C	Sie	N	SOT23	BC547C
502	1Gs	BC847CW	Sie	N	SOT323	BC547C
503	1Gt	BC847CW	Phi	N	SOT323	BC547C
504	1GT	SOA06	SGS	N	SOT23	MPSA06
505	1H	FMMT-A05	Zet	N		MPSA05
506	1H	MMBTA05	Mot	N	SOT23	MPSA05
507	1H-	BC847W	Phi	N	SOT323	BC547
508	1Hp	BC847	Phi	N	SOT23	BC547
509	1Ht	BC847	Phi	N	SOT23	BC547
510	1Ht	BC847W	Phi	N	SOT323	BC547
511	1HT	SOA05	SGS	N	SOT23	MPSA05
512	1J	BC848A	Phi	N	SOT23	BC548A
513	1J	FMMT2369	Zet	N	SOT23	2N2369
514	1J	MMBT2369	Mot	N	SOT23	MPS2369
515	1JA	MMBT2369A	Mot	N	SOT23	MPS2369A
516	1Jp	BCV61A	Phi	VQ	SOT143	nnp current mirror hFe 180
517	1JR	BC848AR	Phi	R	SOT23R	BC548A
518	1Js	BC848A	Sie	N	SOT23	BC548A
519	1Js	BC848AW	Sie	N	SOT323	BC548A
520	1Js	BCV61A	Sie	VQ	SOT143	nnp current mirror hFe 180
521	1JZ	BC848A	Zet	N	SOT23	BC548A
522	1K	BC848B	ITT	N	SOT23	BC548B
523	1K	MMBT6428	Mot	N	SOT23	MPSA18 50V
524	1K	FMMT4400	Zet	N	SOT23	2N4400
525	1KM	MMBT6428L	Mot	N	SOT23	MPSA18 50V
526	1Kp	BC848B	Phi	N	SOT23	BC548B
527	1Kp	BCV61B	Phi	VQ	SOT143B	nnp current mirror hFe 290
528	1KR	BC848BR	Phi	R	SOT23R	BC548B
529	1Ks	BC848B	Sie	N	SOT23	BC548B
530	1Ks	BC848BW	Sie	N	SOT323	BC548B
531	1Ks	BCV61B	Sie	VQ	SOT143B	nnp current mirror hFe 290
532	1KZ	FMMT4400	Zet	N	SOT23	2N4400
533	1L	BC848C	ITT	N	SOT23	BC548C
534	1L	MMBT6429	Mot	N		MPSA18 45V
535	1L	FMMT4401	Zet	N		2N4401
536	1L	BCV61C	Sie	VQ	SOT143B	nnp current mirror hFe 520
537	1Lp	BC848C	Phi	N	SOT23	BC548C
538	1Lp	BCV61C	Phi	VQ	SOT143B	nnp current mirror hFe 520
539	1LR	BC848CR	Phi	R	SOT23R	BC548C

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
540	1Ls	BC848C	Sie	N	SOT23	BC548C
541	1Ls	BC848CW	Sie	N	SOT323	BC548C
542	1M	MMBTA13	Mot	N	SOT23	MPSA13 darlington
543	1M	BC848C	Dio	N	SOT523	BC548
544	1M	FMMT-A13	Zet	N	SOT23	MPSA13
545	1Mp	BC848	Phi	N	SOT23	BC548
546	1Mp	BCV61	Phi	VQ	SOT143B	nnp current mirror
547	1N	FMMT-A14	Zet	N	SOT23	MPSA14
548	1N	MMBTA14	Mot	N	SOT23	MPSA14 darlington
549	1N5	ZTX11N15DF	Zet	N	SOT23	nnp 15V 3A low saturation V
550	1P	FMMT2222A	Zet	N		2N2222A
551	1P	MMBT2222A	Mot	N	SOT23	2N2222A
552	1P	BC847PN	Sie	DI		pnp/nnp separate pair gp AF
553	1Q	MMBT5088	Mot	N	SOT23	MPSA18 Vce 30V
554	1R	MMBT5089	Mot	N	SOT23	MPSA18 Vce 25V
555	1S	MMBT2369A	Nat	N	SOT23	2N2369A 500MHz sw nnp
556	1S	MSC3130	Mot	H	SOT346	nnp RF ft 1.4GHz 10V
557	1T	MMBT3960A	Mot	N		2N3960A
558	1U	MMBT2484L	Mot	N	SOT23	MPSA18
559	1V	MMBT6427	Mot	H	SOT23	2N6426/7 darlington nnp
560	1V-	BF820W	Phi	N	SOT323	nnp 300V 50mA BF420
561	1Vp	BF820	Phi	N	SOT23	nnp 300V 50mA BF420
562	1Vt	BF820	Phi	N	SOT23	nnp 300V 50mA BF420
563	1Vt	BF820W	Phi	N	SOT323	nnp 300V 50mA BF420
564	1W	FMMT3903	Zet	N	SOT23	2N3903
565	1W -	BF822W	Phi	N	SOT323	pnp 300V 50mA BF421
566	1W t	BF822W	Phi	N	SOT323	pnp 300V 50mA BF421
567	1Wp	BF821	Phi	N	SOT23	pnp 300V 50mA BF421
568	1Wt	BF821	Phi	N	SOT23	pnp 300V 50mA BF421
569	1X	MMBT930L	Mot	N	SOT23	MPS3904
570	1Xp	BF822	Phi	N	SOT23	nnp 250V 50mA BF422
571	1Xt	BF822	Phi	N	SOT23	nnp 250V 50mA BF422
572	1Y	MMBT3903	Mot	N	SOT23	2N3903
573	1Yp	BF823	Phi	N	SOT23	pnp 250V 50mA BF423
574	1Yt	BF823	Phi	N	SOT23	pnp 250V 50mA BF423
575	1Z	BAS70-06	Zet	A	SOT23	dual RF CA schottky diode
576	1Z	MMBT6517	Mot	N	SOT23	2N6517 nnp Vce 350V
577	2 (blue)	BAR64-03W	Sie	I	SOD323	pin diode
578	2 (white)	BB439	Sie	I	SOD323	29-5 pF varicap
579	20F	TSDF1220	Tfk	X	SOT143	ft 12GHz nnp 6V 20mA
580	20V	PZM20NB	Phi	C	SOT346	20V 300mW zener
581	20Y	BZV49-C20	Phi	O	SOT89	20V 1W zener
582	22V	PZM22NB	Phi	C	SOT346	22V 300mW zener
583	22Y	BZV49-C22	Phi	O	SOT89	22V 1W zener
584	24V	PZM24NB	Phi	C	SOT346	24V 300mW Zener
585	24Y	BZV49-C24	Phi	O	SOT89	24V 1W zener
586	27V	PZM27NB	Phi	C	SOT346	27V 300mW Zener
587	27Y	BZV49-C27	Phi	O	SOT89	27V 1W zener
588	2A	MMBT3906L	Mot	N	SOT23	2N3906

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
589	2A	MMBT3906W	Mot	N	SOT323	2N3906
590	2A	FMMT3906	Zet	N	SOT23	2N3906
591	2A4	PZM2.4NB2A	Phi	A	SOT346	dual 2.4V cc Zener
592	2A7	PZM2.7NB2A	Phi	A	SOT346	dual 2.7V cc Zener
593	2B	BC849B	ITT	N	SOT23	BC549B
594	2B	FMMT2907	Zet	N	SOT23	2N2907
595	2B	MMBT2907	Mot	N	SOT23	MPS2907
596	2B-	BC849BW	Phi	N	SOT323	BC549B
597	2Bp	BC849B	Phi	N	SOT23	BC549B
598	2BR	BC849BR	Phi	R	SOT23R	BC549B
599	2Bs	BC849B	Sie	N	SOT23	BC549B
600	2Bs	BC849BW	Sie	N	SOT323	BC549B
601	2Bt	BC849BW	Phi	N	SOT323	BC549B
602	2BZ	FMMT2907	Zet	N	SOT23	2N2907
603	2C	BC849C	ITT	N	SOT23	BC549C
604	2C	MMBTA70	Mot	N	SOT23	MPSA70
605	2C-	BC849CW	Phi	N	SOT323	BC549C
606	2Cp	BC849C	Phi	N	SOT23	BC549C
607	2CR	BC849CR	Phi	R	SOT23R	BC549C
608	2Cs	BC849C	Sie	N	SOT23	BC549C
609	2Cs	BC849CW	Sie	N	SOT323	BC549C
610	2Ct	BC849C	Phi	N	SOT23	BC549C
611	2Ct	BC849CW	Phi	N	SOT323	BC549C
612	2CZ	FMMTA70	Zet	N	SOT23	MPSA70
613	2D	MMBTA92	Mot	N	SOT23	MPSA92 pnp Vce 300V
614	2E	MMBTA93	Mot	N	SOT23	MPSA93 pnp Vce 200V
615	2E	FMMT-A93	Zet	N	SOT23	MPSA93
616	2F	BC850B	ITT	N	SOT23	BC550B
617	2F	FMMT2907A	Zet	N	SOT23	2N2907A
618	2F	MMBT2907A	Mot	N	SOT23	MPS2907A
619	2F	MMBT2907AW	Mot	N	SOT323	MPS2907A
620	2F-	BC850BW	Phi	N	SOT323	BC550B
621	2Fp	BC850B	Phi	N	SOT23	BC550B
622	2FR	BC850BR	Phi	R	SOT23R	BC550B
623	2Fs	BC850B	Sie	N	SOT23	BC550B
624	2Fs	BC850BW	Sie	N	SOT323	BC550B
625	2Ft	BC850B	Phi	N	SOT23	BC550B
626	2Ft	BC850BW	Phi	N	SOT323	BC550B
627	2G	BC850C	ITT	N	SOT23	BC550C
628	2G	FMMT-A56	Zet	N	SOT23	MPSA56
629	2G	MMBTA56	Mot	N	SOT23	MPSA56
630	2G-	BC850CW	Phi	N	SOT323	BC550C
631	2GM	MMBTA56	Mot	N	SOT23	MPSA56
632	2Gp	BC850C	Phi	N	SOT23	BC550C
633	2GR	BC850CR	Phi	R	SOT23R	BC550C
634	2Gs	BC850C	Sie	N	SOT23	BC550C
635	2Gt	BC850C	Phi	N	SOT323	BC550C
636	2Gt	BC850CW	Phi	N	SOT323	BC550C
637	2GT	SOA56	SGS	N	SOT23	MPSA56

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
638	2H	FMMT-A55	Zet	N	SOT23	MPSA55
639	2H	MMBTA55	Mot	N	SOT23	MPSA55
640	2HT	SOA55	SGS	N	SOT23	MPSA55
641	2J	MMBT3640	Mot	N	SOT23	MPS3640 pnp sw
642	2K	FMMT4402	Zet	N	SOT23	2N4402
643	2K	MMBT8598	Mot	N		2N4125 pnp 60V
644	2L	MMBT5401	Mot	N	SOT23	2N5401 pnp 150V
645	2L	FMMT4403	Zet	N	SOT23	2N4403
646	2M	FMMT5087	Zet	N	SOT23	2N5087
647	2M	MMBT404	Mot	N	SOT23	pnp-chopper 24V 150mA
648	2N	MMBT404A	Mot	N	SOT23	pnp-chopper 35V 150mA
649	2N0	ZXT11N20DF	Zet	N	SOT23	npn 20V 2.5A low sat switch
650	2P	FMMT2222R	Zet	R	SOT23R	2N2222
651	2P	MMBT5086	Mot	N	SOT23	2N5086
652	2Q	MMBT5087	Mot	N	SOT23	2N5087
653	2R	HSMS-8102	HP	Z	SOT23	10-14GHz schottky mixer pair
654	2T	SO4403	SGS	N	SOT23	2N4403
655	2T	MMBT4403	Mot	N	SOT23	2N4403
656	2T	HT2	Zet	N	SOT23	pnp 80V 100mA
657	2U	MMBTA63	Mot	N	SOT23	MPSA63 darlington
658	2V	MMBTA64	Mot	N	SOT23	MPSA64 darlington
659	2V4	PZM2.4NB	Phi	C	SOT346	2.4V 300mW Zener
660	2V7	PZM2.7NB	Phi	C	SOT346	2.7V 300mW Zener
661	2W	FMMT3905	Zet	N	SOT23	2N3905
662	2W	MMBT8599	Mot	N		2N4125 Vce 80V pnp
663	2X	SO4401	SGS	N	SOT23	2N4401
664	2X	MMBT4401	Mot	N	SOT23	2N4401
665	2Y4	BZV49-C2V4	Phi	O	SOT89	2.4V 1W zener
666	2Y7	BZV49-C2V7	Phi	O	SOT89	2.7V 1W zener
667	2Z	MMBT6520	Mot	N	SOT23	2N6520 pnp Vce 350V
668	2Z	BAS70-04	Zet	D	SOT23	dual series RF schottky 70V 15mA
669	2Z5	BAS70-05	Zet	B	SOT23	dual cc RF Schottky 70V 15mA
670	3 (white)	BAT60A	Sie	I	SOD323	10V 3A sw schottky
671	30V	PZM30NB1	Phi	C	SOT346	30V 300mW zener
672	30Y	BZV49-C30	Phi	O	SOT89	30V 1W zener
673	33V	PZM33NB1	Phi	C	SOT346	33 300mW zener
674	33Y	BZV49-C33	Phi	O	SOT89	33V 1W zener
675	36V	PZM36NB1	Phi	C	SOT346	36V 300mW Zener
676	36Y	BZV49-C36	Phi	O	SOT89	36V 1W zener
677	39V	PZM39NB1	Phi	C	SOT346	39V 300mW Zener
678	39Y	BZV49-C39	Phi	O	SOT89	39V 1W zener
679	3A	BC856A	ITT	N	SOT23	BC556A
680	3A	BC856AT	Phi	N	SOT416	BC556A
681	3A	MMBTH24	Mot	N	SOT23	VHF mixer npn fT 600MHz
682	3A-	BC856AW	Phi	N	SOT323	BC556A
683	3A0	PZM3.0NB2A	Phi	C	SOT346	dual 3.0V Zener
684	3A3	PZM3.3NB2A	Phi	C	SOT346	dual 3.3V Zener
685	3A6	PZM3.6NB2A	Phi	C	SOT346	dual 3.6V Zener
686	3A9	PZM3.9NB2A	Phi	C	SOT346	dual 3.9V Zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
687	3Ap	BC856A	Phi	N	SOT23	BC556A
688	3AR	BC856AR	Phi	R	SOT23R	BC556A
689	3As	BC856A	Sie	N	SOT23	BC556A
690	3At	BC856A	Phi	N	SOT23	BC556A
691	3At	BC856AW	Phi	N	SOT323	BC556A
692	3B	BC856B	ITT	N	SOT23	BC556B
693	3B	BC856BT	Phi	N	SOT416	BC556B
694	3B	FMMT918	Zet	N	SOT23	2N918
695	3B	MMBT918	Mot	N	SOT23	2N918
696	3B-	BC856BW	Phi	N	SOT323	BC556B
697	3Bp	BC856B	Phi	N	SOT23	BC556B
698	3BR	BC856BR	Phi	R	SOT23	BC556B
699	3Bs	BC856B	Sie	N	SOT23	BC556B
700	3Bt	BC856B	Phi	N	SOT23	BC556B
701	3Bt	BC856BW	Phi	N	SOT323	BC556B
702	3C	FMMTA20R	Zet	R	SOT23R	MPSA20
703	3C	BC857	Sie	DO		pnp separate pair gp AF
704	3D	BC856	Phi	N	SOT23	BC556 hfe 75 min
705	3D	MMBTH81L	Mot	N	SOT23	UHF pnp fT 600MHz
706	3D	BC856S	Sie	DO		pnp separate pair gp AF
707	3D-	BC856W	Phi	N	SOT323	BC556 hfe 75 min
708	3Dp	BC856	Phi	N	SOT23	BC556 hfe 75 min
709	3Dt	BC856	Phi	N	SOT23	BC556 hfe 75 min
710	3Dt	BC856W	Phi	N	SOT323	BC556 hfe 75 min
711	3E	BC857A	Phi	N	SOT23	BC557A
712	3E	BC857AT	Phi	N	SOT416	BC557A
713	3E	MMBTH10	Mot	N	SOT23	MPSH10 fT 650MHz
714	3E	FMMT-A42	Zet	N	SOT23	MPSA42
715	3E-	BC857A	Phi	N	SOT323	BC557A
716	3EM	MMBTH10L	Mot	N	SOT23	VHF amp 650MHz fT
717	3Ep	BC857A	Phi	N	SOT23	BC557A
718	3ER	BC857AR	Phi	R	SOT23R	BC557A
719	3Et	BC857A	Phi	N	SOT23	BC557A
720	3Et	BC857A	Phi	N	SOT323	BC557A
721	3EZ	FMMTH10	Zet	N	SOT23	nnp fT 650MHz
722	3F	BC857B	Phi	N	SOT23	BC557B
723	3F	BC857BT	Phi	N	SOT416	BC557B
724	3F-	BC857BW	Phi	N	SOT323	BC557B
725	3Fp	BC857B	Phi	N	SOT23	BC557B
726	3FR	BC857BR	Phi	R	SOT23R	BC557B
727	3Fs	BC857B	Sie	N	SOT23	BC557B
728	3Ft	BC857B	Phi	N	SOT23	BC557B
729	3Ft	BC857BW	Phi	N	SOT323	BC557B
730	3Ft	BC857BS	Phi	N	SOT363	BC557B
731	3G	BC857C	Phi	N	SOT23	BC557C
732	3G	BC857C	Phi	N	SOT23	BC557C
733	3G	MMBTH11	NS	N	SOT23	
734	3G	BC857CT	Dio	N	SOT523	BC557C
735	3G	MGSF3454X	Mot	DK	TSOP6	n-ch enh tmosfet 1.75A

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
736	3G-	BC857CW	Phi	N	SOT323	BC557C
737	3Gp	BC857C	Phi	N	SOT23	BC557C
738	3GR	BC857CR	Phi	R	SOT23R	BC557CR
739	3Gs	BC857C	Sie	N	SOT23	BC557C
740	3Gt	BC857C	Phi	N	SOT23	BC557C
741	3Gt	BC857CW	Phi	N	SOT323	BC557C
742	3H	MMBTH30	NS	N	SOT23	
743	3H-	BC857CW	Phi	N	SOT323	BC557
744	3Hp	BC857C	Phi	N	SOT23	BC557
745	3Ht	BC857C	Phi	N	SOT23	BC557
746	3Ht	BC857CW	Phi	N	SOT323	BC557
747	3J	MMBTH69	Mot	N	SOT23	pnP UHF FT 2GHz
748	3J	BC858A	Phi	N	SOT23	BC558A
749	3Jp	BCV62A	Phi	VQ	SOT143	pnP current mirror hFe 180
750	3JR	BC858AR	Phi	R	SOT23R	BC558A
751	3Js	BC858A	Sie	N	SOT23	BC558A
752	3Js	BCV62A	Sie	VQ	SOT143	pnP current mirror hFe 180
753	3K	BC858B	Phi	N	SOT23	BC558B
754	3Kp	BCV62B	Phi	VQ	SOT143	npn current mirror hFe 290
755	3KR	BC858BR	Phi	R	SOT23R	BC558B
756	3Ks	BCV62B	Sie	VQ	SOT143	npn current mirror hFe 290
757	3L	BC858C	Phi	N	SOT23	BC558C
758	3Lp	BCV62C	Phi	VQ	SOT143	pnP current mirror hFe 520
759	3LR	BC858CR	Phi	R	SOT23R	BC558C
760	3Ls	BCV62C	Sie	VQ	SOT143	pnP current mirror hFe 520
761	3M	BC858	Phi	N	SOT23	BC558
762	3M	FMMT5087R	Zet	R	SOT23R	2N5087 BC322
763	3Mp	BCV62	Phi	VQ	SOT143	pnP current mirror
764	3Ms	BCV62	Sie	VQ	SOT143	pnP current mirror
765	3N	MMBT4402	Nat	N	SOT23	2N4402 pnp
766	3P	FMT2222AR	Zet	R	SOT23R	2N2222A
767	3R	MMBT5571	Nat	N	SOT23	pnP sw 850MHz
768	3S	MMBT5551	Nat	N	SOT23	npn 160V
769	3T	HT3	Zet	N	SOT23	npn 80V 100mA
770	3V	BC857AT	Dio	N	SOT523	BC557A
771	3V0	PZM3.0NB	Phi	C	SOT346	3.0V 300mW Zener
772	3V3	PZM3.3NB	Phi	C	SOT346	3.3V 300mW Zener
773	3V6	PZM3.6NB	Phi	C	SOT346	3.6V 300mW Zener
774	3V9	PZM3.9NB	Phi	C	SOT346	3.9V 300mW Zener
775	3W	FMMT-A12	Zet	N		MPSA12
776	3W	BC857BT	Dio	N	SOT523	BC557B
777	3Y3	BZV49-C3V3	Phi	O	SOT89	3.3V 1W zener
778	3Y6	BZV49-C3V6	Phi	O	SOT89	3.6V 1W zener
779	3Y9	BZV49-C3V9	Phi	O	SOT89	3.9V 1W zener
780	4 (white)	BAS140W	Sie	I	SOD323	40V 120mA sw schottky
781	4 (yellow)	BB644	Sie	I	SOD323	Varicap 42-2.5pF
782	4 (red)	BB57-03W	Sie	I	SOD323	Varicap
783	41A	FMMT491A	Zet	N	SOT23	npn 40v 1A max
784	41D	BAT14-115D	Sie	CY	SOT173	40GHz schottky dual

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
785	42D	BAT14-025D	Sie	CY	SOT173	4GHz schottky dual
786	43V	PZM43NB	Phi	C	SOT346	43V 0.3W zener
787	43Y	BZV49-C43	Phi	O	SOT89	43V 1W zener
788	45D	BAT14-055D	Sie	CY	SOT173	8GHz schottky dual
789	47V	PZM47NB	Phi	C	SOT346	47V 0.3W zener
790	47Y	BZV49-C47	Phi	O	SOT89	47V 1W zener
791	49D	BAT14-095D	Sie	CY	SOT173	18GHz schottky dual
792	4A	MMBV109	Mot	C	SOT23	MV209 varicap
793	4A	FMMV109	Zet	C	SOT23	MV209 varicap
794	4A	HD3A	Zet	C		75V 100mA sw diode
795	4A	BC859A	ITT	N	SOT23	BC559A
796	4A3	PZM4.3NB2A	Phi	A	SOT346	dual ca 4.3V Zener
797	4A7	PZM4.7NB2A	Phi	A	SOT346	dual ca 4.7V Zener
798	4Ap	BC859A	Phi	N	SOT23	BC559A
799	4AR	BC859AR	Phi	R	SOT23R	BC559A
800	4As	BC859AW	Sie	N	SOT323	BC559A
801	4As	BC859A	Sie	N	SOT23	BC559A
802	4B	MMBV432	Mot	B		dual cc varicap 1.5-45pF
803	4B	BC859B	ITT	N	SOT23	BC559B
804	4B-	BC859BW	Phi	N	SOT323	BC559B
805	4Bp	BC859B	Phi	N	SOT23	BC559B
806	4BR	BC859BR	Phi	R	SOT23R	BC559B
807	4Bs	BC859B	Sie	N	SOT23	BC559B
808	4Bs	BC859BW	Sie	N	SOT323	BC559B
809	4Bt	BC859B	Phi	N	SOT23	BC559B
810	4Bt	BC859BW	Phi	N	SOT323	BC559B
811	4C	BC859C	ITT	N	SOT23	BC559C
812	4C	MMVB3102	Mot	C	SOT23	varicap 6-35pF
813	4C	BC859C	Phi	N	SOT23	BC559C
814	4C-	BC859CW	Phi	N	SOT323	BC559C
815	4Cp	BC859C	Phi	N	SOT23	BC559C
816	4CR	BC859CR	Phi	R	SOT23R	BC559C
817	4Cs	BC859C	Sie	N	SOT23	BC559C
818	4Cs	BC859CW	Sie	N	SOT323	BC559C
819	4Ct	BC859C	Phi	N	SOT23	BC559C
820	4Ct	BC859CW	Phi	N	SOT323	BC559C
821	4D	BC859B	Phi	N	SOT23	BC559B
822	4D	MMBV3401	Mot	C	SOT23	VHF pin diode
823	4D	HD3A	Zet	C	SOT23	sw diode 75V 100mA
824	4D-	BC859W	Phi	N	SOT323	BC559B
825	4Dt	BC859W	Phi	N	SOT323	BC559B
826	4E	BC860A	Phi	N	SOT23	BC560A
827	4E	FMMT-A92	Zet	N	SOT23	MPSA92
828	4E	MMBV105G	Mot	C	SOT23	MV105 varicap
829	4ER	BC860AR	Phi	R	SOT23R	BC560A
830	4F	MMBD353	Mot	Z	SOT23	dual MBD101
831	4F	BC860B	Phi	N	SOT23	BC560B
832	4F	Gali-4F	MC	AZ	SOT89	DC-4GHz MMIC amp 15 dBm o/p
833	4F-	BC860BW	Phi	N	SOT323	BC560B

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
834	4Fp	BC860B	Phi	N	SOT23	BC560B
835	4FR	BC860BR	Phi	R	SOT23	BC560B
836	4Fs	BC860B	Sie	N	SOT23	BC560B
837	4Fs	BC860BW	Sie	N	SOT323	BC560B
838	4Ft	BC860B	Phi	N	SOT23	BC560B
839	4Ft	BC860BW	Phi	N	SOT323	BC560B
840	4G	MMBV2101	Mot	C	SOT23	MV2101 varicap
841	4G	BC860C	Phi	N	SOT23	BC560C
842	4G-	BC860CW	Phi	N	SOT323	BC560C
843	4Gp	BC860C	Phi	N	SOT23	BC560C
844	4GR	BC860CR	Phi	R	SOT23	BC560CR
845	4Gs	BC860C	Sie	N	SOT23	BC560C
846	4Gs	BC860CW	Sie	N	SOT323	BC560C
847	4Gt	BC860C	Phi	N	SOT23	BC560C
848	4Gt	BC860CW	Phi	N	SOT323	BC560C
849	4H	MMBV2103	Mot	C	SOT23	MV2103 varicap
850	4H-	BC860W	Phi	N	SOT323	BC560
851	4Hp	BC860	Phi	N	SOT23	BC560
852	4Ht	BC860W	Phi	N	SOT323	BC560
853	4J	FMMT38A	Zet	N	SOT23	BCX38A
854	4J	MMBV2109	Mot	C	SOT23	MV2109 varicap
855	4K	BAP64-04	Phi	D		dual series 3GHz pin diode
856	4K	MMSB3000	Mot	I	SOD123	Si diode 30V 0.2A
857	4L	BAP50-04	Phi	D		dual series GP RF pin diode
858	4M	MMBD101	Mot	C	SOT23	MBD101 schottky diode
859	4Ms	BAT240A	Sie	EQ	SOT143	dual schottky 250V 0.4A
860	4R	MMBV3700	Mot	C	SOT23	200V vhf pin diode
861	4S	MMBD201	Mot	C	SOT23	MBD201
862	4T	MMBD301	Mot	C	SOT23	MBD301 UHF schottky diode
863	4U	MMBV2105	Mot	C	SOT23	MV2105 varicap
864	4V	MMBV2106	Mot	C	SOT23	MV2106 varicap
865	4V	BCW65AR	Zet	R	SOT23R	nnp 32V 0.8A
866	4V3	PZM4.3NB	Phi	C	SOT346	4.3V 0.3W zener
867	4V7	PZM4.7NB	Phi	C	SOT346	4.7V 0.3W zener
868	4W	MMBV2107	Mot	C	SOT23	MV2107 varicap
869	4W	BCW67AR	Zet	R	SOT23R	pnp 32V 0.8A
870	4X	MMBV2108	Mot	C	SOT23	MV2108 varicap
871	4Y	MMBV2102	Mot	C	SOT23	MV2102 varicap
872	4Y3	BZV49-C4V3	Phi	O	SOT89	4.3V 1W zener
873	4Y7	BZV49-C4V7	Phi	O	SOT89	4.7V 1W zener
874	4Z	MMBV2104	Mot	C	SOT23	MV2104 varicap
875	5 (red)	BBY57-03W	Sie	I	SOD323	varicap
876	5 (white)	BAT60B	Sie	I		10V 3A sw Schottky
877	51D	BAT15-115D	Sie	CY	SOT173	40GHz schottky dual
878	51V	PZM51NB	Phi	C	SOT346	51V 0.3W zener
879	51Y	BZV49-C51	Phi	O	SOT89	51V 1W zener
880	52D	BAT15-025D	Sie	CY	SOT173	4GHz schottky dual
881	53s	BAT17	Sie	C	SOT23	schottky diode 4V 100mA
882	54s	BAT17-04	Sie	D	SOT23	dual series BAT17

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
883	54s	BAT17-04W	Sie	D	SOT323	dual series BAT17
884	55D	BAT15-055D	Sie	CY	SOT173	8GHz schottky dual
885	55s	BAT17-05	Sie	A	SOT23	dual ca BAT17
886	55s	BAT17-05W	Sie	A	SOT323	dual ca BAT17
887	56s	BAT17-06	Sie	B	SOT23	dual cc BAT17
888	56s	BAT17-06W	Sie	B	SOT323	dual cc BAT17
889	56V	PZM56NB	Phi	C	SOT346	56V 0.3W zener
890	56Y	BZV49-C56	Phi	O	SOT89	56V 1W zener
891	57s	BAT17-07	Sie	S	SOT143	dual BAT17
892	59D	BAT15-095D	Sie	CY	SOT173	18GHz schottky dual
893	5A	BC807-16	Phi	N	SOT23	BC327-16
894	5A	BSS123	Mot	M	SOT23	n-ch tmosfet Vds 100V
895	5A	MMBD6050	Mot	C	SOT23	sw diode 70V 0.2A
896	5A	FMMD6050	Zet	C	SOT23	sw diode 70V 100mA
897	5A-	BC807-16W	Phi	N	SOT323	BC327-16
898	5A1	PZM5.1NB2A	Phi	A	SOT346	dual ca 5.1V 0.3W zener
899	5A6	PZM5.6NB2A	Phi	A	SOT346	dual ca 5.6V 0.3W zener
900	5Ap	BC807-16	Phi	N	SOT23	BC327-16
901	5AR	BC807-16R	Phi	R	SOT23R	BC327-16
902	5As	BC807-16	Sie	N	SOT23	BC327-16
903	5As	BC807-16W	Sie	N	SOT323	BC327-16
904	5At	BC807-16	Phi	N	SOT23	BC327-16
905	5At	BC807-16W	Phi	N	SOT323	BC327-16
906	5B	MMBT4123	Mot	N	SOT23	2N4123
907	5B	BC807-25	SGS	N	SOT23	BC327-25
908	5B	MMBD6100	Mot	B	SOT23	cc dual diode 70V 0.2A
909	5B	FMMD6100	Zet	B	SOT23	cc dual diode 70V 0.2A
910	5B-	BC807-25W	Phi	N	SOT323	BC327-25
911	5BM	MMBD6100	Mot	B	SOT23	cc dual diode 70V 0.2A
912	5Bp	BC807-25	Phi	N	SOT23	BC327-25
913	5BR	BC807-25R	Phi	R	SOT23R	BC327-25
914	5Bs	BC807-25	Sie	N	SOT23	BC327-25
915	5Bs	BC807-25W	Sie	N	SOT323	BC327-25
916	5Bs	BC807-25U	Sie	N	SC74	BC327-25
917	5Bt	BC807-25	Phi	N	SOT23	BC327-25
918	5Bt	BC807-25W	Phi	N	SOT323	BC327-25
919	5C	BC807-40	SGS	N	SOT23	BC327-40
920	5C	MMBD7000	Mot	D	SOT23	2 ser diodes 100V 0.2A
921	5C	FMMD7000	Zet	D	SOT23	2 ser diodes 70V 200mA
922	5C-	BC807-40W	Phi	N	SOT323	BC327-40
923	5Cp	BC807-40	Phi	N	SOT23	BC327-40
924	5CR	BC807-40R	Phi	R	SOT23E	BC327-40
925	5Cs	BC807-40	Sie	N	SOT23	BC327-40
926	5Cs	BC807-40W	Sie	N	SOT323	BC327-40
927	5Ct	BC807-40	Phi	N	SOT23	BC327-40
928	5Ct	BC807-40W	Phi	N	SOT323	BC327-40
929	5D	FMMD914	Zet	C	SOT23	1N914
930	5D	MMBD914	Mot	C	SOT23	1N914
931	5D	MMSD914	Mot	I	SOD123	1N914

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
932	5D	HD2A	Zet	B		dual cc HD2 75V 100mA
933	5D-	BC807W	Phi	N	SOT323	BC327
934	5Dp	BC807	Phi	N	SOT23	BC327
935	5Dt	BC807	Phi	N	SOT23	BC327
936	5Dt	BC807W	Phi	N	SOT323	BC327
937	5E	BC808-16	Phi	N	SOT23	BC328-16
938	5E	FMMT-A43R	Zet	R	SOT23R	MPSA43
939	5E	BC808-16	Phi	N	SOT23	BC328-16
940	5ER	BC808-16R	Phi	R	SOT23R	BC328-16
941	5Es	BC808-16	Sie	N	SOT23	BC328-16
942	5Es	BC808-16W	Sie	N	SOT323	BC328-16
943	5F	BC808-25	Phi	N	SOT23	BC328-25
944	5F	MMBD501	Mot	C	SOT23	MBD501 hot carrier diode
945	5F	Gali-5F	MC	AZ	SOT89	DC-4GHz MMIC amp 20 dB gain
946	5FR	BC808-25R	Phi	R	SOT23R	BC328-25
947	5Fs	BC808-25	Sie	N	SOT23	BC328-25
948	5Fs	BC808-25W	Sie	N	SOT323	BC328-25
949	5G	BC808-40	Phi	N	SOT23	BC328-40
950	5G	MMBD353	Mot	D		dual series MBD101
951	5GR	BC808-40R	Phi	R	SOT23R	BC328-40
952	5Gs	BC808-40	Sie	N	SOT23	BC328-40
953	5Gs	BC808-40W	Sie	N	SOT323	BC328-40
954	5H	MMBD701	Mot	C	SOT23	MBD701 UHF schottky diode
955	5H	MMBD4148	Nat	C	SOT23	1N4148
956	5Hp	BC808	Phi	N	SOT23	BC328
957	5HZ	BC808	Zet	N	SOT23	BC328
958	5I	MMSD4148	Mot	C		1N4148
959	5J	FMMT38B	Zet	N		BCX38B
960	5K	MMBV809	Mot	C	SOT23	Hyperabrupt varicap
961	5Kp	BAP64-05	Phi	B		dual cc 3GHz RF pin diode
962	5L	MMBV609	Mot	B	SOT23	dual cc Hyperabrupt varicap
963	5N	MMBD452L	Mot	D	SOT23	series UHF schottky diodes
964	5P	FMMT2907AR	Zet	R	SOT23R	2N2907A
965	5T	BCW66GR	Sie	R	SOT23R	npn 45V 0.8A 350mW
966	5V	BCW65BR	Zet	R	SOT23R	npn 32V 0.8A
967	5V1	PZM5.1NB	Phi	C	SOT346	5.1V 0.3W zener
968	5V6	PZM5.6NB	Phi	C	SOT346	5.6V 0.3W zener
969	5W	BCW67BR	Zet	R	SOT23R	pnp 32V 0.8A
970	5Y1	BZV49-C5V1	Phi	O	SOT89	5.1V 1W zener
971	5Y6	BZV49-C5V6	Phi	O	SOT89	5.6V 1W zener
972	6 (red)	BBY56-03W	Sie	I	SOD323	varicap
973	60s	BAR60	Sie	QQ	SOT143	3 pin diodes
974	61A	MMBF4117	Nat	F		n-ch jfet ultra low i/p Ig
975	61A	MMBF4119	Nat	F		n-ch jfet ultra low i/p Ig
976	61C	MMBF4118	Nat	F		n-ch jfet ultra low i/p Ig
977	61J	MMBF4091	Nat	F		n-ch jfet sw/chopper
978	61K	MMBF4092	Nat	F		n-ch jfet sw/chopper
979	61L	MMBF4093	Nat	F		n-ch jfet sw/chopper
980	61M	MMBF4859	Nat	F		n-ch jfet sw/chopper

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
981	61N	MMBF5514	Nat	F		p-ch jfet sw/chopper
982	61P	MMBF5115	Nat	F		p-ch jfet sw/chopper
983	61Q	MMBF5516	Nat	F		p-ch jfet sw/chopper
984	61s	BAR61	Sie	PQ	SOT143	3 pin diodes pi atten
985	61S	MMBF5458	Nat	F		n-ch jfet gp 2N5458
986	61T	MMBF5459	Nat	F		n-ch jfet gp 2N5459
987	61U	MMBF5461	Nat	F		p-ch jfet gp 2N5461
988	61V	MMBF5462	Nat	F		p-ch jfet gp 2N5462
989	62P	MMBFJ201	Nat	F		n-ch jfet gp J201
990	62Q	MMBFJ202	Nat	F		n-ch jfet gp J202
991	62R	MMBFJ203	Nat	F		n-ch jfet gp J203
992	62S	MMBFJ270	Nat	F		p-ch jfet gp J270
993	62T	MMBFJ271	Nat	F		p-ch jfet gp J271
994	62V	PZM62NB1	Phi	C	SOT346	62V 0.3W zener
995	62Y	BZV49-C62	Phi	O	SOT89	62V 1W zener
996	63Q	MMBFJ304	Nat	F		n-ch jfet vhf J304
997	63s	BAT64	Sie	C	SOT23	Schottky 40V 250mA gp
998	63s	BAT64W	Sie	C	SOT323	Schottky 40V 250mA gp
999	64s	BAT64-04	Sie	D	SOT23	dual ser gp Schottky 40V 250mA
1000	64s	BAT64-04W	Sie	D	SOT323	dual ser gp Schottky 40V 250mA
1001	65s	BAT64-05	Sie	B	SOT23	dual cc gp Schottky 40V 250mA
1002	65s	BAT64-05W	Sie	B	SOT323	dual cc gp Schottky 40V 250mA
1003	66s	BAT64-06	Sie	A	SOT23	dual ca gp Schottky 40V 250mA
1004	66s	BAT64-06W	Sie	A	SOT323	dual ca gp Schottky 40V 250mA
1005	67R	BFP67R	Tfk	WQ		nnp Rf FT 7.5GHz 10V 50mA
1006	67s	BAT64-07	Sie	S	SOT143	dual gp Schottky 40V 250mA
1007	67s	BAT64-07W	Sie	S	SOT343	dual gp Schottky 40V 250mA
1008	68V	PZM68NB1	Phi	C	SOT346	68V 0.3W zener
1009	68Y	BZV49-C68	Phi	O	SOT89	68V 1W zener
1010	6A	MMBF4416	Mot	ZC	SOT23	2N4416 n-ch vhf jfet
1011	6A	MUN2111	Mot	N	SOT23	pnp dtr with 10k+10k
1012	6A	MUN5111	Mot	N	SOT323	pnp dtr with 10k+10k
1013	6A	BC817-16	Phi	N	SOT23	BC337-16
1014	6A-	BC817-16W	Phi	N	SOT323	BC337-16
1015	6A2	PZM6.2NB2A	Phi	A	SOT346	dual ca 6.2V 0.3W zener
1016	6A8	PZM6.8NB2A	Phi	A	SOT346	dual ca 6.8V 0.3W zener
1017	6Ap	BC817-16W	Phi	N	SOT23	BC337-16
1018	6AR	BC817-16R	Phi	R	SOT23	BC337-16
1019	6As	BC817-16	Sie	N	SOT23	BC337-16
1020	6As	BC817-16	Sie	N	SOT323	BC337-16
1021	6At	BC817-16	Phi	N	SOT23	BC337-16
1022	6At	BC817-16W	Phi	N	SOT323	BC337-16
1023	6AZ	BC817-16	Zet	N	SOT23	BC337-16
1024	6B	MMBF5484	Mot	ZC	SOT23	n-ch jfet 2N5484
1025	6B	BC817-25	Phi	N	SOT23	BC337-25
1026	6B	MUN2112	Mot	N	SOT23	pnp dtr 22k+22k
1027	6B	MUN5112	Mot	N	SOT323	MUN2112
1028	6B-	BC817-25W	Phi	N	SOT323	BC337-25
1029	6Bp	BC817-25	Phi	N	SOT23	BC337-25

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1030	6BR	BC817-25R	Phi	R	SOT23R	BC337-25
1031	6Bs	BC817-25	Sie	N	SOT23	BC337-25
1032	6Bs	BC817-25W	Sie	N	SOT323	BC337-25
1033	6Bt	BC817-25	Phi	N	SOT23	BC337-25
1034	6Bt	BC817-25W	Phi	N	SOT323	BC337-25
1035	6BZ	BC817-25	Zet	N	SOT23	BC337-25
1036	6C	BC817-40	Phi	N	SOT23	BC337-40
1037	6C	MMBFU310	Mot	F	SOT23	n-ch jfet U310
1038	6C	MUN2113	Mot	N	SOT23	pn-p dtr 47k+47k
1039	6C	MUN5113	Mot	N	SOT323	MUN2113
1040	6C-	BC817-40W	Phi	N	SOT323	BC337-40
1041	6Cp	BC817-40	Phi	N	SOT23	BC337-40
1042	6CR	BC817-40R	Phi	R	SOT23R	BC337-40
1043	6Cs	BC817-40	Sie	N	SOT23	BC337-40
1044	6Cs	BC817-40W	Sie	N	SOT323	BC337-40
1045	6Ct	BC817-40	Phi	N	SOT23	BC337-40
1046	6Ct	BC817-40W	Phi	N	SOT323	BC337-40
1047	6CZ	BC817-40	Zet	N	SOT23	BC337-40
1048	6D	MMBF5457	Mot	F	SOT23	2N5457 n-ch jfet
1049	6D	MUN2114	Mot	N	SOT23	pn-p dtr 10k+47k
1050	6D	MUN5114	Mot	N	SOT323	MUN2114
1051	6D-	BC817W	Phi	N	SOT323	BC337
1052	6Dp	BC817	Phi	N	SOT23	BC337
1053	6Dt	BC817	Phi	N	SOT23	BC337
1054	6Dt	BC817W	Phi	N	SOT323	BC337
1055	6DZ	BC817	Zet	N	SOT23	BC337
1056	6E	FMPT-A93R	Zet	R	SOT23R	MPSA93
1057	6E	MMBF5460	Mot	F	SOT23	p-ch jfet 2N5460
1058	6E	BC818-16	Phi	N	SOT23	BC338-16
1059	6E	MUN2115	Mot	N	SOT23	pn-p dtr R1 10k
1060	6E	MUN5115	Mot	N	SOT323	MUN2115
1061	6ER	BC818-16R	Phi	R	SOT23	BC338-16
1062	6Es	BC818-16	Sie	N	SOT23	BC338-16
1063	6Es	BC818-16W	Sie	N	SOT323	BC338-16
1064	6EZ	BC818-16	Zet	N	SOT23	BC338-16
1065	6F	MMBF4860	Mot	F	SOT23	2N4860 n-ch jfet
1066	6F	BC818-25	Phi	N	SOT23	BC338-25
1067	6F	MUN2116	Mot	N	SOT23	pn-p dtr R1 4k7
1068	6F	MUN5116	Mot	N	SOT323	MUN2116
1069	6F	Gali-6F	MC	AZ	SOT89	DC-4GHz MMIC amp 12 dB gain
1070	6FR	BC818-25R	Phi	R	SOT23R	BC338-25
1071	6Fs	BC818-25	Sie	N	SOT23	BC338-25
1072	6Fs	BC818-25W	Sie	N	SOT323	BC338-25
1073	6FZ	BC818-25	Zet	N	SOT23	BC338-25
1074	6G	BC818-40	Phi	N	SOT23	BC338-40
1075	6G	MMBF4393	Mot	ZC	SOT23	n-ch jfet 2N4393
1076	6G	MUN2130	Mot	N	SOT23	pn-p dtr 1k0+1k0
1077	6G	MUN5130	Mot	N	SOT323	ial">MUN2130
1078	6GR	BC818-40R	Phi	R	SOT23	BC338-40

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1079	6Gs	BC818-40	Sie	N	SOT23	BC338-40
1080	6Gs	BC818-40W	Sie	N	SOT323	BC338-40
1081	6GZ	BC818-40	Zet	N	SOT23	BC338-40
1082	6H	MMBF5486	Mot	ZC	SOT23	n-ch jfet 2N5486
1083	6H	MUN2131	Mot	N	SOT23	pnv dtr 2k2 +2k2
1084	6H	MUN5131	Mot	N	SOT323	MUN2121
1085	6Hp	BC818	Phi	N	SOT23	BC338
1086	6HZ	BC818	Zet	N	SOT23	BC338
1087	6J	MMBF4391	Mot	F	SOT23	n-ch jfet 2N4391
1088	6J	MUN2132	Mot	N	SOT23	pnv dtr 4k7+ 4k7
1089	6J	MUN5132	Mot	N	SOT323	MUN2132
1090	6K	MMBF4932	Mot	F	SOT23	n-ch jfet 2N4932
1091	6K	MUN2133	Mot	N	SOT23	pnv dtr 4k7+ 47k
1092	6K	MUN5133	Mot	N	SOT323	MUN2133
1093	6L	MMBF5459	Mot	F	SOT23	n-ch jfet 2N5459
1094	6L	MUN2134	Mot	N	SOT23	pnv dtr 22k+47k
1095	6L	MUN5134	Mot	N	SOT323	MUN2134
1096	6M	MMBF5485	Nat	ZC	SOT23	n-ch jfet vhf 2N5485
1097	6N	MMBF4861	Nat	F	SOT23	n-ch jfet sw/chopper
1098	6P	MMBFJ111	Nat	F		J111 n-ch jfet
1099	6P	BCX71HR	Phi	R	SOT23R	BCX79
1100	6P	MMBFJ113	Nat	F		J113 n-ch jfet
1101	6Q	MMBFJ305	Nat	F		n-ch jfet vhf J305
1102	6R	MMBFJ112	Nat	F		J112 n-ch jfet
1103	6S	MMBFJ176	Nat	F		J176 n-ch jfet
1104	6S	MMSD71	Mot	C		gp Si diode
1105	6T	BCW68GR	Sie	R		pnv 45V 0.8A 350mW
1106	6T	MMBFJ310	Mot	F	SOT23	uhf n-ch jfet J310
1107	6U	MMBFJ309	Nat	F	SOT23	uhf n-ch jfet J309
1108	6V	BCW65CR	Zet	R	SOT23R	npn 32V 0.8A
1109	6V	MMBFJ174	Nat	F		J174 p-ch jfet sw/chopper
1110	6V2	PZM6.2NB	Phi	C	SOT346	6.2V 0.3W zener
1111	6V8	PZM6.8NB	Phi	C	SOT346	6.8V 0.3W zener
1112	6W	BCW67CR	Zet	R	SOT23R	pnv32V 0.8A
1113	6W	MMBFJ175	Mot	F	SOT23	J175 p-ch jfet
1114	6X	MMBFJ174	Nat	F		J174 p-ch jfet sw/chopper
1115	6Y	MMBFJ177	Mot	F	SOT23	J177 p-ch jfet
1116	6Y2	BZV49-C6V2	Phi	O	SOT89	6.2V 1W zener
1117	6Y8	BZV49-C6V8	Phi	O	SOT89	6.8V 1W zener
1118	6Z	MMBF170	Mot	M	SOT23	tmosfet n-ch Vds 60V
1119	7 (white)	BBY55-02W	Sie	I	SCD80	UHF Varicap
1120	73-	BAS70W	Phi	C	SOT323	schottky diode 70V 50mA
1121	73p	BAS70	Phi	C	SOT23	schottky diode 70V 50mA
1122	73s	BAS70	Sie	C	SOT23	schottky diode 70V 50mA
1123	73S	BFQ73S	Sie	CX	SOT173	npn fT 5.3GHz 15V 100mA
1124	73t	BAS70	Phi	C	SOT23	schottky diode 70V 50mA
1125	73t	BAS70W	Phi	C	SOT323	schottky diode 70V 50mA
1126	74p	BAS70-04	Phi	D	SOT23	dual series BAS70
1127	74s	BAS70-04	Sie	D	SOT23	dual series BAS70

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1128	74t	BAS70-04	Phi	D	SOT23	dual series BAS70
1129	74t	BAS70-04W	Phi	D	SOT323	dual series BAS70
1130	74t	BAS70-04W	Phi	D	SOT323	dual series BAS70
1131	75-	BAS70-05W	Phi	B	SOT323	dual cc BAS70
1132	75p	BAS70-05	Phi	B	SOT23	dual cc BAS70
1133	75s	BAS70-05	Sie	B	SOT23	dual cc BAS70
1134	75s	BAS70-05W	Sie	B	SOT323	dual cc BAS70
1135	75t	BAS70-05W	Phi	B	SOT323	dual cc BAS70
1136	75t	BAS70-05	Phi	B	SOT23	dual cc BAS70
1137	75Y	BZV49-C75	Phi	O	SOT89	75V 1W zener
1138	76-	BAS70-06W	Phi	A	SOT323	dual ca BAS70
1139	76p	BAS70-06	Phi	A	SOT23	dual ca BAS70
1140	76s	BAS70-06	Sie	A	SOT23	dual ca BAS70
1141	76t	BAS70-06	Phi	A	SOT23	dual ca BAS70
1142	76t	BAS70-06W	Phi	A	SOT323	dual ca BAS70
1143	77s	BAS70-07	Sie	S	SOT143	dual BAS70
1144	77s	BAS70-07	Sie	S	SOT343	dual BAS70
1145	7A	MMBR901	Mot	N	SOT23	npn RF MRF901
1146	7A	MUN5211DW1	Mot	DN	SOT363	dual npn dtr 10k+10k
1147	7A5	PZM7.5NB2A	Phi	A	SOT346	dual ca 7.5V 0.3W zener
1148	7B	MMBR920	Mot	N	SOT23	npn RF ?MRF920
1149	7B	MUN5212DW1	Mot	DN	SOT363	dual npn dtr 22k+22k
1150	7C	MMBR930	Mot	N	SOT23	npn RF ?MRF930
1151	7C	MUN5213DW1	Mot	DN	SOT363	dual npn dtr 47k+47k
1152	7D	MMBR931	Mot	N	SOT23	npn RF ?MRF931
1153	7D	HD4A	Zet	A		ca dual HD3A
1154	7D	MUN5214DW1	Mot	DN	SOT363	dual npn dtr 10k+47k
1155	7E	FMMT-A42R	Zet	R		MPSA42
1156	7E	MMBR2060	Mot	N		npn RF FT 1GHz Vce 30V 50mA
1157	7E	MUN5215DW1	Mot	DN	SOT363	dual npn 10k base res
1158	7F	MMBR4957	Mot	N		npn RF FT 1.2GHz 30V 30mA
1159	7F	MUN5211DW1	Mot	DN	SOT363	dual npn dtr R1 4k7
1160	7G	MMBR5031	Mot	N	SOT23	npn RF FT 1GHz 10V 20mA
1161	7G	MUN5230DW1	Mot	DN	SOT363	dual npn dtr 1k0+1k0
1162	7H	MMBR5179	Mot	N	SOT23	npn RF 2N5179/BFY90
1163	7H	MUN5231DW1	Mot	DN	SOT363	dual npn dtr 2k2+2k2
1164	7J	FMMT38C	Zet	N	SOT23	BCX38C
1165	7J	MUN5232DW1	Mot	DN	SOT363	dual npn dtr 4k7+4k7
1166	7K	MMBR2857	Mot	N		npn RF FT 1GHz Vce 15V 40mA
1167	7K	MUN5233DW1	Mot	DN	SOT363	dual npn dtr 4k7+47k bias
1168	7L	MUN5234DW1	Mot	DN	SOT3636	dual npn dtr 22k+47k bias
1169	7M	MUN5235DW1	Mot	DN	SOT363	dual npn dtr 2k2+47k bias
1170	7M	MMBR521L	Mot	N	SOT23	pnp RF MRF521
1171	7M	BCW66HR	Zet	R	SOT23R	npn 45V 0.8A
1172	7N	MMBR941BL	Mot	N	SOT23	npn RF FT 8GHz MRF941
1173	7N	BCW68HR	Zet	R	SOT23	pnp 45V 0.8A
1174	7P	BCW66FR	SGS	R	SOT23R	npn 45V 0.8A 350mW
1175	7P	MMBR911L	Mot	N	SOT23	npn RF FT 6GHz MRF911
1176	7R	MMBR536	Mot	N		npn RF MRF536

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1177	7T	BCW68FR	Zet	R	SOT23R	pnp 45V 0.8A
1178	7V5	PZM7.5NB	Phi	C	SOT346	7.5V 0.3W zener
1179	7X	MMBR571L	Mot	N	SOT23	nnp RF ft 8GHz MRF571
1180	7Y	MMBR941L	Mot	N	SOT23	nnp RF ft 8GHz MRF941
1181	7Y5	BZV49-C7V5	Phi	O	SOT89	7.5V 1W zener
1182	7Z	MMBR951L	Mot	N	SOT23	nnp RF ft7.5GHz MRF951
1183	8 (yellow)	BBY58-03W	Sie	I	SOD323	varicap
1184	81A	MMBZ5250B	Mot	C	SOT23	20V zener 0.225W
1185	81A	PMBZ5250B	Phi	C	SOT23	20V zener 0.225W
1186	81B	MMBZ5251B	Mot	C	SOT23	22V zener 0.225W
1187	81B	PMBZ5251B	Phi	C	SOT23	22V zener 0.225W
1188	81C	MMBZ5252B	Mot	C	SOT23	24V zener 0.225W
1189	81C	PMBZ5252B	Phi	C	SOT23	24V zener 0.225W
1190	81D	MMBZ5253B	Mot	C	SOT23	25V zener 0.225W
1191	81D	PMBZ5253B	Phi	C	SOT23	25V zener 0.225W
1192	81E	MMBZ5254B	Mot	C	SOT23	27V zener 0.225W
1193	81E	PMBZ5254B	Mot	C	SOT23	27V zener 0.225W
1194	81F	MMBZ5255B	Mot	C	SOT23	28V zener 0.225W
1195	81F	PMBZ5255B	Sie	C	SOT23	28V zener 0.225W
1196	81G	MMBZ5256B	Mot	C	SOT23	30V zener 0.225W
1197	81G	PMBZ5256B	Phi	C	SOT23	30V zener 0.225W
1198	81H	MMBZ5257B	Mot	C	SOT23	33V zener 0.225W
1199	81H	PMBZ5257B	Phi	C	SOT23	33V zener 0.225W
1200	82P	BFP182T	Tfk	X		nnp RF ft 7.5GHz 10V 35mA
1201	83P	BFP183T	Tfk	X		nnp RF ft 7.4GHz 10V 65mA
1202	83s	BAT68	Sie	C	SOT23	gp Schottky 8V 130mA
1203	83s	BAT68W	Sie	C	SOT323	gp Schottky 8V 130mA
1204	84s	BAT68-04	Sie	D	SOT23	dual ser gp Schottky 8V 130mA
1205	84s	BAT68-04W	Sie	D	SOT323	dual ser gp Schottky 8V 130mA
1206	85s	BAT68-05	Sie	B	SOT23	gp dual cc Schottky 8V 130mA
1207	85s	BAT68-05W	Sie	B	SOT323	gp dual cc Schottky 8V 130mA
1208	86s	BAT68-06	Sie	A	SOT23	gp dual ca Schottky 8V 130mA
1209	86s	BAT68-06W	Sie	A	SOT323	gp dual ca Schottky 8V 130mA
1210	87s	BAT68-07	Sie	S	SOT143	gp dual schottky 8V 130mA
1211	8A	NJM78L02A	NJR	KQ	SOT89	78L 2.0V 0.1A regulator
1212	8A	2DA1774Q	Dio	N	SOT523	gp pnp 60V 150mA hfe 120-270
1213	8A	MMBZ5226B	Mot	C	SOT23	3.3V zener 0.225W
1214	8A	MUN2211	Mot	N	SOT23	nnp dtr 10k +10k
1215	8A	MUN5211	Mot	N	SOT323	nnp dtr 10k +10k
1216	8A2	PZM8.2NB2A	Phi	C	SOT23	dual ca 8.2V 0.3W zener
1217	8B	NJM78L03A	NJR	KQ	SOT89	78L 3.0V 0.1A regulator
1218	8B	2DA1774Q	Dio	N	SOT523	gp pnp 60V 150mA hfe 180-390
1219	8B	MMBZ5227B	Mot	C	SOT23	3.6V zener 0.225W
1220	8B	MUN2212	Mot	N	SOT23	nnp dtr 22k+22k
1221	8B	MUN5212	Mot	N	SOT323	nnp dtr 22k+22k
1222	8C	NJM78L05A	NJR	KQ	SOT89	78L 5.0V 0.1A regulator
1223	8C	2DA1774S	Dio	N	SOT523	gp pnp 60V 150mA hfe 270-560
1224	8C	MMBZ5228B	Mot	C	SOT23	3.9V zener 0.225W
1225	8C	MUN2213	Mot	N	SOT23	nnp dtr 47k + 47k

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1226	8C	MUN5213	Mot	N	SOT323	nnp dtr 47k + 47k
1227	8D	2DC4617Q	Dio	N	SOT523	gp npn 60V 150mA hfe 120-270
1228	8D	MUN2214	Mot	N	SOT23	nnp dtr 10k + 47k
1229	8D	MUN5214	Mot	N	SOT323	MUN2214
1230	8E	NJM78L06A	NJR	KQ	SOT89	78L 6.0V 0.1A regulator
1231	8E	2DC4617R	Dio	N	SOT523	gp npn 60V 150mA hfe 180-390
1232	8E	FMMT-A92R	Zet	R	SOT23R	MPSA92
1233	8E	MMBZ5230B	Mot	C	SOT23	4.7V zener 0.225W
1234	8E	MUN2215	Mot	N	SOT23	nnp dtr R1 10k
1235	8E	MUN5215	Mot	N	SOT323	nnp dtr R1 10k
1236	8F	NJM78L07A	NJR	KQ	SOT89	78L 7.0V 0.1A regulator
1237	8F	2DC4617S	Dio	N	SOT523	gp npn 60V 150mA hfe 270-560
1238	8F	MMBZ5231B	Mot	C	SOT23	5.1V zener 0.225W
1239	8F	MUN2216	Mot	N	SOT23	nnp dtr R1 4k7
1240	8F	MUN5216	Mot	N	SOT323	MUN2216
1241	8G	NJM78L08A	NJR	KQ	SOT89	78L 8.0V 0.1A regulator
1242	8G	MMBZ5232B	Mot	C	SOT23	5.6V zener 0.225W
1243	8G	MUN2230	Mot	N	SOT23	nnp dtr 1k0+1k0
1244	8G	MUN5230	Mot	N	SOT323	nnp dtr 1k0+1k0
1245	8H	NJM78L09A	NJR	KQ	SOT89	78L 9.0V 0.1A regulator
1246	8H	MMBZ5233B	Mot	C	SOT23	6.0V zener 0.225W
1247	8H	MUN2231	Mot	N	SOT23	nnp dtr 2k2+2k2
1248	8H	MUN5231	Mot	N	SOT323	nnp dtr 2k2+2k2
1249	8J	NJM78L10A	NJR	KQ	SOT89	78L 10V 0.1A regulator
1250	8J	MMBZ5234B	Mot	C	SOT23	6.2V zener 0.225W
1251	8J	MUN2232	Mot	N	SOT23	nnp dtr 4k7+ 4k7
1252	8J	MUN5232	Mot	N	SOT323	nnp dtr 4k7+ 4k7
1253	8K	NJM78L12A	NJR	KQ	SOT89	78L 12V 0.1A regulator
1254	8K	MMBZ5235B	Mot	C	SOT23	6.8V zener 0.225W
1255	8K	MUN2233	Mot	N	SOT23	nnp dtr 4k7+ 47k
1256	8K	MUN5233	Mot	N	SOT323	nnp dtr 4k7+ 47k
1257	8L	NJM78L15A	NJR	KQ	SOT89	78L 15V 0.1A regulator
1258	8L	MMBZ5236B	Mot	C	SOT23	7.5V zener 0.225W
1259	8L	MUN2234	Mot	N	SOT23	nnp dtr 22k + 47k
1260	8L	MUN5234	Mot	N	SOT323	nnp dtr 22k + 47k
1261	8M	NJM78L18A	NJR	KQ	SOT89	78L 18V 0.1A regulator
1262	8M	MMBZ5237B	Mot	C	SOT23	8.2V zener 0.225W
1263	8N	NJM78L20A	NJR	KQ	SOT89	78L 20V 0.1A regulator
1264	8N	MMBZ5238B	Mot	C	SOT23	8.7V zener 0.225W
1265	8P	NJM78L24A	NJR	KQ	SOT89	78L 24V 0.1A regulator
1266	8P	MMBZ5239B	Mot	C	SOT23	9.1V zener 0.225W
1267	8Q	MMBZ5240B	Mot	C	SOT23	10V zener 0.225W
1268	8R	MMBZ5241B	Mot	C	SOT23	11V zener 0.225W
1269	8S	MMBZ5242B	Mot	C	SOT23	12V zener 0.225W
1270	8T	MMBZ5243B	Mot	C	SOT23	13V zener 0.225W
1271	8U	MMBZ5244B	Mot	C	SOT23	14V zener 0.225W
1272	8V	MMBZ5245B	Mot	C	SOT23	15V zener 0.225W
1273	8V2	PZM8.2NB	Phi	C	SOT23	8.2V 0.3W zener
1274	8W	MMBZ5246B	Mot	C	SOT23	16V zener 0.225W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1275	8X	MMBZ5247B	Mot	C	SOT23	17V zener 0.225W
1276	8Y	MMBZ5248B	Mot	C	SOT23	18V zener 0.225W
1277	8Y2	BZV49-C8V2	Phi	O	SOT89	8.2V 1W zener
1278	8Z	NJM78L62A	NJR	KQ	SOT89	78L 6.2V 0.1A regulator
1279	8Z	MMBZ5249B	Mot	C	SOT23	19V zener 0.225W
1280	91A	FMMT591A	Zet	N	SOT23	pnp 40V 1A 0.5W FT 150 MHz
1281	92V	BFP92A	Tfk	W		nnp RF 6GHz 16V 30mA
1282	9A	FMMT2369AR	Zet	R	SOT23	2N2369A
1283	9A	DTA125TUA	Roh	N	SC70	pnp dtr R1 200k 50V 100mA
1284	9A	DTA125TKA	Roh	N	SC59	pnp dtr R1 200k 50V 100mA
1285	9A	PLVA650A	Phi	C	SOT23	5.0V avalanche reg diode
1286	9A1	PZM9.1NB2A	Phi	A	SOT346	dual ca 9.1V 0.3W zener
1287	9B	NJM79L03UA	NJR	KQR	SOT89	79L reg 3.0V 0.1A
1288	9B	PLVA653A	Phi	C	SOT23	5.3V avalanche reg diode
1289	9C	NJM79L05UA	NJR	KQR	SOT89	79L reg 5.0V 0.1A
1290	9C	PLVA656A	Phi	C	SOT23	5.6V avalanche reg diode
1291	9D	PLVA659A	Phi	C	SOT23	5.9V avalanche reg diode
1292	9E	NJM79L06UA	NJR	KQR	SOT89	79L reg 6.0V 0.1A
1293	9E	PLVA662A	Phi	C	SOT23	6.2V avalanche reg diode
1294	9F	PLVA665A	Phi	C	SOT23	6.5V avalanche reg diode
1295	9G	NJM79L08UA	NJR	KQR	SOT89	79L reg 8.0V 0.1A
1296	9G	PLVA668A	Phi	C	SOT23	6.8V avalanche reg diode
1297	9H	NJM79L09UA	NJR	KQR	SOT89	79L reg 9.0V 0.1A
1298	9J	PLVA2650A	Phi	A	SOT23	dual ca 5.0V reg diode
1299	9K	NJM79L12UA	NJR	KQR	SOT89	79L reg 12V 0.1A
1300	9K	PLVA2653A	Phi	A	SOT23	dual ca 5.3V reg diode
1301	9L	NJM79L15UA	NJR	KQR	SOT89	79L reg 15V 0.1A
1302	9L	PLVA2656A	Phi	A	SOT23	dual 5.60V reg diode
1303	9M	NJM79L18UA	NJR	KQR	SOT89	79L reg 18V 0.1A
1304	9M	PLVA2659A	Phi	A	SOT23	dual ca 5.9V reg diode
1305	9N	PLVA2662A	Phi	A	SOT23	dual ca 6.2V reg diode
1306	9O	PLVA2665A	Phi	A	SOT23	dual ca 6.5V reg diode
1307	9P	NJM79L24UA	NJR	KQR	SOT89	79L reg 24V 0.1A
1308	9P	BCX70HR	Zet	R	SOT23	BCX70H
1309	9P	PLVA2668A	Phi	A	SOT23	dual ca 6.8V reg diode
1310	9R	FMMT2369R	Zet	R	SOT23	2N2369
1311	9V1	PZM9.1NB	Phi	C	SOT346	9.1V 0.3W zener
1312	9Y1	BZV49-C9V1	Phi	O	SOT89	9.1V 1W zener
1313	A	BA892	Sie	I	SCD80	35V 100mA pin
1314	A	1SS355	Roh	I	USM	100V 50mA sw
1315	A	MRF947	Mot	N	SOT323	nnp RF 8 GHz
1316	A0	HSMS-2800	HP	C	SOT23	HP2800 schottky
1317	A0	HSMS-280B	HP	C	SOT323	HP2800 schottky
1318	A03	VAM-03	MC	AQ		modamp MAR 3 Similar
1319	A06	VAM-06	MC	AQ		modamp MAR 6 Similar
1320	A07	VAM-07	MC	AQ		modamp MAR 7 Similar
1321	A1	HSMS-2801	HP	K		HP2800 schottky
1322	A1	BAW56W	Phi	A	SOT323	dual ca BAW62 (1N4148)
1323	A1	BAW56	Phi	A	SOT23	dual ca BAW62 (1N4148)

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1324	A1	BAW56	Phi	A	SOT23	dual ca BAW62 (1N4148)
1325	A11	MMBD1501A	Fch	C	SOT23	180V 200mA diode
1326	A13	MMBD1503A	Fch	D	SOT23	180V 200mA dual diode series
1327	A14	MMBD1504A	Fch	B	SOT23	180V 200mA dual diode cc
1328	A15	MMBD1505A	Fch	A	SOT23	180V 200mA dual diode ca
1329	A16	ZC934A	Zet	C	SOT23	25-95pF hyperabrupt varicap
1330	A17	ZC933A	Zet	C	SOT23	12-42pF hyperabrupt varicap
1331	A1p	BAW56	Phi	A	SOT23	dual ca BAW62 (1N4148)
1332	A1s	BAW56W	Sie	A	SOT323	dual ca BAW62 (1N4148)
1333	A1s	BAW56	Sie	A	SOT23	dual ca BAW62 (1N4148)
1334	A1s	BAW56U	Sie	A	SC74	dual ca BAW62 (1N4148)
1335	A1t	BAW56T	Phi	A	SOT416	dual ca BAW62 (1N4148)
1336	A1t	BAW56S	Phi		SOT363	dual ca BAW62 (1N4148)
1337	A1X	MBAW56	Mot	A		ditto
1338	A2	HSMS-2802	HP	D	SOT23	dual HP2800
1339	A2	HSMS-280C	HP	D	SOT323	dual HP2800
1340	A2	BAT18	Phi	C	SOT23	BA482
1341	A2	MMBD2836	Mot	A	SOT23	dual ca sw diode 75V
1342	A2	CFY30	Sie	CQ	SOT143	n-ch GaAsfet 6 GHz
1343	A2	MBT3906DW1	Mot	DO	SOT363	dual 2N3906
1344	A22	BAS21	Phi	C	SOD27	BAV21
1345	A2s	BAT18	Sie	C	SOT23	BA482
1346	A2X	MMBD2836	Mot	A	SOT23	dual ca sw 75V 100mA 15ns
1347	A3	BAP64-03	Phi	I	SOD323	3 GHz pin diode
1348	A3	HSMS-2803	HP	D	SOT23	HP2800 ser pair
1349	A3	MMBD1005	Mot	A	SOT23	dual ca Si diode low leakage
1350	A3	BAS16	Zet	C		Si sw 75V 100mA
1351	A3	BAT17	Phi	C	SOT23	BA481
1352	A3	MBT3906DW	Mot	N	SOT363	dual 2N3906
1353	A3p	BAT17	Phi	C	SOT23	BA481
1354	A3t	BAT17	Phi	C	SOT23	BA481
1355	A3X	MMBD2835	Mot	A	SOT23	dual ca sw 35V 100mA 15nS
1356	A4	HSMS-2804	HP	B	SOT23	dual cc HP2800 schottky
1357	A4	BAV70W	Phi	B	SOT323	dual cc BAW62
1358	A4p	BAV70	Phi	B	SOT23	dual cc BAW62
1359	A4s	BAV70W	Sie	B	SOT323	dual cc BAW62
1360	A4s	BAV70	Sie	B	SOT23	dual cc BAW62
1361	A4s	BAV70T	Sie	B	SOT416	dual cc BAW62
1362	A4s	BAV70U	Sie	B	SC74	dual cc BAW62
1363	A4t	BAV70	Phi	B	SOT23	dual cc BAW62
1364	A4t	BAV70	Phi	B	SOT363	dual cc BAW62
1365	A4X	MBAV70	Mot	B		ditto
1366	A5	BAP51-03	Phi	I	SOD323	GP RF pin diode
1367	A5	HSMS-2805	HP	S	SOT143	dual HP2800 schottky
1368	A5	MMBD1010	Mot	B	SOT23	dual cc Si diodes
1369	A5	MMBD2837	Mot	B	SOT23	dual cc diodes 30V 150mA
1370	A51	BRY62	Phi		SOT143	
1371	A5p	BRY61	Phi		SOT143	
1372	A5t	BRY61	Phi		SOT143	

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1373	A6	BAS16W	Phi	C	SOT323	BAW62 (1N4148)
1374	A6	BAS16T	Phi	C	SOT416	BAW62 (1N4148)
1375	A6	BAS216	Phi	I	SOD110	BAW62 (1N4148)
1376	A6	MMBD2836	Mot	B	SOT23	dual sw diode cc 75V
1377	A6A	MMUN2111	Mot	N	SOT23	pnv dtr 10k+10k
1378	A6B	MMUN2112	Mot	N	SOT23	pnv dtr 22k+22k
1379	A6C	MMUN2113	Mot	N	SOT23	pnv dtr 47k+47k
1380	A6D	MMUN2114	Mot	N	SOT23	pnv dtr 100k+100k
1381	A6E	MMUN2115	Mot	N	SOT23	pnv dtr R1 10k
1382	A6F	MMUN2116	Mot	N	SOT23	pnv dtr R1 4k7
1383	A6G	MMUN2130	Mot	N	SOT23	pnv dtr 1k0+1k0
1384	A6H	MMUN2131	Mot	N	SOT23	pnv dtr 2k2+2k2
1385	A6J	MMUN2132	Mot	N	SOT23	pnv dtr 4k7+4k7
1386	A6K	MMUN2133	Mot	N	SOT23	pnv dtr 4k7+47k
1387	A6L	MMUN2134	Mot	N	SOT23	pnv dtr 22k+47k
1388	A6p	BAS16	Phi	C	SOT23	BAW62 (1N4148)
1389	A6p	BAS316	Phi	I	SOD323	BAW62 (1N4148)
1390	A6s	BAS16W	Sie	C	SOT323	BAW62 (1N4148)
1391	A6s	BAS16	Sie	C	SOT23	BAW62 (1N4148)
1392	A6s	BAS16U	Sie	C	SC74	BAW62 (1N4148)
1393	A6t	BAS16	Phi	C	SOT23	BAW62 (1N4148)
1394	A6X	MMBD2838	Mot	B	SOT23	dual sw 50V 100mA
1395	A7	BAV99W	Phi	D	SOT323	dual ser BAW92
1396	A7	BAV99	Phi	D	SOT23	dual ser BAW92
1397	A7	HSMS-2807	HP	RQ	SOT143	HP2800 ring quad
1398	A7s	BAV99	Sie	D	SOT23	dual ser BAW92
1399	A7s	BAV99W	Sie	D	SOT323	dual ser BAW92
1400	A7s	BAV99T	Sie	D	SC75	dual ser BAW92
1401	A7s	BAV99U	Sie	D	SC74	dual ser BAW92
1402	A8	HSMS-2808	HP	BQ	SOT143	HP2800 bridge quad
1403	A8	BAP50-03	Phi	I	SOD323	GP RF pin diode
1404	A8	BAS19	Phi	C	SOT23	BAV19
1405	A8	SI2308DS	Sil	M	SOT23	N-ch mosfet, 60V 0.1A
1406	A81	BAS20	Phi	C	SOT23	BAV20
1407	A82	BAS21	Phi	C	SOT23	BAV21
1408	A8A	MMUN2211	Mot	N	SOT23	npv dtr 10k +10k
1409	A8B	MMUN2212	Mot	N	SOT23	npv dtr 22k +22k
1410	A8C	MMUN2213	Mot	N	SOT23	npv dtr 47k+47k
1411	A8D	MMUN2214	Mot	N	SOT23	npv dtr 100k+100k
1412	A8E	MMUN2215	Mot	N	SOT23	npv dtr R1 10k
1413	A8F	MMUN2216	Mot	N	SOT23	npv dtr R1 4k7
1414	A8G	MMUN2230	Mot	N	SOT23	npv dtr 1k0 +1k0
1415	A8H	MMUN2231	Mot	N	SOT23	npv dtr 2k2+2k2
1416	A8J	MMUN2232	Mot	N	SOT23	npv dtr 4k7+4k7
1417	A8K	MMUN2233	Mot	N	SOT23	npv dtr 4k7+47k
1418	A8L	MMUN2234	Mot	N	SOT23	npv dtr 22k+47k
1419	A9	SI2309DS	Sil	M	SOT23	P-ch mosfet, 60V 0.1A
1420	A91	BAS17	Phi	C	SOT23	BA314
1421	AA	BCX51	Sie	P	SOT89	pnv 45V audio comp BCX54

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1422	AA	BCW60A	TT	N	SOT23	BCY58-vii
1423	AA	ZMV829A	Zet	I	SOD323	varicap hyperabrupt 28V 8.2pF@2V
1424	AAA	MMBF4856	Mot	F	SOT23	2N4856 n-ch chopper jfet
1425	AAG	MMBR951AL	Mot	N	SOT23	nnp RF 8GHz
1426	AAH	MAX6326_R22-T	Max	ZB	SC70	microproc -ve reset gen 2.200V
1427	AAI	MAX6327_R22-T	Max	ZB	SC70	microproc +ve reset gen 2.200V
1428	AAJ	MAX6328_R22-T	Max	ZB	SC70	microproc -ve reset gen 2.200V
1429	AAN	MAX809LXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
1430	AAO	MAX809MXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
1431	AAP	MAX809TXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
1432	AAQ	MAX809SXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
1433	AAR	MAX809RXR	Max	ZB	SC70	microproc -ve reset gen 3.0V
1434	AAs	BCW60A	Sie	N	SOT23	BCY58-vii
1435	AAS	MAX803ZXR	Max	ZB	SC70	microproc -ve reset gen 2.5V
1436	AAT	MAX810LXR	Max	ZB	SC70	microproc +ve reset gen 5.0V
1437	AAU	MAX810MXR	Max	ZB	SC70	microproc +-ve reset gen 5.0V
1438	AAV	MAX810TXR	Max	ZB	SC70	microproc +ve reset gen 3.3V
1439	AAW	MAX810RXR	Max	ZB	SC70	microproc +ve reset gen 3.0V
1440	AAX	MAX810SXR	Max	ZB	SC70	microproc +ve reset gen 3.3V
1441	AAY	MAX810ZXR	Max	ZB	SC70	microproc +ve reset gen 2.5V
1442	AAZ	MAX803LXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
1443	AB	BCW60B	ITT	N	SOT23	BCY58-viii
1444	AB	ZMV830A	Zet	I	SOD323	varicap hyperabrupt 28V 10pF@2V
1445	ABA	MAX803TXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
1446	ABB	MAX803MXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
1447	ABC	MAX803SXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
1448	ABD	MAX803RXR	Max	ZB	SC70	microproc -ve reset gen 3.0V
1449	ABE	MAX803ZXR	Max	ZB	SC70	microproc -ve reset gen 2.5V
1450	ABF	LM4041AIX3-1.2	Max	L	SC70	1.225V 0.1% shunt V ref
1451	ABG	LM4041BIX3-1.2	Max	L	SC70	1.225V 0.2% shunt V ref
1452	ABH	LM4041DIX3-1.2	Max	L	SC70	1.225V 0.5% shunt V ref
1453	ABI	LM4041DIX3-1.2	Max	L	SC70	1.225V 1.5% shunt V ref
1454	ABJ	LM4040AIX3-2.1	Max	L	SC70	2.048V 0.1% shunt V ref
1455	ABK	LM4040BIX3-2.1	Max	L	SC70	2.048V 0.2% shunt V ref
1456	ABL	LM4040CIX3-2.1	Max	L	SC70	2.048V 0.5% shunt V ref
1457	ABM	LM4040DIX3-2.1	Max	L	SC70	2.048V 1% shunt V ref
1458	ABN	LM4040AIX3-2.5	Max	L	SC70	2.5001% shunt V ref
1459	ABO	LM4040BIX3-2.5	Max	L	SC70	2.500V 0.2% shunt V ref
1460	ABp	BCW60B	Phi	N	SOT23	BCY58-viii
1461	ABP	LM4040CIX3-2.5	Max	L	SC70	2.500V 0.5% shunt V ref
1462	ABQ	LM4040DIX3-2.5	Max	L	SC70	2.500V 1% shunt V ref
1463	ABR	LM4040AIX3-3.0	Max	L	SC70	3.000V 0.1% shunt V ref
1464	ABs	BCW60B	Sie	N	SOT23	BCY58-viii
1465	ABS	LM4040BIX3-3.0	Max	L	SC70	3.000V 0.2% shunt V ref
1466	ABt	BCW60B	Phi	N	SOT23	BCY58-viii
1467	ABT	LM4040CIX3-3.0	Max	L	SC70	3.000V 0.5% shunt V ref
1468	ABU	LM4040DIX3-3.0	Max	L	SC70	3.000V 1% shunt V ref
1469	ABV	LM4040AIX3-4.1	Max	L	SC70	4.096V 0.1% shunt V ref
1470	ABW	LM4040BIX3-4.1	Max	L	SC70	4.096V 0.2% shunt V ref

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1471	ABX	LM4040CIX3-4.1	Max	L	SC70	4.096V 0.5% shunt V ref
1472	ABY	LM4040DIX3-4.1	Max	L	SC70	4.096V 1% shunt V ref
1473	ABZ	LM4040AIX3-5.0	Max	L	SC70	5.000V 0.1% shunt V ref
1474	AC	BCX51-100	Sie	P	SOT89	45V pnp audio hfe 100
1475	AC	BCX51-10	Phi	P	SOT89	45V pnp audio hfe 100
1476	AC	BCW60C	Phi	N	SOT23	BCY58-ix
1477	AC	ZMV831A	Zet	I	SOD323	varicap hyperabrupt 28V 15pF@2V
1478	ACA	LM4040BIX3-5.0	Max	L	SC70	5.000V 0.2% shunt V ref
1479	ACB	LM4040CIX3-5.0	Max	L	SC70	5.000V 0.5% shunt V ref
1480	ACC	LM4040DIX3-5.0	Max	L	SC70	5.000V 1% shunt V ref
1481	ACE	MAX6326_R31-T	Max	ZB	SC70	microproc -ve reset gen 3.080V
1482	ACF	MAX6347_R46-T	Max	ZB	SC70	microproc +ve reset gen 4.630V
1483	ACH	MAX6326_R23-T	Max	ZB	SC70	microproc -ve reset gen 2.320V
1484	ACI	MAX6326_R26-T	Max	ZB	SC70	microproc -ve reset gen 2.630V
1485	ACJ	MAX6328_R26-T	Max	ZB	SC70	microproc -ve reset gen 2.630V
1486	ACK	MAX6346_R44-T	Max	ZB	SC70	microproc -ve reset gen 4.380V
1487	ACL	MAX6347_R44-T	Max	ZB	SC70	microproc +ve reset gen 4.380V
1488	ACM	MAX6348_R46-T	Max	ZB	SC70	microproc -ve reset gen 4.630V
1489	ACN	MAX6348_R44-T	Max	ZB	SC70	microproc -ve reset gen 4.380V
1490	ACO	MAX6346_R46-T	Max	ZB	SC70	microproc -ve reset gen 4.630V
1491	ACp	BCW60C	Phi	N	SOT23	BCY58-ix
1492	ACP	MAX6326_R29-T	Max	ZB	SC70	microproc -ve reset gen 2.930V
1493	ACQ	MAX6327_R23-T	Max	ZB	SC70	microproc +ve reset gen 2.320V
1494	ACR	MAX6327_R26-T	Max	ZB	SC70	microproc +ve reset gen 2.630V
1495	ACs	BCW60C	Sie	N	SOT23	BCY58-ix
1496	ACS	MAX6327_R29-T	Max	ZB	SC70	microproc +ve reset gen 2.930V
1497	ACt	BCW60C	Phi	N	SOT23	BCY58-ix
1498	ACT	MAX6327_R31-T	Max	ZB	SC70	microproc +ve reset gen 3.080V
1499	ACU	MAX6328_R23-T	Max	ZB	SC70	microproc -ve reset gen 2.320V
1500	ACV	MAX6328_R29-T	Max	ZB	SC70	microproc -ve reset gen 2.930V
1501	ACW	MAX6326_R31-T	Max	ZB	SC70	microproc -ve reset gen 3.080V
1502	AD	BCX51-160	Sie	P	SOT89	45V pnp audio hfe 160
1503	AD	BCX51-16	Phi	P	SOT89	45V pnp audio hfe 160
1504	AD	BCW60D	Phi	N	SOT23	BCY58-x
1505	AD	ZMV832A	Zet	I	SOD323	varicap hyperabrupt 28V 22pF@2V
1506	ADN	2SC3838K	Roh	N		nnp 11V 3.2GHz TV tuners
1507	ADp	BCW60D	Phi	N	SOT23	BCY58-x
1508	ADs	BCW60D	Sie	N	SOT23	BCY58-x
1509	ADt	BCW60D	Ph	N	SOT23	BCY58-x
1510	AE	BCX52	Sie	P	SOT89	pnp 60V audio comp BCX55
1511	AE	ZMV833A	Zet	I	SOD323	varicap hyperabrupt 28V 33pF@2V
1512	AEN	2SC3839K	Roh	N		nnp 20V 2.0GHz TV tuners
1513	AF	ZMV834A	Zet	I	SOD323	varicap hyperabrupt 28V 47pF@2V
1514	AFs	BCW60FF	Sie	N	SOT23	BCY58
1515	AG	ZMV835A	Zet	I	SOD323	varicap hyperabrupt 28V 68pF@2V
1516	AG	BCX70G	Phi	N	SOT23	BCY59-vii BC107
1517	AG	BCX52-10	Sie	P	SOT89	60V pnp BCX52 hfe 100
1518	AGp	BCX70G	Phi	N	SOT23	BCY59-vii BC107
1519	AGs	BCX70G	Sie	N	SOT23	BCY59-vii BC107

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1520	AGt	BCX70G	Phi	N	SOT23	BCY59-vii BC107
1521	AH	BCX70H	Phi	N	SOT23	BCY59-viii BC107B
1522	AH	BCP53	Mot	P	SOT223	pnp amp 80V 150mA
1523	AH	BCX53	Sie	P	SOT89	pnp 80V audio comp BCX56
1524	AH	ZMV930	Zet	I	SOD323	2.9-8.3pF hyperabrupt varicap
1525	AHp	BCX70H	Phi	N	SOT23	BCY59-viii BC107B
1526	AHs	BCX70H	Sie	N	SOT23	BCY59-viii BC107B
1527	AHt	BCX70H	Phi	N	SOT23	BCY59-viii BC107B
1528	AJ	BCX70J	Phi	N	SOT23	BCY59-ix BC107
1529	AJ	ZMV931	Zet	I	SOD323	4 -13.5pF hyperabrupt varicap
1530	AJ s	BCX70J	Sie	N	SOT23	BCY59-ix BC107
1531	AJp	BCX70J	Phi	N	SOT23	BCY59-ix BC107
1532	AJt	BCX70J	Phi	N	SOT23	BCY59-ix BC107
1533	AK	BCX70K	Phi	N	SOT23	BCY59-x BC107
1534	AK	ZMV932	Zet	I	SOD323	5.5-17pF hyperabrupt varicap
1535	AK	BCX53-10	Sie	P	SOT89	pnp 80V BCX53 hfe 100
1536	AKp	BCX70K	Phi	N	SOT23	BCY59-x BC107
1537	AKp	BCX70K	Phi	N	SOT23	BCY59-x BC107
1538	AKs	BCX70K	Sie	N	SOT23	BCY59-x BC107
1539	AL	BCX53-16	Sie	P	SOT89	80V pnp BCX53 hfe 100
1540	AL	MMBTA55L	Mot	N	SOT23	pnp 25V (MPSA55)
1541	AL	ZMV933	Zet	I	SOD323	12-42pF hyperabrupt varicap
1542	ALs	BFP405	Sie	MQ	SOT343	
1543	AM	MMBT3904W	Mot	N	SOT323	2N3904
1544	AM	BCX52-16	Sie	P	SOT89	pnp 60V BCX52 hfe 160
1545	AM	BSS64	Mot	N	SOT23	npn 80V 0.1A fT 60MHz
1546	AM	ZMV933A	Zet	I	SOD323	12-42pF hyperabrupt varicap
1547	AMp	BSS64	Phi	N	SOT23	npn 80V 0.1A fT 60MHz
1548	AMs	BFP420	Sie	MQ	SOT343	npn fT 25GHz 4.5V 35mA
1549	AMs	BSS64	Sie	N	SOT23	npn 80V 0.1A fT 60MHz
1550	AMt	BSS64	Phi	N	SOT23	npn 80V 0.1A fT 60MHz
1551	AN	BCW60FN	Sie	N	SOT23	gp npn 35V 0.2A
1552	AN	ZMV934	Zet	I	SOD323	25-95pF hyperabrupt varicap
1553	ANs	BFP450	Sie	MQ	SOT343	npn fT 25GHz 4.5V 100mA
1554	AO	BCW60AR	ITT	R	SOT23R	BCY58-vii
1555	AO	ZMV934A	Zet	I	SOD323	25-95pF hyperabrupt varicap
1556	AP	BCW60BR	ITT	R	SOT23R	BCY58-viii
1557	APs	BFP520	Sie	MQ	SOT343	npn fT 40GHz 2.5V 40mA
1558	A-Q	2PD1820AQ	Phi	N	SOT323	gp sw amp 50V npn hfe 85-170
1559	A-Q	2PD1820AR	Phi	N	SOT323	gp sw amp 50V npn hfe 120-240
1560	AR	BCW60CR	ITT	R	SOT23R	BCY58-ix
1561	AR	MSD709R	Mot	N		pnp gp 25V
1562	AR1	BSR40	Phi	P	SOT89	npn 70V 1A 1.35W hfe 40-120
1563	AR2	BSR41	Phi	P	SOT89	npn 70V 1A 1.35W hfe 100-300
1564	AR3	BSR42	Phi	P	SOT89	npn 90V 1A 1.35W hfe 40-120
1565	AR4	BSR43	Phi	P	SOT89	npn 90V 1A 1.35W hfe 100-300
1566	AS	BCW60DR	ITT	R	SOT23R	BCY58-x
1567	AS	MSD709S	Mot	N		pnp gp 25V
1568	A-S	2PD1820AS	Phi	N	SOT323	gp sw amp 50V npn hfe 170-340

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1569	AS1	BST50	Mot	P	SOT89	npn darlington 0.5A 60V
1570	AS2	BST51	Mot	P	SOT89	npn darlington 0.5A 80V
1571	AS3	BST52	Mot	P	SOT89	npn darlington 0.5A 90V
1572	AS3	BSP52	Mot	P	SOT223	npn darlington 0.5A hfe 2000
1573	ASs	BAT18-05	Sie	B	SOT23	dual BAT18 RF pin
1574	AtQ	2PD1820AQ	Phi	N	SOT323	gp sw amp 50V npn hfe 85-170
1575	AtQ	2PD1820AR	Phi	N	SOT323	gp sw amp 50V npn hfe 120-240
1576	AtS	2PD1820AS	Phi	N	SOT323	gp sw amp 50V npn hfe 170-340
1577	ATs	BAT18-06	Sie	A	SOT23	dual ca BAT18 RF pin
1578	ATs	BFP540	Sie	MQ	SOT343	npn microwave
1579	AU	BCW60GR	ITT	R	SOT23R	BCY58
1580	AUs	BAT18-04	Sie	D	SOT23	dual BAT18 RF pin
1581	AV	DAN212K	Roh	C		80V 100mA sw
1582	AW	BCW60HR	ITT	R	SOT23R	BCY58
1583	AX	BCX70JR	ITT	R	SOT23R	BCY59-ix
1584	AY	BCX70KR	ITT	R	SOT23R	BCY59-x
1585	AY	MMBD1000	Mot	C	SOT23	Si sw diode 30V 0.2A
1586	B	MRF957	Mot	N	SOT323	npn RF ft 9GHz
1587	B	BAS16-03W	Sie	I	SOD323	Varicap 18pF 1V
1588	B	BB555	Sie	I	SCD80	Varicap 18pF 1V
1589	B0	BZX399C4V3	Phi	I	SOD323	4.3V 0.3W zener
1590	B0	HSMS-2810	HP	C	SOT23	HP2810 schottky
1591	B0	HSMS-281B	HP	C	SOT323	HP2810 schottky
1592	B08	SST6908	Sil	ZQ		2N6908 prot n-ch jfet
1593	B09	SST6909	Sil	ZQ		2N6909 prot n-ch jfet
1594	B1	BZX399C1V8	Phi	I	SOD323	1.8V 0.3W zener
1595	B1	HSMS-2811	HP	K	SOT23	HP2811 schottky
1596	B1	BAS40	Mot	C	SOT23	schottky sw diode
1597	B10	SST6910	Sil	ZQ		2N6910 prot n-ch jfet
1598	B2	BZX399C2V0	Phi	I	SOD323	2.0V 0.3W zener
1599	B2	BSV52	Phi	N	SOT23	BSX20 12V ft 400MHz sw
1600	B2	HSMS-2812	HP	D	SOT23	dual HP2810 schottky
1601	B2	HSMS-281C	HP	D	SOT323	dual HP2810 schottky
1602	B26	BF570	Phi		SOT23	
1603	B2p	BSV52	Phi	N	SOT23	BSX20 12V ft 400MHz sw
1604	B2t	BSV52	Phi	N	SOT23	BSX20 12V ft 400MHz sw
1605	B3	BZX399C2V2	Phi	I	SOD323	2.2V 0.3W zener
1606	B3	HSMS-2813	HP	A	SOT23	dual ca HP2810 schottky
1607	B3	MMBD717L	Mot	A	SOT323	dual ca schottky
1608	B4	BZX399C2V4	Phi	I	SOD323	2.4V 0.3W zener
1609	B4	BSV52R	Phi	R	SOT23R	BSX20
1610	B4	HSMS-2814	HP	B	SOT23	dual cc HP2810 schottky
1611	B5	BZX399C2V7	Phi	I	SOD323	2.7V 0.3W zener
1612	B5	HSMS-2815	HP	S	SOT143	dual HP2810 schottky
1613	B6	BZX399C3V0	Phi	I	SOD323	3.0V 0.3W zener
1614	B6	BAT54A	Mot	A	SOT23	dual ca 30V schottky
1615	B7	BZX399C3V3	Phi	I	SOD323	3.3V 0.3W zener
1616	B7	HSMS-2817	HP	RQ	SOT143	HP2810 ring quad
1617	B8	BZX399C3V6	Phi	I	SOD323	3.6V 0.3W zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1618	B8	HSMS-2818	HP	BQ	SOT143	HP2810 bridge quad
1619	B9	BZX399C3V9	Phi	I	SOD323	3.9V 0.3W zener
1620	B9	2SC4617	Mot	N	SC90	npn gp
1621	BA	BCX54	Sie	P	SOT89	npn AF 45V comp BCX51
1622	BA	BCW61A	Phi	N	SOT23	BCY78-vii
1623	BA	DAN217	Roh	D		80V 100mA dual
1624	BA	BZX399C4V7	Phi	I	SOD323	4.7V 0.3W zener
1625	BAp	BCW61A	Phi	N	SOT23	BCY78-vii
1626	BAt	BCW61A	Phi	N	SOT23	BCY78-vii
1627	BB	BCW61B	Phi	N	SOT23	BCY78-viii
1628	BB	BAR81	Sie	NQ	SOT143	Dual pin shunt switch
1629	BB	BZX399C5V1	Phi	I	SOD323	5.1V 0.3W zener
1630	BBp	BCW61B	Phi	N	SOT23	BCY78-viii
1631	BBs	BCW61B	Sie	N	SOT23	BCY78-viii
1632	BBs	BAR81W	Sie	NQ	SOT343	Dual pin shunt switch
1633	BBt	BCW61B	Phi	N	SOT23	BCY78-viii
1634	BC	BCW61C	Phi	N	SOT23	BCY78-ix
1635	BC	BCX54-10	Sie Phi	P	SOT89	npn hfe100
1636	BC	BZX399C5V6	Phi	I	SOD323	5.6V 0.3W zener
1637	BCp	BCW61C	Phi	N	SOT23	BCY78-ix
1638	BCs	BCW61C	Sie	N	SOT23	BCY78-ix
1639	BCt	BCW61C	Phi	N	SOT23	BCY78-ix
1640	BD	BCW61D	Phi	N	SOT23	BCY78-x
1641	BD	BCX54-16	Sie	P	SOT89	npn hfe160 comp BCX51-16
1642	BD	BZX399C6V2	Phi	I	SOD323	6.2V 0.3W zener
1643	BD	ZHCS400	Zet	E	SOT23	40V 0.4A schottky diode
1644	BDp	BCW61D	Phi	N	SOT23	BCY78-x
1645	BDs	BCW61D	Sie	N	SOT23	BCY78-x
1646	BDt	BCW61D	Phi	N	SOT23	BCY78-x
1647	BE	BAS70	Mot	C	SOT23	schottky sw diode
1648	BE	BCX55	Sie	P	SOT89	npn AF 60V comp BCX52
1649	BE	BZX399C6V8	Phi	I	SOD323	6.8V 0.3W zener
1650	BF	BCW61FF	Sie	N	SOT23	low noise BCW61
1651	BF	BZX399C7V5	Phi	I	SOD323	7.5V 0.3W zener
1652	BG	BCX71G	Phi	N	SOT23	BCY79-vii
1653	BG	BCX55-10	Sie Phi	P	SOT89	npn hfe 100
1654	BG	BZX399C8V2	Phi	I	SOD323	8.2V 0.3W zener
1655	BGp	BCX71G	Phi	N	SOT23	BCY79-vii
1656	BGs	BCX71G	Sie	N	SOT23	BCY79-vii
1657	BGt	BCX71G	Phi	N	SOT23	BCY79-vii
1658	BH	BCX71H	Phi	N	SOT23	BCY79-viii
1659	BH	BCP56	Mot	P	SOT223	npn amp 80V 150mA
1660	BH	BCX56	Sie	P	SOT89	npn AF 80V
1661	BH	BZX399C9V1	Phi	I	SOD323	9.1V 0.3W zener i
1662	BHp	BCX71H	Phi	N	SOT23	BCY79-viii
1663	BHs	BCX71H	Sie	N	SOT23	BCY79-viii
1664	BHt	BCX71H	Phi	N	SOT23	BCY79-viii
1665	BJ	BCX71J	Phi	N	SOT23	BCY79-ix
1666	BJ	BZX399C10	Phi	I	SOD323	10V 0.3W zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1667	BJp	BCX71J	Phi	N	SOT23	BCY79-ix
1668	BJs	BCX71J	Sie	N	SOT23	BCY79-ix
1669	BJt	BCX71J	Phi	N	SOT23	BCY79-ix
1670	BK	BCP56-10	Mot	P	SOT223	npn amp 80V 150mA
1671	BK	BCX71K	Phi	N	SOT23	BCY79
1672	BK	BCX56-10	Sie	P	SOT89	npn hfe 100
1673	BK	BZX399C11	Phi	I	SOD323	11V 0.3W zener
1674	BKp	BCX71K	Phi	N	SOT23	BCY79
1675	BKs	BCX71K	Sie	N	SOT23	BCY79
1676	BKt	BCX71K	Phi	N	SOT23	BCY79
1677	BL	MBD54DW	Mot	DL	SOT363	2x schottky detector diodes
1678	BL	BCP56-16	Mot	P	SOT223	npn amp 80V 150mA
1679	BL	BCX56-16	Sie	P	SOT89	npn hfe 160
1680	BL	BZX399C12	Phi	I	SOD323	12V 0.3W zener
1681	BL	BGA310	Sie	GQ	SOT143	MMIC amp 9dB @1GHz
1682	BLs	BGA420	Sie	HQ	SOT343	MMIC amp 13 dB @1.8GHz
1683	BM	BSS63L	Mot	N	SOT23	100v pnp comp BSS64
1684	BM	BCX55-16	Sie	P	SOT89	npn hfe 160
1685	BM	BGA312	Sie	GQ	SOT143	MMIC amp 11dB @1GHz
1686	BM	BZX399C13	Phi	I	SOD323	13V 0.3W zener
1687	BMp	BSS63	Phi	N	SOT23	100v pnp comp BSS64
1688	BMs	BG427	Sie	HQ	SOT343	MMIC amp 18 dB @1.8GHz
1689	BMt	BSS63	Phi	N	SOT23	100v pnp comp BSS64
1690	BN	BZX399C15	Phi	I	SOD323	15V 0.3W zener
1691	BN	BGA318	Sie	GQ	SOT143	MMIC amp 16dB @1GHz
1692	BNs	BCW61FN	Sie	N	SOT23	low noise BCW61
1693	BO	BCW61AR	Phi	N	SOT23	BCX78, BCY78-vii
1694	BP	BCW61BR	Phi	N	SOT23	BCY78-viii
1695	BP	BZX399C16	Phi	I	SOD323	16V 0.3W zener
1696	BQ	BZX399C18	Phi	I	SOD323	18V 0.3W zener in SOD323
1697	BQ	2PB709AQ	Phi	N	SC-59	PNP 45V 0.1A hfe 160-260
1698	BR	BCW61CR	Phi	N	SOT23	BCY78-ix
1699	BR	2SC2412K	Roh	N		npn 50V 150mA min hfe 180
1700	BR	2SC4081	Roh	N	UMT	2SC2412K above
1701	BR	2SC4617	Roh	N	EM3	2SC2412K above
1702	BR	MSB1218A	Mot	N	SOT323	gp pnp 45V
1703	BR	BZX399C20	Phi	I	SOD323	20V 0.3W zener
1704	BR	2PB709AR	Phi	N	SC-59	pnp45V 0.1A hfe 210-340
1705	BR1	BSR30	Phi	P	SOT89	pnp 70V 1A 1.35W hfe 40-120
1706	BR2	BSR31	Phi	P	SOT89	pnp 70V 1A 1.35W hfe 100-300
1707	BR4	BSR33	Phi	P	SOT89	pnp 90V 1A 1.35W hfe 100-300
1708	BS	BCW61DR	Phi	R	SOT23	BCY78-x
1709	BS	BZX399C22	Phi	I	SOD323	22V 0.3W zener
1710	BS	2PB709AS	Phi	N	SC-59	pnp 45V 0.1A hfe 290-460
1711	BS1	BST60	Mot	P	SOT89	pnp darlington 0.5A 60V
1712	BS2	BST61	Mot	P	SOT89	pnp darlington 0.5A 80V
1713	BS3	BST62	Mot	P	SOT89	pnp darlington 0.5A 90V
1714	BS3	BSP62	Mot	P	SOT89	pnp darlington 0.5A hfe 2000
1715	BT	BZX399C24	Phi	I	SOD323	24V 0.3W zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1716	BT2	BSP16	Mot	P	SOT223	pn _p -300V 1A
1717	BT2	BST16	Phi	P	SOT89	pn _p -300V 1A
1718	BU	BCX71GR	Phi	N	SOT23	BCX79-vii
1719	BU	BZX399C27	Phi	I	SOD323	27V 0.3W zener
1720	BV	BZX399C30	Phi	I	SOD323	30V 0.3W zener
1721	BW	BCW71HR	Phi	N	SOT23R	BCX79-viii
1722	BW	BZX399C33	Phi	I	SOD323	33V 0.3W zener
1723	BX	BCW71JR	Phi	N	SOT23R	BCX79-ix
1724	BX	BZX399C36	Phi	I	SOD323	36V 0.3W zener
1725	BY	BCW71KR	Phi	N	SOT23R	BCX79-x
1726	BY	BZX399C39	Phi	I	SOD323	39V 0.3W zener
1727	BZ	BZX399C43	Phi	I	SOD323	43V 0.3W zener
1728	C	BB565	Sie	I	SCD80	uhf varicap 2-20pF
1729	C	BB179B	Phi	I	SOD 523	UHF Varicap 2-11pF
1730	C	KV1832E	Tok	I	URD	uhf varicap 4-17pf
1731	C white	BAT165	Sie	I		40V 750mA sw Schottky
1732	C0	HSMS-2820	HP	C	SOT23	HP2835 schottky
1733	C0	HSMS-282B	HP	C	SOT323	HP2835 schottky
1734	C06	DDX123JU	Dio	DO	SOT363	dual dtr pnp/npn 50V 0.1A 2k2/47k
1735	C06	DDX123JK	Dio	DO	SOT26	dual dtr pnp/npn 50V 0.1A 2k2/47k
1736	C07	DDX143TU	Dio	DO	SOT363	dual dtr pnp/npn 50V 0.1A R1 4k7
1737	C07	DDX143TK	Dio	DO	SOT26	dual dtr pnp/npn 50V 0.1A R1 4k7
1738	C1	HSMS-2821	HP	K	SOT23	HP2835 schottky
1739	C1	BCW29	Phi	N	SOT23	BC178A
1740	C1	BFQ51C	Phi	CX	SOT173	pn _p BFR90A complement
1741	C11	SST111	Sil	F	SOT23	J111 n-ch fet
1742	C12	SST112	Sil	F	SOT23	J112 n-ch fet
1743	C12	DDX114TU	Dio	DO	SOT363	dual dtr pnp/npn 50V 0.1A R1 10k
1744	C12	DDX114TK	Dio	DO	SOT26	dual dtr pnp/npn 50V 0.1A R1 10k
1745	C13	SST113	Sil	F	SOT23	J113 n-ch fet
1746	C13	DDX114EU	Dio	DO	SOT363	dual dtr pnp/npn 50V 0.1A 10k/10k
1747	C13	DDX114EK	Dio	DO	SOT26	dual dtr pnp/npn 50V 0.1A 10k/10k
1748	C14	DDX114YU	Dio	DO	SOT363	dual dtr pnp/npn 50V 0.1A 10k/47k
1749	C14	DDX114YK	Dio	DO	SOT26	dual dtr pnp/npn 50V 0.1A 10k/47k
1750	C17	DDX124EU	Dio	DP	SOT363	dual dtr pnp/npn 50V 0.1A 22k/22k
1751	C17	DDX124EK	Dio	DP	SOT26	dual dtr pnp/npn 50V 0.1A 22k/22k
1752	C1p	BCW29	Phi	N	SOT23	BC178A
1753	C1t	BCW29	Phi	N	SOT23	BC178A
1754	C2	BCW30	Phi	N	SOT23	BC178B
1755	C2	BFQ32C	Phi	CX	SOT173	pn _p 4.5GHz 15V 100mA
1756	C2	HSMS-2822	HP	D	SOT23	dual HP2835 schottky
1757	C2	HSMS-282C	HP	D	SOT323	dual HP2835 schottky
1758	C2	SST112	Tem	F	SOT23	J112 analog sw n-ch jfet
1759	C20	DDX144EU	Dio	DO	SOT363	dual dtr pnp/npn 50V 0.1A 47k/47k
1760	C20	DDX144EK	Dio	DO	SOT26	dual dtr pnp/npn 50V 0.1A 47k/47k
1761	C2A	ZDC833A	Zet	B	SOT23	dual cc 28V varicap 15pF @2V
1762	C2p	BCW30	Phi	N	SOT23	BC178B
1763	C2t	BCW30	Phi	N	SOT23	BC178B
1764	C3	HSMS-2823	HP	A	SOT23	dual HP2835 schottky

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1765	C3	BFQ23C	Phi	CX	SOT173	pnnp complement BFP91A
1766	C3	SMBT4126	Sie	N		2N4126
1767	C3	SST113	Tem	F	SOT23	J113 analog sw jfet
1768	C38	SST5638	Sil	F	SOT23	2N5638
1769	C39	SST5639	Sil	F	SOT23	2N5639
1770	C4	BCW29R	Phi	R	SOT23R	BC178A
1771	C4	HSMS-2824	HP	B	SOT23	dual HP2835 schottky
1772	C40	SST5640	Sil	F	SOT23	2N5640
1773	C41	SST4091	Sil	F	SOT23	2N4091
1774	C42	SST4092	Sil	F	SOT23	2N4092
1775	C43	SST4093	Sil	F	SOT23	2N4093
1776	C5	MMBA811C5	Mot	N		2N5086 pnp hfe 135-270
1777	C5	BCW30R	Phi	R	SOT23R	BC178B
1778	C5	HSMS-2825	HP	S	SOT143	dual HP2835 schottky
1779	C56	SST4856	Sil	F	SOT23	2N4856
1780	C57	SST4857	Sil	F	SOT23	2N4857
1781	C58	SST4858	Sil	F	SOT23	2N4858
1782	C59	SST4859	Sil	F	SOT23	2N4859
1783	C5A	ZDC834A	Zet	B	SOT23	dual cc 28V varicap 47pF @2V
1784	C6	MMBA811C6	Mot	N		2N5086 pnp hfe 200-400
1785	C60	SST4860	Sil	F	SOT23	2N4860
1786	C61	SST4861	Sil	F	SOT23	2N4861
1787	C7	MMBA811C7	Mot	N		2N5086 pnp hfe 300-600
1788	C7	HSMS-2827	HP	RQ	SOT143	HP2835 ring quad
1789	C8	HSMS-2828	HP	BQ	SOT143	HP2835 bridge quad
1790	C8	BCF30	SGS	N	SOT23	BC559B
1791	C8	MMBA811C8	Mot	N		2N5086 pnp hfe 450-900
1792	C91	SST4391	Sil	F	SOT23	2N4391
1793	C92	SST4392	Sil	F	SOT23	2N4392
1794	C93	SST4393	Sil	F	SOT23	2N4393
1795	CA	BCW61AR	Phi	R	SOT23R	BCY78-vii
1796	CA	BCP68	Mot	P	SOT223	20V 1A npn
1797	CA	ZMV829B	Zet	I	SOD323	varicap hyperab 28V 8.2pF@2V
1798	CB	BCX68-10	Sie	P	SOT89	nnp AF 20V 2A hfe 100
1799	CB	BCW61BR	Phi	R	SOT23R	BCY78-viii
1800	CB	ZMV830B	Zet	I	SOD323	varicap hyperabrupt 28V 10pF@2V
1801	CC	BCW61CR	Phi	R	SOT23R	BCY78-ix
1802	CC	BCX68-16	Sie	P	SOT89	nnp AF 20V 2A hfe 160
1803	CC	ZMV831B	Zet	I	SOD323	varicap hyperabrupt 28V 15pF@2V
1804	CC	ZMDC831B	Zet	B	SOT323	dual cc ZMV831B (above)
1805	CD	BCW61DR	Phi	R	SOT23R	BCY78-x
1806	CD	BCX68-25	Sie	P	SOT89	nnp AF 20V 2A hfe 250
1807	CD	ZMV832B	Zet	I	SOD323	varicap hyperabrupt 28V 22pF@2V
1808	CD	ZMDC832B	Zet	B	SOT323	dual cc ZMV832B (above)
1809	CDs	BSS81B	Sie	N	SOT23	nnp sw 35V 0.8A
1810	CE	BCP69	Mot	P	SOT223	20V 1A pnp
1811	CE	ZMV833B	Zet	I	SOD323	varicap hyperabrupt 28V 33pF@2V
1812	CEs	BSS79B	Sie	N	SOT23	nnp 40V 0.8A hfe 40-120
1813	CF	BSS79C	Sie	N	SOT23	nnp 40V 0.8A hfe 100 min

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1814	CF	BCX69-10	Sie	P	SOT89	pnnp AF 20V 2A hfe 100
1815	CF	ZMV834B	Zet	I	SOD323	varicap hyperabrupt 28V 47pF@2V
1816	CG	BCX71GR	Phi	R	SOT23R	BCY79-vii
1817	CG	BCX69-16	Sie	P	SOT89	pnnp AF 20V 2A hfe 160
1818	CG	ZMV835B	Zet	I	SOD323	varicap hyperabrupt 28V 68pF@2V
1819	CGs	BSS81C	Sie	N	SOT23	npn sw 35V 1A
1820	CH	BSS82BL	Mot	N	SOT23	pnnp 60V
1821	CH	BCX69-25	Sie	N	SOT89	pnnp AF 20V 2A hfe 250
1822	CHs	BSS80B	Sie	N	SOT23	pnnp 40V 0.8A hfe 40-120
1823	CJs	BSS80C	Sie	N	SOT23	pnnp 40V 0.8A hfe 100 min
1824	CK	BCX71JR	Phi	R	SOT23R	BCY79-viii
1825	CLs	BSS82B	Sie	N	SOT23	pnnp 60V 0.8A hfe 40-120
1826	CMs	BSS82C	Sie	N	SOT23	pnnp 60V 0.8A hfe 100 min
1827	CQ	2SC2411K	Roh	N		npn darlington
1828	CQ	MSD710Q	Mot	N	SOT346	pnnp gp 25V 150mA
1829	CR	MSD701R	Mot	N	SOT346	pnnp gp 25V 150mA
1830	D	BB659	Sie	I	SCD80	2-38p varicap
1831	D	BAS21-03W	Sie	I	SOD323	
1832	D	1SS376	Roh	I	USM	300V 50mA sw
1833	D	MRF577	Mot	N	SOT323	npn RF FT 7GHz
1834	D0	HSMP-3800	HP	C	SOT23	HP3800 pin atten diode
1835	D1	BCW31	Phi	N	SOT23	BC108A
1836	D1	HSMP-3801	HP	K		HP3800 pin atten diode
1837	D1	SST211	Tem	XQ		n-ch mosfet 30V 1nS
1838	D1	AZZ23C2V7	Dio	A	SOT23	dual ca zener 2.7V 0.3W
1839	D10	AZZ23C6V2	Dio	A	SOT23	dual ca zener 6.2V 0.3W
1840	D11	SST211	Sil	XQ		n-ch mosfet sw
1841	D11	AZZ23C6V8	Dio	A	SOT23	dual ca zener 6.8V 0.3W
1842	D12	AZZ23C7V5	Dio	A	SOT23	dual ca zener 7.5V 0.3W
1843	D13	SST213	Sil	XQ		n-ch mosfet sw
1844	D13	AZZ23C8V2	Dio	A	SOT23	dual ca zener 8.2V 0.3W
1845	D14	AZZ23C9V1	Dio	A	SOT23	dual ca zener 9.1V 0.3W
1846	D15	AZZ23C10	Dio	A	SOT23	dual ca zener 10V 0.3W
1847	D15	SST215	Sil	XQ		n-ch mosfet sw
1848	D16	AZZ23C11	Dio	A	SOT23	dual ca zener 11V 0.3W
1849	D17	AZZ23C12	Dio	A	SOT23	dual ca zener 12V 0.3W
1850	D18	AZZ23C13	Dio	A	SOT23	dual ca zener 13V 0.3W
1851	D19	AZZ23C15	Dio	A	SOT23	dual ca zener 15V 0.3W
1852	D1p	BCW31	Phi	N	SOT23	BC108A
1853	D1t	BCW31	Phi	N	SOT23	BC108A
1854	D2	BCW32	Phi	N	SOT23	BC108B
1855	D2	HSMP-3802	HP	D		dual HP3800 pin atten diode
1856	D2	AZZ23C3V0	Dio	A	SOT23	dual ca zener 3.0V 0.3W
1857	D20	AZZ23C16	Dio	A	SOT23	dual ca zener 16V 0.3W
1858	D21	AZZ23C18	Dio	A	SOT23	dual ca zener 18V 0.3W
1859	D22	AZZ23C20	Dio	A	SOT23	dual ca zener 20V 0.3W
1860	D23	AZZ23C22	Dio	A	SOT23	dual ca zener 22V 0.3W
1861	D24	AZZ23C24	Dio	A	SOT23	dual ca zener 24V 0.3W
1862	D25	AZZ23C27	Dio	A	SOT23	dual ca zener 27V 0.3W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1863	D26	AZZ23C30	Dio	A	SOT23	dual ca zener 30V 0.3W
1864	D27	AZZ23C33	Dio	A	SOT23	dual ca zener 33V 0.3W
1865	D28	AZZ23C36	Dio	A	SOT23	dual ca zener 36V 0.3W
1866	D29	AZZ23C39	Dio	A	SOT23	dual ca zener 39V 0.3W
1867	D2p	BCW32	Phi	N	SOT23	BC108B
1868	D2t	BCW32	Phi	N	SOT23	BC108B
1869	D3	BCW33	Phi	N	SOT23	BC108C
1870	D3	AZ23C3V3	Dio	A	SOT23	dual ca zener 3.3V 0.3W
1871	D30	AZZ23C43	Dio	A	SOT23	dual ca zener 43V 0.3W
1872	D31	AZZ23C47	Dio	A	SOT23	dual ca zener 47V 0.3W
1873	D32	AZZ23C51	Dio	A	SOT23	dual ca zener 51V 0.3W
1874	D3B	RB420D	Roh	C		25V 100mA schottky
1875	D3E	RB411D	Roh	C	SOT23	20V 500mA schottky
1876	D3J	RB420D	Roh	C		25V 100mA schottky
1877	D3L	RB706D-40	Roh	B		dual 45V 30mA schottky
1878	D3p	BCW33	Phi	N	SOT23	BC108C
1879	D3t	BCW33	Phi	N	SOT23	BC108C
1880	D4	BCW31R	Phi	R	SOT23R	BC108A
1881	D4	HSMP-3804	HP	B	SOT23	dual cc HP3800 pin atten diode
1882	D4	AZ23C3V6	Dio	A	SOT23	dual ca zener 3.6V 0.3W
1883	D5	SST215	Tem	XQ		n-ch mosfet 20V 1nS
1884	D5	BCW32R	Phi	R	SOT23R	BC108B
1885	D5	AZ23C3V9	Dio	A	SOT23	dual ca zener 3.9V 0.3W
1886	D58	FLLD261	Zet	B	SOT23	low leakage dual cc Si diode
1887	D6	BCW33R	Phi	R	SOT23R	BC108C
1888	D6	MMBC1622D6	Mot	N		MPS3904 hfe 200-400
1889	D6	AZ23C4V3	Dio	A	SOT23	dual ca zener 4.3V 0.3W
1890	D63	FLLD263	Zet	A	SOT23	low leakage dual ca Si diode
1891	D7	MMBC1622D7	Mot	N		MPS3904 hfe 300-600
1892	D7	AZ23C4V7	Dio	A	SOT23	dual ca zener 4.7V 0.3W
1893	D76	BAR18J	SGS	I	SOD232	schottky 70V 15mA
1894	D76	BAR18	SGS	C	SOT23	schottky 70V 30mA
1895	D7p	BCF32	Phi	N	SOT23	
1896	D7t	BCF32	Phi	N	SOT23	
1897	D8	AZ23C5V1	Dio	A	SOT23	dual ca zener 5.1V 0.3W
1898	D85	BAT17DS	SGS	D		2xBA481
1899	D86	BAT54J	ST	I	SOD232	schottky 30V 300mA
1900	D86	BAT54	ST	C	SOT23	schottky 30V 300mA
1901	D87	BAT54C	ST	B	SOT23	dual cc schottky 30V 300mA
1902	D88	BAT54S	ST	D	SOT23	dual series schottky 30V 300mA
1903	D8p	BCF33	Phi	N	SOT23	BC146/03
1904	D9	AZ23C5V6	Dio	A	SOT23	dual ca zener 5.6V 0.3W
1905	D94	BAR42	SGS	C	SOT23	schottky 30V 100mA
1906	D95	BAR43	SGS	C	SOT23	schottky 30V 100mA
1907	D96	BAS70-04	SGS	D	SOT23	2xBA18
1908	D97	BAS70-05	SGS	B	SOT23	2xBA18
1909	D98	BAS70-06	SGS	A	SOT23	2xBA18
1910	DA	BCW67A	SGS	N	SOT23	pnP 32V 0.8A hfe 100 min
1911	DA	BF622	Sie	P	SOT89	npn 250V video o/p

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1912	DA5	BAR43S	SGS	D	SOT23	2xBAR43
1913	DB	BCW67B	SGS	N	SOT23	npn 32V 0.8A hfe 160 min
1914	DB	BF623	Sie	P	SOT89	npn 250V video o/p
1915	DB1	BAR43A	SGS	A	SOT23	2xBAR43
1916	DB2	BAR43C	SGS	B	SOT23	2xBAR43
1917	DC	BCW67C	SGS	N	SOT23	npn 32V 0.8A hfe 250 min
1918	DC	BF720	Mot	P	SOT223	npn 1.5W 300V
1919	DC	BFN20	Sie	P	SOT89	npn video o/p 300V comp BFN21
1920	DD	BFN16	Sie	P	SOT89	npn video o/p 250V comp BFN17
1921	DE	BFN18	Sie	P	SOT89	npn video o/p 300V comp BFN19
1922	DF	BCW68F	SGS	N	SOT23	npn 45V 0.8A hfe 100 min
1923	DF	BF721	Mot	P	SOT223	npn 1.5W 300V
1924	DF	BFN21	Sie	P	SOT89	npn 300V video o/p comp BFN20
1925	DG	BCW68G	SGS	N	SOT23	npn 45V 0.8A hfe 160 min
1926	DG	BFN17	Sie	P	SOT89	npn video o/p 250V comp BFN16
1927	DH	BCW68H	SGS	N	SOT23	npn 45V 0.8A hfe 250 min
1928	DH	BCW68G	Mot	N	SOT23	npn 45V 0.8A hfe 160 min
1929	DH	MMBD2000	Mot	C	SOT323	Si sw diode 20V 0.2A SOT323
1930	DH	BFN19	Sie	P	SOT89	npn video o/p 300V comp BFN18
1931	DK	BCX42	Sie	N	SOT23	gp audio npn 125V comp BCX41
1932	DP	MMBD2010	Mot	B	SOT323	dual cc MMBD2000
1933	DQ	2P710AQ	Phi	N	SOT346	gp npn hfe 85-170
1934	DR	2P710AR	Phi	N	SOT346	gp npn hfe 120-240
1935	DS	2P710AS	Phi	N	SOT346	gp npn hfe 170-340
1936	DT	BCW67AR	SGS	R	SOT23R	npn 32V 0.8A hfe 100 min
1937	DU	BCW67BR	SGS	R	SOT23R	npn 32V 0.8A hfe 160 min
1938	DW	BCW67CR	SGS	R	SOT23R	npn 32V 0.8A hfe 250 min
1939	DX	BCW68FR	SGS	R	SOT23R	npn 45V 0.8A hfe 100 min
1940	DY	BCW68GR	SGS	R	SOT23R	npn 45V 0.8A hfe 160 min
1941	DZ	BCW68HR	SGS	R	SOT23R	npn 45V 0.8A hfe 250 min
1942	e	BAT64-02W	Sie	I	SCD80	
1943	E	1SS780	Roh	I	USM	40V 100mA lo leakage
1944	E	BB689	Sie	I	SCD80	2-55pF varicap
1945	E0	HSMP-3810	HP	C	SOT23	HP3810 pin atten diode
1946	E0	HSMP-381B	HP	C	SOT323	HP3810 pin atten diode
1947	E01	DTDG14EP	Roh	P	SOT89	npn dtr 60V 1A R2 10k, + c to b zener
1948	E02	DTDG23YP	Roh	P	SOT89	npn dtr 60V 1A 2k2+ 10k, + c to b zener
1949	E1	HSMP-3811	HP	K	SOT23	HP3810 pin atten diode
1950	E11	DTA113ZE	Roh	N	EMT3	npn dtr 1k0 + 10k 50V 100mA
1951	E11	DTA113ZKA	Roh	N	SC59	npn dtr 1k0 + 10k 50V 100mA
1952	E13	DTA143ZE	Roh	N	EMT3	npn dtr 4k7 + 47k 50V 100mA
1953	E13	DTA143ZKA	Roh	N	SC59	npn dtr 4k7 + 47k 50V 100mA
1954	E1p	BFS17	Phi	N	SOT23	BFY90 BFW92
1955	E1p	BFS17W	Phi	N	SOT323	BFY90 BFW92
1956	E2	BFS17A	Phi	N	SOT23	npn RF 3GHz 25mA
1957	E2	BAL99	Zet	C		sw diode 75V 100mA
1958	E2	HSMP-3812	HP	D	SOT23	dual series HP3810 pin atten diode
1959	E23	DTC143ZCA	Roh	N	SOT23	npn dtr 4k7 + 47k 50V 100mA
1960	E23	DTC143ZE	Roh	N	EMT3	npn dtr 4k7 + 47k 50V 100mA

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
1961	E23	DTC143ZKA	Roh	N	SC59	npn dtr 4k7 + 47k 50V 100mA
1962	E3	BAR99	Zet	C		sw diode 75V 100mA
1963	E3	HSMP-3813	HP	A	SOT23	dual HP3810 pin atten diode
1964	E32	DTA123JE	Roh	N	EMT3	pnp dtr 2k2 + 47k 50V 100mA
1965	E32	DTA123JKA	Roh	N	SC59	pnp dtr 2k2 + 47k 50V 100mA
1966	E4	BFS17R	Phi	R		BFY90 BFW92
1967	E4	HSMP-3814	HP	B	SOT23	dual cc HP3810 pin atten diode
1968	E42	DTC123JE	Roh	N	EMT3	npn dtr 2k2 + 47k 50V 100mA
1969	E42	DTC123JKA	Roh	N	SC59	npn dtr 2k2 + 47k 50V 100mA
1970	E5	BFS17AR	Tfk	R		npn rf 3 GHz 25mA
1971	E56	DTA144VKA	Roh	N	SC59	pnp dtr 47k + 10k 50V 100mA
1972	E6	ZC2800E	Zet	C		HP2800
1973	E66	DTC144VKA	Roh	N	SC59	npn dtr 47k + 10k 50V 100mA
1974	E8	ZC2811E	Zet	C		HP2811
1975	E9	ZC5800E	Zet	C		HP5800
1976	EAs	BCW65A	Sie	N	SOT23	npn 32V 800mA hfe 100 min
1977	EB	HSMP-4810	HP	J	SOT23	0.5-3GHz pin 2 cathode connections
1978	EB	MSC1022-B	Mot	H		pnp RF 150MHz fT 20V
1979	EBs	BCW65B	Sie	N	SOT23	npn 32V 800mA hfe 160 min
1980	EC	MSC1022-C	Mot	H		pnp RF 150MHz fT 20V
1981	ECs	BCW65C	Sie	N	SOT23	npn 32V 800mA hfe 250 min
1982	ED	BCV28	Sie	P	SOT89	pnp darlington 30V 0.8A comp BCV29
1983	EE	BCV48	Sie	P	SOT89	pnp darlington 60V 0.8A comp BCV49
1984	EF	BCV29	Sie	P	SOT89	npn darlington 30V 0.8A comp BCV28
1985	EF	BCW66F	Sie	N	SOT23	npn 45V 800mA hfe 100 min
1986	EG	BCV49	Sie	P	SOT89	npn darlington 60V 0.8A comp BCV48
1987	EGs	BCW66G	Sie	N	SOT23	npn 45V 800mA hfe 160 min
1988	EHAA	MAX6326_R22-T	Max	ZB	SOT23	microproc -ve reset gen 2.200V
1989	EHs	BCW66H	Sie	N	SOT23	npn 45V 800mA hfe 240 min
1990	EIAA	MAX6327_R22-T	Max	ZB	SOT23	microproc +ve reset gen 2.200V
1991	EJAA	MAX6328_R22-T	Max	ZB	SOT23	microproc -ve reset gen 2.200V
1992	EKs	BCX41	Sie	N	SOT23	gp npn 125V 1A comp BCX42
1993	ET	BCW65AR	Sie	R	SOT23R	npn 32V 800mA hfe 100 min
1994	EU	BCW65BR	Sie	R	SOT23R	npn 32V 800mA hfe 160 min
1995	EW	BCW65CR	Sie	R	SOT23R	npn 32V 800mA hfe 240 min
1996	EWAA	MAX6326_R23-T	Max	ZB	SOT23	microproc -ve reset gen 2.320V
1997	EX	BCW65FR	Sie	R	SOT23R	npn 45V 800mA hfe 100 min
1998	EXAA	MAX6326_R24-T	Max	ZB	SOT23	microproc -ve reset gen 2.400V
1999	EY	BCW65GR	Sie	R	SOT23R	npn 45V 800mA hfe 160 min
2000	EYAA	MAX6326_R25-T	Max	ZB	SOT23	microproc -ve reset gen 2.500V
2001	EZ	BCW65HR	Sie	R	SOT23R	npn 45V 800mA hfe 240 min
2002	EZAA	MAX6326_R26-T	Max	ZB	SOT23	microproc -ve reset gen 2.630V
2003	f	BAS20-02W	Sie	I	SCD80	
2004	F	KV1831E	Tok	I	URD	uhf varicap 2.5-22pf
2005	F	MRF927	Mot	N	SOT323	npn RF fT 8GHz
2006	F0	HSMP-3820	HP	C	SOT23	35V RF pin sw diode
2007	F02	DTD123TK	Roh	N	SC59	npn dtr R1 2k2 40V 100mA
2008	F03	DTD143TK	Roh	N	SC59	npn dtr R1 4k7 40V 100mA
2009	F05	TSDF1205	Tfk	X		fT 12GHz npn RF 4V 12mA

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2010	F1	HSMP-3821	HP	K	SOT23	35V RF pin sw diode
2011	F1	BFS18	Phi	N	SOT23	BF495
2012	F1	MMBC1009F1	Mot	N		RF npn fT 150MHz hfe30-60
2013	F11	DTB113EK	Roh	N	SC59	pnp dtr 1k + 1k 50V 500mA
2014	F12	DTB123EK	Roh	N	SC59	pnp dtr 2k2 + 2k2 50V 500mA
2015	F13	DTB143EC	Roh	N	SOT23	pnp dtr 4k7+ 4k7 50V 500mA
2016	F13	DTB143EK	Roh	N	SC59	pnp dtr 4k7+ 4k7 50V 500mA
2017	F14	DTB114EK	Roh	N	SC59	pnp dtr 10k + 10k 50V 500mA
2018	F2	HSMP-3822	HP	D	SOT23	dual series HP3820 pin sw diode
2019	F2	BFS19	SGS	N	SOT23	BF184 BF494
2020	F20	TSDF1220	Tfk	X		fT 12GHz npn 6V 20mA
2021	F21	DTD113EK	Roh	N	SC59	nnp dtr 1k + 1k 50V 500mA
2022	F22	DTD123EK	Roh	N	SC59	nnp dtr 2k2 + 2k2 50V 500mA
2023	F23	DTD143EC	Roh	N	SOT23	nnp dtr 4k7 + 4k7 50V 500mA
2024	F23	DTD143EK	Roh	N	SC59	nnp dtr 4k7 + 4k7 50V 500mA
2025	F24	DTD114EK	Roh	N	SC59	nnp dtr 10k + 10k 50V 500mA
2026	F2p	BFS19	Phi	N	SOT23	BF184 BF494
2027	F2t	BFS19	Phi	N	SOT23	BF184 BF494
2028	F3	MMBC1009F3	Mot	N		RF npn fT150MHz hfe60-120
2029	F4	BFS18R	Phi	N		BF495
2030	F4	HSMP-3824	HP	B	SOT23	dual cc HP3820 pin sw diode
2031	F5	BFS19R	Phi	N		BF184 BF494
2032	F52	DTB123YC	Roh	N	SOT23	pnp dtr 2k2 + 10k 50V 100mA
2033	F52	DTB123YK	Roh	N	SC59	pnp dtr 2k2 + 10k 50V 100mA
2034	F62	DTD123YK	Roh	N	SC59	nnp dtr 2k2 + 10k 50V 100mA
2035	F8p	BF824	Phi	N	SOT23	
2036	F8t	BF824	Phi	N	SOT23	
2037	F8t	BF824W	Phi	N	SOT323	
2038	F92	DTB123TK	Roh	N	SC59	pnp dtr R1 2k2 40V 100mA
2039	F93	DTB143TK	Roh	N	SC59	pnp dtr R1 4k7 40V 100mA
2040	F94	DTB114TK	Roh	N	SC59	pnp dtr R110k 40V 100mA
2041	FA	HSMP-4820	HP	B	SOT23	0.5-3GHz cc pin dual anode
2042	FA	BFQ17	Phi	P	SOT89	nnp RF 1.5GHz 300mA
2043	FA	BFP81	Sie	X		BFQ69
2044	FA	BFQ19	Phi	P	SOT89	nnp RF Ft 5.5GHz 100mA
2045	FAAA	MAX6326_R27-T	Max	ZB	SOT23	microproc -ve reset gen 2.700V
2046	FB	BFP17	Sie	X		BFW92
2047	FBAA	MAX6328_R31-T	Max	ZB	SOT23	microproc -ve reset gen 2.800V
2048	FC	BFQ64	Sie	P		BFT98T
2049	FC	BFP29	Sie	X		BFT97
2050	FCAA	MAX6326_R29-T	Max	ZB	SOT23	microproc -ve reset gen 2.930V
2051	FD	BCV26	SGS	N	SOT23	pnp darlington
2052	FD	BFQ17P	Sie	P	SOT89	BFW16A
2053	FD	BFP35A	Sie	X		BFR34A
2054	FDAA	MAX6326_R31-T	Max	ZB	SOT23	microproc -ve reset gen 3.080V
2055	FDp	BCV26	Phi	N	SOT23	pnp darlington
2056	FDt	BCV26	Phi	N	SOT23	pnp darlington
2057	FE	BCV46	SGS	N	SOT23	pnp darlington
2058	FE	BFP93A	Sie	X	SOT143	BFR91A

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2059	FEAA	MAX6326_R30-T	Max	ZB	SOT23	microproc -ve reset gen 3.000V
2060	FEp	BCV46	Phi	N	SOT23	pnnp darlington
2061	FEs	BFQ19P	Sie	P	SOT89	BFR96
2062	FEt	BCV46	Phi	N	SOT23	pnnp darlington
2063	FF	BCV27	SGS	N	SOT23	npn darlington
2064	FF	BBY65-02V	Inf	I	SC79	hyperabrupt varicap 2.7-30pF
2065	FFAA	MAX6327_R23-T	Max	ZB	SOT23	microproc +ve reset gen 2.320V
2066	FFMA	MAX6327_R31-T	Max	ZB	SOT23	microproc +ve reset gen 3.080V
2067	FFNA	MAX6327_R30-T	Max	ZB	SOT23	microproc +ve reset gen 3.000V
2068	FFp	BCV27	Phi	N	SOT23	npn darlington
2069	FFt	BCV27	Phi	N	SOT23	npn darlington
2070	FG	BCV47	Phi	N	SOT23	npn darlington
2071	FG	BFQ19S	Sie	P	SOT89	BFR96S
2072	FGAA	MAX6327_R24-T	Max	ZB	SOT23	microproc +ve reset gen 2.400V
2073	FGp	BCV47	Phi	N	SOT23	npn darlington
2074	FGt	BCV47	Phi	N	SOT23	npn darlington
2075	FHAA	MAX6327_R25-T	Max	ZB	SOT23	microproc +ve reset gen 2.500V
2076	FHs	BFN24	Sie	N	SOT23	npn 250V comp to BFN25
2077	FIAA	MAX6327_R26-T	Max	ZB	SOT23	microproc +ve reset gen 2.630V
2078	FJ	BFN26	Sie	N	SOT23	npn 300V comp to BFN27
2079	FJAA	MAX6327_R27-T	Max	ZB	SOT23	microproc +ve reset gen 2.700V
2080	FK	BFN25	Sie	N	SOT23	pnnp 250V comp to BFN24
2081	FKAA	MAX6327_R28-T	Max	ZB	SOT23	microproc +ve reset gen 2.800V
2082	FL	BFN27	Sie	N	SOT23	pnnp 300V comp to BFN26
2083	FLAA	MAX6327_R29-T	Max	ZB	SOT23	microproc +ve reset gen 2.930V
2084	FOAA	MAX6328_R23-T	Max	ZB	SOT23	microproc -ve reset gen 2.320V
2085	FPAA	MAX6328_R24-T	Max	ZB	SOT23	microproc -ve reset gen 2.400V
2086	F-Q	2PA1576Q	Phi	N	SOT323	gp npn SC70 hfe 120-270
2087	FQAA	MAX6328_R25-T	Max	ZB	SOT23	microproc -ve reset gen 2.500V
2088	FR	2SA1037AK	Roh	N		hfe 150@1ma preamp npn
2089	FR	2SA1576A	Roh	N	UMT	see 2SA1037K above
2090	FR	2SA1774	Roh	N	EM3	see 2SA1037K above
2091	F-R	2PA1576R	Phi	N	SOT323	gp npn hfe 180-390
2092	FRAA	MAX6328_R26-T	Max	ZB	SOT23	microproc -ve reset gen 2.630V
2093	F-S	2PA1576S	Phi	N	SOT323	gp npn hfe 270-560
2094	FSAA	MAX6328_R27-T	Max	ZB	SOT23	microproc -ve reset gen 2.700V
2095	FTAA	MAX6328_R28-T	Max	ZB	SOT23	microproc -ve reset gen 2.800V
2096	FtQ	2PA1576Q	Phi	N	SOT323	gp npn SC70 hfe 120-270
2097	FtR	2PA1576R	Phi	N	SOT323	gp npn hfe 180-390
2098	FtS	2PA1576S	Phi	N	SOT323	gp npn hfe 270-560
2099	FUAA	MAX6328_R29-T	Max	ZB	SOT23	microproc -ve reset gen 2.930V
2100	FVAA	MAX6328_R31-T	Max	ZB	SOT23	microproc -ve reset gen 3.080V
2101	FWAA	MAX6328_R30-T	Max	ZB	SOT23	microproc -ve reset gen 3.000V
2102	FZAP	MAX6012A	Max	ZC	SOT23	precision reference 1.247V
2103	FZAQ	MAX6025A	Max	ZC	SOT23	precision reference 2.500V
2104	FZAR	MAX6041A	Max	ZC	SOT23	precision reference 4.096V
2105	FZAS	MAX6045A	Max	ZC	SOT23	precision reference 4.500V
2106	FZAT	MAX6050A	Max	ZC	SOT23	precision reference 5.000V
2107	FZAU	MAX6021A	Max	ZC	SOT23	precision reference 2.048V

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2108	FZAV	MAX6346_R33-T	Max	ZB	SOT23	micrproc -ve reset gen 3.300V
2109	FZAW	MAX6346_R34-T	Max	ZB	SOT23	micrproc -ve reset gen 3.400V
2110	FZAX	MAX6346_R35-T	Max	ZB	SOT23	micrproc -ve reset gen 3.500V
2111	FZAY	MAX6346_R36-T	Max	ZB	SOT23	micrproc -ve reset gen 3.600V
2112	FZAZ	MAX6346_R37-T	Max	ZB	SOT23	micrproc -ve reset gen 3.700V
2113	FZBA	MAX6346_R38-T	Max	ZB	SOT23	micrproc -ve reset gen 3.800V
2114	FZBB	MAX6346_R39-T	Max	ZB	SOT23	micrproc -ve reset gen 3.900V
2115	FZBC	MAX6346_R40-T	Max	ZB	SOT23	micrproc -ve reset gen 4.0800V
2116	FZBD	MAX6346_R41-T	Max	ZB	SOT23	micrproc -ve reset gen 4.100V
2117	FZBE	MAX6346_R42-T	Max	ZB	SOT23	micrproc -ve reset gen 4.200V
2118	FZBF	MAX6346_R43-T	Max	ZB	SOT23	micrproc -ve reset gen 4.300V
2119	FZBG	MAX6346_R44-T	Max	ZB	SOT23	micrproc -ve reset gen 4.380V
2120	FZBH	MAX6346_R45-T	Max	ZB	SOT23	micrproc -ve reset gen 4.500V
2121	FZBI	MAX6346_R46-T	Max	ZB	SOT23	micrproc -ve reset gen 4.630V
2122	FZBJ	MAX6347_R33-T	Max	ZB	SOT23	micrproc +ve reset gen 3.300V
2123	FZBK	MAX6347_R34-T	Max	ZB	SOT23	micrproc +ve reset gen 3.400V
2124	FZBL	MAX6347_R35-T	Max	ZB	SOT23	micrproc +ve reset gen 3.500V
2125	FZBM	MAX6347_R36-T	Max	ZB	SOT23	micrproc +ve reset gen 3.600V
2126	FZBN	MAX6347_R37-T	Max	ZB	SOT23	micrproc +ve reset gen 3.700V
2127	FZBO	MAX6347_R38-T	Max	ZB	SOT23	micrproc +ve reset gen 3.800V
2128	FZBP	MAX6347_R39-T	Max	ZB	SOT23	micrproc +ve reset gen 3.900V
2129	FZBQ	MAX6347_R40-T	Max	ZB	SOT23	micrproc +ve reset gen 4.0800V
2130	FZBR	MAX6347_R41-T	Max	ZB	SOT23	micrproc +ve reset gen 4.100V
2131	FZBS	MAX6347_R42-T	Max	ZB	SOT23	micrproc +ve reset gen 4.200V
2132	FZBT	MAX6347_R43-T	Max	ZB	SOT23	micrproc +ve reset gen 4.300V
2133	FZBU	MAX6347_R44-T	Max	ZB	SOT23	micrproc +ve reset gen 4.380V
2134	FZBV	MAX6347_R45-T	Max	ZB	SOT23	micrproc +ve reset gen 4.500V
2135	FZBW	MAX6347_R46-T	Max	ZB	SOT23	micrproc +ve reset gen 4.630V
2136	FZBX	MAX6348_R33-T	Max	ZB	SOT23	microproc -ve reset gen 3.300V
2137	FZBY	MAX6348_R34-T	Max	ZB	SOT23	microproc -ve reset gen 3.400V
2138	FZBZ	MAX6348_R35-T	Max	ZB	SOT23	microproc -ve reset gen 3.500V
2139	FZCA	MAX6348_R36-T	Max	ZB	SOT23	microproc -ve reset gen 3.600V
2140	FZCB	MAX6348_R37-T	Max	ZB	SOT23	microproc -ve reset gen 3.700V
2141	FZCC	MAX6348_R38T	Max	ZB	SOT23	microproc -ve reset gen 3.800V
2142	FZCD	MAX6348_R39-T	Max	ZB	SOT23	microproc -ve reset gen 3.900V
2143	FZCE	MAX6348_R40-T	Max	ZB	SOT23	microproc -ve reset gen 4.000V
2144	FZCF	MAX6348_R41-T	Max	ZB	SOT23	microproc -ve reset gen 4.100V
2145	FZCG	MAX6348_R42T	Max	ZB	SOT23	microproc -ve reset gen 4.200V
2146	FZCH	MAX6348_R43-T	Max	ZB	SOT23	microproc -ve reset gen 4.380V
2147	FZCI	MAX6348_R44-T	Max	ZB	SOT23	microproc -ve reset gen 4.400V
2148	FZCJ	MAX6348_R45-T	Max	ZB	SOT23	microproc -ve reset gen 4.500V
2149	FZCK	MAX6348_R46-T	Max	ZB	SOT23	microproc -ve reset gen 4.600V
2150	FZCW	MAZ6001UR	Max	ZC	SOT23	1.250V V reference
2151	FZCX	MAZ6002UR	Max	L	SOT23	2.500V V reference
2152	FZCY	MAZ6004UR	Max	L	SOT23	4.096V V reference
2153	FZCZ	MAZ6005UR	Max	L	SOT23	5.000V V reference
2154	FZDA	MAX6012B	Max	ZC	SOT23	precision reference 1.247V
2155	FZDB	MAX6025B	Max	ZC	SOT23	precision reference 2.500V
2156	FZDC	MAX6041B	Max	ZC	SOT23	precision reference 4.096V

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2157	FZDD	MAX6045B	Max	ZC	SOT23	precision reference 4.500V
2158	FZdE	MAX6050B	Max	ZC	SOT23	precision reference 5.000V
2159	FZDF	MAX6021B	Max	ZC	SOT23	precision reference 2.047V
2160	FZDK	MAZ6003UR	Max	L	SOT23	3.000V V reference
2161	FZDW	MAX6030A	Max	ZC	SOT23	precision reference 3.000V
2162	FZDX	MAX6012B	Max	ZC	SOT23	precision reference 3.000V
2163	FZEB	LM4041AIM3-1.2	Max	L	SOT23	1.225V 0.1% shunt V ref
2164	FZEC	LM4041BIM3-1.2	Max	L	SOT23	1.225V 0.2% shunt V ref
2165	FZED	LM4041DIM3-1.2	Max	L	SOT23	1.225V 0.5% shunt V ref
2166	FZEE	LM4041DIM3-1.2	Max	L	SOT23	1.225V 1.5% shunt V ref
2167	FZEF	LM4040A IM3-2.1	Max	L	SOT23	2.048V shunt reference 0.1%
2168	FZEG	LM4040B IM3-2.1	Max	L	SOT23	2.048V shunt reference 0.2 %
2169	FZEH	LM4040C IM3-2.1	Max	L	SOT23	2.048V shunt reference 0.5%
2170	FZEI	LM4040D IM3-2.1	Max	L	SOT23	2.048V shunt reference 1.0%
2171	FZEJ	LM4040A IM3-2.5	Max	L	SOT23	2.500V shunt reference 0.1%
2172	FZEK	LM4040B IM3-2.5	Max	L	SOT23	2.500V shunt reference 0.2 %
2173	FZEL	LM4040C IM3-2.5	Max	L	SOT23	2.500V shunt reference 0.5%
2174	FZEM	LM4040D IM3-2.5	Max	L	SOT23	2.500V shunt reference 1.0%
2175	FZEN	LM4040A IM3-3.0	Max	L	SOT23	3.000V shunt reference 0.1%
2176	FZEO	LM4040B IM3-3.0	Max	L	SOT23	3.000V shunt reference 0.2 %
2177	FZEP	LM4040C IM3-3.0	Max	L	SOT23	3.000V shunt reference 0.5%
2178	FZEQ	LM4040D IM3-3.0	Max	L	SOT23	3.000V shunt reference 1.0%
2179	FZER	LM4040A IM3-4.1	Max	L	SOT23	4.096V shunt reference 0.1%
2180	FZES	LM4040B IM3-4.1	Max	L	SOT23	4.096V shunt reference 0.2 %
2181	FZET	LM4040C IM3-4.1	Max	L	SOT23	4.096V shunt reference 0.5%
2182	FZEU	LM4040DIM3-4.1	Max	L	SOT23	4.096V shunt reference 1.0%
2183	FZEV	LM4040A IM3-5.0	Max	L	SOT23	5.000V shunt reference 0.1%
2184	FZEW	LM4040B IM3-5.0	Max	L	SOT23	5.000V shunt reference 0.2 %
2185	FZEX	LM4040C IM3-5.0	Max	L	SOT23	5.000V shunt reference 0.5%
2186	FZEY	LM4040D IM3-5.0	Max	L	SOT23	5.000V shunt reference 1.0%
2187	FZEZ	MAZ803LUR	Max	ZB	SOT23	microproc -ve reset gen, 5.0V
2188	FZFA	MAZ803MUR	Max	ZB	SOT23	microproc -ve reset gen, 5.0V
2189	FZFB	MAZ803TUR	Max	ZB	SOT23	microproc -ve reset gen, 3.3V
2190	FZFC	MAZ803SUR	Max	ZB	SOT23	microproc -ve reset gen, 3.3V
2191	FZFD	MAZ803RUR	Max	ZB	SOT23	microproc -ve reset gen, 3.0V
2192	FZGH	MAZ6006AUR	Max	L	SOT23	1.250V 0.2% shunt V reference
2193	FZGI	MAZ6006BUR	Max	L	SOT23	1.250V 0.5% shunt V reference
2194	FZGJ	MAZ6006CUR	Max	L	SOT23	1.250V 1.0% shunt V reference
2195	FZGK	MAZ6007AUR	Max	L	SOT23	2.480V 0.2% shunt V reference
2196	FZGL	MAZ6007BUR	Max	L	SOT23	2.480V 0.5% shunt V reference
2197	FZGM	MAZ6007CUR	Max	L	SOT23	2.480V 1.0% shunt V reference
2198	FZGN	MAZ6008AUR	Max	L	SOT23	2.500V 0.2% shunt V reference
2199	FZGO	MAZ6008BUR	Max	L	SOT23	2.500V 0.5% shunt V reference
2200	FZGP	MAZ6008CUR	Max	L	SOT23	2.500V 1.0% shunt V reference
2201	FZGQ	MAZ6009AUR	Max	L	SOT23	3.000V 0.2% shunt V reference
2202	FZGR	MAZ6009BUR	Max	L	SOT23	3.000V 0.5% shunt V reference
2203	FZGS	MAZ6009CUR	Max	L	SOT23	3.000V 1.0% shunt V reference
2204	G	BAR63-02W	Sie	I	SCD80	RF pin to 3GHz
2205	G	BAR63-03W	Sie	I	SOD323	RF pin to 3GHz

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2206	G	KV1181E	Tok	I	URD	uhf varicap 2-16pF
2207	G	MRF947A	Mot	N	SOT323	nnp RF 8GHz
2208	G0	HSMP-3890	HP	C	SOT23	HP3890 pin sw diode
2209	G0	HSMP-389B	HP	C	SOT323	HP3890 pin sw diode
2210	G08	DTD133HKA	Roh	N	SC59	nnp dtr 3k3+10k 50V 500mA
2211	G1	BFS20	Phi	N	SOT23	BF199
2212	G1	BFS20	Phi	N	SOT23	BF199
2213	G1	MMBT5551	Mot	N	SOT23	2N5551 npn Vce 140V
2214	G11	DTB113ZKA	Roh	N	SC59	pnp dtr 1k0 +10k 50V 500mA
2215	G1E	BC847A	Rho	N	SOT23	BC547A
2216	G1F	BC847B	Rho	N	SOT23	BC547B
2217	G1G	BC847C	Rho	N	SOT23	BC547C
2218	G1J	BC848A	Rho	N	SOT23	BC548A
2219	G1K	BC848B	Rho	N	SC70	BC548B
2220	G1K	BC848B	Rho	N	SOT23	BC548B
2221	G1L	BC848C	Rho	N	SOT23	BC548C
2222	G1p	BFS20	Phi	N	SOT23	BF199
2223	G1t	HSMP-3891	HP	K	SOT23	HP3890 pin sw diode
2224	G2	HSMP-3892	HP	D	SOT23	dual ser HP3890 pin sw diode
2225	G2	CGY50	Sie	IQ	SOT143	GaAs MMIC amp
2226	G21	DTD113ZKA	Roh	N	SC59	nnp dtr 1k0 +10k 50V 500mA
2227	G3	HSMP-3893	HP	A	SOT23	dual HP3890 pin sw diode
2228	G3	BAR63	Sie	C	SOT23	single 3GHz pin
2229	G3C	DTB122JK	Roh	N	SC59	pnp dtr 220R + 470R 50V 500mA
2230	G3E	BC857A	Roh	N	SOT23	BC557A
2231	G3F	BC857B	Roh	N	SOT23	BC557B
2232	G3J	BC858A	Roh	N	SOT23	BC558A
2233	G3K	BC858B	Roh	N	SOT23	BC558B
2234	G3K	BC858B	Roh	N	SC70	BC558B
2235	G3L	BC858C	Roh	N	SOT23	BC558C
2236	G4	BFS20R	Phi	N	SOT23	BF199
2237	G4	HSMP-3894	HP	B	SOT23	dual HP3890 pin sw diode
2238	G4	BAR63-04	Sie	D	SOT23	dual series 3GHz pin
2239	G4C	DTD122JK	Roh	N	SC59	nnp dtr 220R + 470R 50V 500mA
2240	G4s	BAR63-04W	Sie	D	SOT323	dual series 3GHz pin
2241	G5	HSMP-3895	HP	S	SOT143	dual HP3890 pin sw diode
2242	G5	BAR63-05	Sie	B	SOT23	dual cc 3GHz pin
2243	G5B	BC807-25	Roh	N	SOT23	BC327-25
2244	G5s	BAR63-05W	Sie	B	SOT323	dual cc 3GHz pin
2245	G6	BAR63-06	Sie	A	SOT23	dual ca 3GHz pin
2246	G6A	BC817-16	Roh	N		BC337-16
2247	G6B	BC817-25	Roh	N	SOT23	BC337-25
2248	G6s	BAR63-06W	Sie	A	SOT323	dual ca 3GHz pin
2249	G7	BF579	Tfk	N		BF979 pnp uhf ft 1.75GHz
2250	G98	DTB133HKA	Roh	N	SC59	pnp dtr 3k3+10k 50V 500mA
2251	GA	HSMP-4890	HP	B	SOT23	0.5-3GHz dual cc pin limiter
2252	GA	BAW78A	Sie	LQ	SOT89	50V 1A sw diode
2253	GAB	BCW60B	Rho	N	SOT23	BCY58-viii
2254	GAC	BCW60C	Rho	N	SOT23	BCY58-ix

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2255	GAD	BCW60D	Rho	N	SOT23	BCY58-x
2256	GAH	BCX70H	Rho	N	SOT23	BCY59-viii BC107B
2257	GAJ	BCX70J	Rho	N	SOT23	BCY59-ix BC107
2258	GAK	BCX70K	Rho	N	SOT23	BCY59-x BC107
2259	GB	BAW78B	Sie	LQ	SOT89	100V 1A sw diode
2260	GBB	BCW61B	Rho	N	SOT23	BCY78-viii
2261	GBC	BCW61C	Rho	N	SOT23	BCY78-ix
2262	GBG	BCX71G	Rho	N	SOT23	BCY79-vii
2263	GBH	BCX71H	Rho	N	SOT23	BCY79-viii
2264	GBJ	BCX71J	Rho	N	SOT23	BCY79-ix
2265	GC	BAW78C	Sie	LQ	SOT89	200V 1A sw diode
2266	GC1	BCW29	Roh	N	SOT23	BC178A
2267	GC2	BCW30	Roh	N	SOT23	BC178B
2268	GD	BAW78D	Sie	LQ	SOT89	400V 1A sw diode
2269	GD1	BCW31	Roh	N	SOT23	BC108C
2270	GD2	BCW32	Roh	N	SOT23	BC108B
2271	GD3	BCW33	Roh	N	SOT23	BC108A
2272	GE	BFR35AP	Sie	N	SOT23	BFR34A
2273	GE	BAW79A	Sie	JQ	SOT89	dual cc 50V 1A switch diodes
2274	GEC	BCW65C	Rho	N	SOT23	npn 32V 800mA hfe 250 min
2275	GF	BFR92P	Sie	N	SOT23	BFR90
2276	GF	BAW79B	Sie	JQ	SOT89	dual cc 100V 1A switch diodes
2277	GG	BF579R	Tfk	R		BF979 pnp uhf fT1.75GHz
2278	GG	BFR93P	Sie	N	SOT23	BFR91A
2279	GG	BAW79C	Sie	JQ	SOT89	dual cc 200V 1A switch diodes
2280	GH	BAW79D	Sie	JQ	SOT89	dual cc 400V 1A switch diodes
2281	GH1	BCW69	Roh	N	SOT23	BC177A
2282	GH2	BCW70	Roh	N	SOT23	BC177B
2283	GK1	BCW71	Roh	N	SOT23	BC107A
2284	GK2	BCW72	Roh	N	SOT23	BC107B ZXT300
2285	GLP	MMBT1010	Mot	N	SOT23	pnp 15V hfe 300-600 @100mA
2286	GLP	MMBT1010	Mot	N	SOT346	pnp 15V hfe 300-600 @100mA
2287	GMA	BFS17	Roh	N	SOT23	BFW92
2288	GT1	BCX17	Roh	N	SOT23	BC327
2289	GT2	BCX18	Roh	N	SOT23	BC328
2290	GU1	BCX19	Roh	N	SOT23	BC337
2291	GU2	BCX20	Roh	N	SOT23	BC338
2292	H	MRF947B	Mot	N	SOT323	npn RF 8GHz
2293	H	BB659C	Sie	I	SCD80	2.5-39 pF varicap in
2294	H	BBY51-03W	Sie	I	SOD323	3-5 pF varicap in
2295	H	BB141	Phi	I	SOD 523	Low Voltage Varicap
2296	H02	DTC323TU	Rho	N	SC70	npn dtr 15V 0.6A, R1 2k Ω , for muting
2297	H04	DTC323TU	Rho	N	SC70	npn dtr 15V 0.6A, R1 10k Ω , for muting
2298	H1	BCW69	Phi	N	SOT23	BC177A
2299	H11	UMH11TN	Roh	DI		npn/pnpdtr pair 10k Ω +10k
2300	H16	SST4416	Sil	F		2N4416 n-ch jfet
2301	H1p	BCW69	Phi	N	SOT23	BC177A
2302	H1t	BCW69	Phi	N	SOT23	BC177A
2303	H2	BCW70	Phi	N	SOT23	BC177B

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2304	H27	DTC323TU	Rho	N	SC70	npn dtr 15V 0.6A, R1 6k8 , for muting
2305	H2p	BCW70	Phi	N	SOT23	BC177B
2306	H2t	BCW70	Phi	N	SOT23	BC177B
2307	H3	BCW89	Phi	N	SOT23	BC556
2308	H31	BCW89R	Phi	N	SOT23R	BC556
2309	H3p	BCW89	Phi	N	SOT23	BC556
2310	H3t	BCW89	Phi	N	SOT23	BC556
2311	H4	BCW69R	Phi	R	SOT23R	BC177A
2312	H5	BCW70R	Phi	R	SOT23R	BC177B
2313	H5	MBD770DW	Mot	DL		Dual UHF schottky diode
2314	H6	BCW89R	Phi	R	SOT23R	BC556
2315	H84	SST5484	Sil	F	SOT23	2N5484
2316	H85	SST5485	Sil	F	SOT23	2N5485
2317	H86	SST5486	Sil	F	SOT23	2N5486
2318	HB	BFN22	SGS	P	SOT23	npn Vce 250V
2319	HC	BFN23	SGS	P	SOT23	pnnp Vce 250V
2320	HG	CFY77-08	Sie	DM		20GHz HEMT 0.8dB nf
2321	HH	CFY77-10	Sie	DM		20GHz HEMT 1.0 dB nf
2322	HH	BBY51-07	Sie	S	SOT143	dual varicap like BBY51
2323	HQ	2SA1036K	Roh	N		pnnp 500mA driver
2324	I	BBY51-02W	Sie	I	SCD80	3-5 pF varicap
2325	I	BBY52-03W	Sie	I	SOD323	1.25-1.75 pF varicap in
2326	I08	SST108	Sil	F	SOT23	J108 n-ch jfet
2327	I09	SST109	Sil	F	SOT23	J109 n-ch jfet
2328	I10	SST110	Sil	F	SOT23	J110 n-ch jfet
2329	J0	HSMS-2840	HP	C	SOT23	schottky diode
2330	J01	SO2906R		N		2N2906
2331	J03	SO2907AR		R		2N2907A
2332	J05	SO2907R		R		2N2907
2333	J1	HSMS-2841	HP	K	SOT23	schottky diode
2334	J1	ZC830	Zet	C		ZC820 varicaps
2335	J1	BSS138L	Mot	M	SOT23	n-ch enh TMOS fet
2336	J12	SO2906AR		R		2N2906A
2337	J1A	ZC830A	Zet	C	SOT23	varicap hyperabrupt 28V 10pF@2V
2338	J1B	ZC830B	Zet	C	SOT23	varicap hyperabrupt 28V 10pF@2V
2339	J2	ZC833	Zet	C	SOT23	ZC823
2340	J2A	ZC833A	Zet	C	SOT23	varicap hyperabrupt 28V 33pF@2V
2341	J2B	ZC833B	Zet	C	SOT23	varicap hyperabrupt 28V 33pF@2V
2342	J3	ZC831	Zet	C	SOT23	ZC821
2343	J32	SO5400R	SGS	R		2N5400
2344	J33	SO5401R	SGS	R		2N5401
2345	J39	SO692R	SGS			pnnp Vce 300V
2346	J3A	ZC831A	Zet	C	SOT23	varicap hyperabrupt 28V 15pF@2V
2347	J3B	ZC831B	Zet	C	SOT23	varicap hyperabrupt 28V 15pF@2V
2348	J3D	MSB81T1	Mot			vhf pnp fT 0.6GHz
2349	J4	ZC832	Zet	C	SOT23	ZC823
2350	J4A	MBV109	Mot	C	SOT23	29pF VHF varicap diode
2351	J4A	ZC832A	Zet	C	SOT23	varicap hyperabrupt 28V 22pF@2V
2352	J4B	ZC832B	Zet	C	SOT23	varicap hyperabrupt 28V 22pF@2V

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2353	J5	ZC834	Zet	C	SOT23	ZC824
2354	J5A	ZC834A	Zet	C	SOT23	varicap hyperabrupt 28V 47pF@2V
2355	J5B	ZC834B	Zet	C	SOT23	varicap hyperabrupt 28V 47pF@2V
2356	J6	M1MA174	Mot	C		gp Si diode 100V
2357	J6	ZC835	Zet	C	SOT23	ZC825
2358	J6A	ZC835A	Zet	C	SOT23	varicap hyperabrupt 28V 68pF@2V
2359	J6B	ZC835B	Zet	C	SOT23	varicap hyperabrupt 28V 68pF@2V
2360	J7	ZC836	Zet	C	SOT23	ZC826
2361	J7A	ZC830A	Zet	C	SOT23	varicap hyperabrupt 28V 100pF@2V
2362	J7B	ZC830B	Zet	C	SOT23	varicap hyperabrupt 28V 100pF@2V
2363	J8	BCX71JR	Phi	R	SOT23R	BCY79-ix
2364	J9A	ZC829A	Zet	I	SOT23	varicap hyperabrupt 28V 8.2pF@2V
2365	J9B	ZC829B	Zet	I	SOT23	varicap hyperabrupt 28V 8.2pF@2V
2366	JA	BAV74	Zet	B	SOT23	dual diode cc 50V 0.1A
2367	JA	BAV74	Mot	B	SOT23	dual sw diodes
2368	JBs	BAR74	Sie	C	SOT23	fast sw diode 50V 0.25A
2369	JCs	BAL74	Sie	V	SOT23	fast sw diode 50V 0.25A
2370	JFs	BAL99	Sie	V	SOT23	fast sw diode 70V 0.25A
2371	JG	BAR99	Sie	E		fast sw diode 70V 0.25A
2372	JKs	BF1009	Sie	W	SOT143	biased n-ch dg mosfet 1GHz 9V
2373	JL	MRF949	Mot	N	SOT323	nnp RF FT 9GHz
2374	JLs	BF1009S	Sie	W	SOT143	biased n-ch dg mosfet 1GHz 9V
2375	JPs	BAS19	Sie	C	SOT23	120V 250mA fast sw diode
2376	JPs	BAW101	Sie	S	SOT143	pair isolated 300V sw diodes
2377	JRs	BAS20	Sie	C	SOT23	150V 250mA fast sw diode
2378	JS	BAW100	Sie	Y	SOT143	dual isolated fast sw diodes
2379	JSs	BAS21	Sie	C	SOT143	200V 250mA fast sw diode
2380	JTs	BAS28	Sie	S	SOT143	dual isolated fast sw diodes
2381	JTs	BAS28W	Sie	FQ	SOT343	dual isolated fast sw diodes
2382	JV	BAS116	Sie	C	SOT23	250V 75mA Ir 5nA
2383	JX	BAV170	Mot	B	SOT23	dual cc Si diode low Ir
2384	JY	BAV199	Mot	D	SOT23	dual series Si diode low Ir
2385	JZ	BAW156	Mot	A	SOT23	dual ca Si diode low Ir
2386	K	BAT68-03W	Sie	I	SOD323	BAT68 Schottky
2387	K	BBY52-02W	Sie	I	SCD80	UHF varicap 1.75-1.25pF
2388	K	MRF917	Mot	N	SOT323	nnp RF FT 6GHz
2389	K	BB142	Phi	I	SOD 523	Low Voltage Varicap
2390	K0	HSMP-3830	HP	C	SOT23	gp pin diode HP3830
2391	K1	HSMP-3831	HP	K	SOT23	gp pin diode HP3830
2392	K1	BCW71	Phi	N	SOT23	BC107A
2393	K14	DTA114GE	Roh	N	EMT3	pnp dtr 50V 100mA R2 10k
2394	K14	DTA114GUA	Roh	N	SC70	pnp dtr 50V 100mA R2 10k
2395	K14	DTA114GKA	Roh	N	SC59	pnp dtr 50V 100mA R2 10k
2396	K15	DTA124GKA	Roh	N	SC59	pnp dtr 50V 50mA R2 22k
2397	K16	DTA144GUA	Roh	N	SC70	nnp dtr 50V 100mA R2 47k
2398	K16	DTA144GKA	Roh	N	SC59	nnp dtr 50V 100mA R2 47k
2399	K19	DTA115GUA	Roh	N	SC70	nnp dtr 50V 100mA R2 100k
2400	K19	DTA115GKA	Roh	N	SC59	nnp dtr 50V 100mA R2 100k
2401	K1p	BCW71	Phi	N	SOT23	BC107A

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2402	K1t	BCW71	Phi	N	SOT23	BC107A
2403	K2	BCW72	Phi	N	SOT23	BC107B ZXT300
2404	K2	HSMP-3832	HP	D	SOT23	dual HP3830 pin diode
2405	K24	DTC114GUA	Roh	N	SC70	npn dtr 50V 100mA R2 22k
2406	K24	DTC114GKA	Roh	N	SC59	npn dtr 50V 100mA R2 22k
2407	K25	DTA124GUA	Roh	N	SC70	pnp dtr 50V 50mA R2 22k
2408	K25	DTA124GKA	Roh	N	SC59	pnp dtr 50V 50mA R2 22k
2409	K26	DTC144GE	Roh	N	EMT3	npn dtr 50V 100mA R2 47k
2410	K26	DTC144GUA	Roh	N	SC70	npn dtr 50V 100mA R2 47k
2411	K26	DTC144GKA	Roh	N	SC59	npn dtr 50V 100mA R2 47k
2412	K29	DTC115GUA	Roh	N	SC70	npn dtr 50V 100mA R2 100k
2413	K29	DTC115GKA	Roh	N	SC59	npn dtr 50V 100mA R2 100k
2414	K2p	BCW72	Phi	N	SOT23	BC107B ZXT300
2415	K2t	BCW72	Phi	N	SOT23	BC107B ZXT300
2416	K3	HSMP-3833	HP	A	SOT23	dual HP3830 pin diode
2417	K3	BCW81	Phi	N	SOT23	npn 50V 0.1A 0.2W hfe 420
2418	K3	BB145C	Phi	I	SOD 523	Low Voltage Varicap
2419	K31	BCW81R	Phi	R		npn 50V 0.1A 0.2W hfe 420
2420	K3p	BCW81	Phi	N	SOT23	npn 50V 0.1A 0.2W hfe 420
2421	K3t	BCW81	Phi	N	SOT23	npn 50V 0.1A 0.2W hfe 420
2422	K4	BCW71R	Phi	R	SOT23R	BC107A
2423	K4	HSMP-3834	HP	B	SOT23	dual HP3830 pin diode
2424	K5	BCW72R	Phi	R	SOT23R	BC107B ZTX300
2425	K6	BCV71R	Phi	R	SOT23R	BC546A
2426	K7	BCV71	Phi	N	SOT23	BC546A
2427	K7p	BCV71	Phi	N	SOT23	BC546A
2428	K7t	BCV71	Phi	N	SOT23	BC546A
2429	K8	BCV72	Phi	N	SOT23	BC546B
2430	K8p	BCV72	Phi	N	SOT23	BC546B
2431	K8t	BCV72	Phi	N	SOT23	BC546B
2432	K9	BCV72R	Phi	R	SOT23R	BC546B
2433	KB	MMBT8099L	Mot	N	SOT23	npn 80V gp
2434	KC	BFQ29P	Sie	N		BFT66
2435	KD1	AZ23C2V7	Dio	A	SOT23	dual ca zener 2.7V 0.3W
2436	KD2	AZ23C3V0	Dio	A	SOT23	dual ca zener 3.0V 0.3W
2437	KD3	AZ23C3V3	Dio	A	SOT23	dual ca zener 3.3V 0.3W
2438	KD4	AZ23C3V6	Dio	A	SOT23	dual ca zener 3.6V 0.3W
2439	KD5	AZ23C3V9	Dio	A	SOT23	dual ca zener 3.9V 0.3W
2440	KD6	AZ23C4V3	Dio	A	SOT23	dual ca zener 4.3V 0.3W
2441	KD7	AZ23C4V7	Dio	A	SOT23	dual ca zener 4.7V 0.3W
2442	KD8	AZ23C5V1	Dio	A	SOT23	dual ca zener 5.1V 0.3W
2443	KD9	AZ23C5V6	Dio	A	SOT23	dual ca zener 5.6V 0.3W
2444	KD9	AZZ23C5V6W	Dio	A	SOT323	dual ca zener 5.6V 0.2W
2445	KDA	AZ23C6V2	Dio	A	SOT23	dual ca zener 6.2V 0.3W
2446	KDB	AZZ23C6V8	Dio	A	SOT23	dual ca zener 6.8V 0.3W
2447	KDB	AZZ23C6V8W	Dio	A	SOT323	dual ca zener 6.8V 0.2W
2448	KDC	AZZ23C7V5	Dio	A	SOT23	dual ca zener 7.5V 0.3W
2449	KDD	AZZ23C8V2	Dio	A	SOT23	dual ca zener 8.2V 0.3W
2450	KDE	AZZ23C9V1	Dio	A	SOT23	dual ca zener 9.1V 0.3W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2451	KDF	AZZ23C10	Dio	A	SOT23	dual ca zener 10V 0.2W
2452	KDF	AZZ23C10W	Dio	A	SOT323	dual ca zener 10V 0.3W
2453	KDG	AZZ23C11	Dio	A	SOT23	dual ca zener 11V 0.3W
2454	KDH	AZZ23C12	Dio	A	SOT23	dual ca zener 12V 0.3W
2455	KDI	AZZ23C13	Dio	A	SOT23	dual ca zener 13V 0.3W
2456	KDJ	AZZ23C15	Dio	A	SOT23	dual ca zener 15V 0.3W
2457	KDK	AZZ23C16	Dio	A	SOT23	dual ca zener 16V 0.3W
2458	KDL	AZZ23C18	Dio	A	SOT23	dual ca zener 18V 0.3W
2459	KDL	AZZ2318W	Dio	A	SOT323	dual ca zener 18V 0.2W
2460	KDM	AZZ23C20	Dio	A	SOT23	dual ca zener 20V 0.3W
2461	KDN	AZZ23C22	Dio	A	SOT23	dual ca zener 22V 0.3W
2462	KDO	AZZ23C24	Dio	A	SOT23	dual ca zener 24V 0.3W
2463	KDP	AZZ23C27	Dio	A	SOT23	dual ca zener 27V 0.3W
2464	KDQ	AZZ23C30	Dio	A	SOT23	dual ca zener 30V 0.3W
2465	KDR	AZZ23C33	Dio	A	SOT23	dual ca zener 33V 0.3W
2466	KDS	AZZ23C36	Dio	A	SOT23	dual ca zener 36V 0.3W
2467	KDT	AZZ23C39	Dio	A	SOT23	dual ca zener 39V 0.3W
2468	KM	BST80	Phi	T		VN10
2469	KN	BST84	Phi	T		Nch VMOS 200V 0.25A
2470	KO	BST86	Phi	T		nch VMOS 180V 0.3A
2471	KV1	DZ23C2V7	Dio	A	SOT23	dual cc zener 2.7V 0.3W
2472	KV2	DZ23C3V0	Dio	A	SOT23	dual cc zener 3.0V 0.3W
2473	KV3	DZ23C3V3	Dio	A	SOT23	dual cc zener 3.3V 0.3W
2474	KV4	DZ23C3V6	Dio	A	SOT23	dual cc zener 3.6V 0.3W
2475	KV5	DZ23C3V9	Dio	A	SOT23	dual cc zener 3.9V 0.3W
2476	KV6	DZ23C4V3	Dio	A	SOT23	dual cc zener 4.3V 0.3W
2477	KV7	DZ23C4V7	Dio	A	SOT23	dual cc zener 4.7V 0.3W
2478	KV8	DZ23C5V1	Dio	A	SOT23	dual cc zener 5.1V 0.3W
2479	KV9	DZ23C5V6	Dio	A	SOT23	dual cc zener 5.6V 0.3W
2480	KVA	DZ23C6V2	Dio	A	SOT23	dual cc zener 6.2V 0.3W
2481	KVB	DZZ23C6V8	Dio	A	SOT23	dual cc zener 6.8V 0.3W
2482	KVC	DZZ23C7V5	Dio	A	SOT23	dual cc zener 7.5V 0.3W
2483	KVD	DZZ23C8V2	Dio	A	SOT23	dual cc zener 8.2V 0.3W
2484	KVE	DZZ23C9V1	Dio	A	SOT23	dual cc zener 9.1V 0.3W
2485	KVF	DZZ23C10	Dio	A	SOT23	dual cc zener 10V 0.2W
2486	KVG	DZZ23C11	Dio	A	SOT23	dual cc zener 11V 0.3W
2487	KVH	DZZ23C12	Dio	A	SOT23	dual cc zener 12V 0.3W
2488	KVI	DZZ23C13	Dio	A	SOT23	dual cc zener 13V 0.3W
2489	KVJ	DZZ23C15	Dio	A	SOT23	dual cc zener 15V 0.3W
2490	KVK	DZZ23C16	Dio	A	SOT23	dual cc zener 16V 0.3W
2491	KVL	DZZ23C18	Dio	A	SOT23	dual cc zener 18V 0.3W
2492	KVM	DZZ23C20	Dio	A	SOT23	dual cc zener 20V 0.3W
2493	KVN	DZZ23C22	Dio	A	SOT23	dual cc zener 22V 0.3W
2494	KVO	DZZ23C24	Dio	A	SOT23	dual cc zener 24V 0.3W
2495	KVP	DZZ23C27	Dio	A	SOT23	dual cc zener 27V 0.3W
2496	KVQ	DZZ23C30	Dio	A	SOT23	dual cc zener 30V 0.3W
2497	KVR	DZZ23C33	Dio	A	SOT23	dual cc zener 33V 0.3W
2498	KVS	DZZ23C36	Dio	A	SOT23	dual cc zener 36V 0.3W
2499	KVT	DZZ23C39	Dio	A	SOT23	dual cc zener 39V 0.3W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2500	KVU	DZZ23C43	Dio	A	SOT23	dual cc zener 43V 0.3W
2501	KVV	DZZ23C47	Dio	A	SOT23	dual cc zener 47V 0.3W
2502	KVW	DZZ23C51	Dio	A	SOT23	dual cc zener 51V 0.3W
2503	L	BAT62-03W	Sie	I	SOD323	BAT62 schottky detector
2504	L	BBY53-02W	Sie	I	SCD80	varicap 5.3-2.2 pF
2505	L	BB14	Phi	I	SOD 523	Low Voltage Varicap
2506	L0	HSMP-386B	HP	C	SOT323	gp RF pin diode
2507	L0	HSMP-3860	HP	C	SOT23	dual series pin diode
2508	L0	BAT721S	Phi	C	SOT23	dual series 40V 200mA schottky
2509	L05	ZLLS500	Zet	C	SOT23	schottky 40V 0.7A low leakage high temp
2510	L1	BSS65	Zet	N		pnnp 12V 0.1A 400MHz sw
2511	L10	ZLLS1000	Zet	C	SOT23	schottky 40V 1.1A low leakage high temp
2512	L14	DTB114GK	Rho	N	SC59	pnnp dtr 0.5A, R2 10k
2513	L14	DTD114GK	Rho	N	SC59	npnp dtr 0.5A, R2 10k
2514	L2	HSMP-3862	HP	D	SOT23	dual RF pin diode
2515	L2	BSS69	Zet	N		pnnp 40V 0.1A 200MHz sw
2516	L2	BB202	Phi	I	SOD 523	Low Voltage Varicap
2517	L20	BAS29	Nat	C	SOT23	Si diode 120V 50mA
2518	L21	BAS31	Nat	D	SOT23	dual BAS29 diodes
2519	L22	BAS35	Nat	A	SOT23	dual BAS29 diodes
2520	L3	BSS70	Zet	N		pnnp 40V 0.1A 200MHz sw
2521	L3	MMBC1623L3	Mot	N		npnp 40V gp
2522	L3	HSMP-3863	HP	A	SOT23	ca gp RF pin diode
2523	L30	BAV23	Phi	S	SOT143	dual 200V 225mA diodes
2524	L4	HSMP-3864	HP	B	SOT23	cc gp RF pin diode
2525	L4	BAT54W	Phi	C	SOT323	BAT85 schottky
2526	L4	MMBC1623L4	Mot	N		npnp 40V gp
2527	L41	BAT74	Phi	S	SOT143	2x BAT85
2528	L42p	BAT54A	Phi	A	SOT23	dual c anode schottky
2529	L43p	BAT54C	Phi	B	SOT23	dual c cathode schottky
2530	L44p	BAT54S	Phi	D	SOT23	dual series schottky
2531	L4p	BAT54	Phi	C	SOT23	BAT85 schottky
2532	L4Z	BAT54	Zet	C	SOT23	BAT85 schottky
2533	L5	BSS65R	Zet	R		pnnp 12V 0.1A 400MHz sw
2534	L5	MMBC1623L5	Mot	N		MPS3904 hfe 135-270
2535	L51	BAS56	Phi	S	SOT143	dual 60V 200mA diodes
2536	L6	BAR17	Sie	C		pin diode
2537	L6	BSS69R	Zet	N		pnnp 40V 0.1A 200MHz sw
2538	L6	MMBC1623L6	Mot	N		MPS3904 hfe 200-400
2539	L7	BSS70R	Zet	N		pnnp 40V 0.1A 200MHz sw
2540	L7	MMBC1623L7	Mot	N		MPS3904 hfe 300-600
2541	L7	BAR14-1	Sie	D		dual pin 100mA max
2542	L8	BAT721A	Phi	A	SOT23	dual c anode 40V 200mA schottky
2543	L8	BAR15-1	Sie	A		dual pin 100mA max
2544	L9	BAT721C	Phi	B	SOT23	dual c cathode 40V 200mA schottky
2545	L9	BAR16-1	Sie	B		dual pin 100mA max
2546	LAp	BF550	Phi	N	SOT23	pnnp 40V 25mA
2547	LB	S525T	Tfk	G		n-ch vhf mosfet 200MHz
2548	LBs	BF999	Sie	G	SOT23	n-ch vhf mosfet 300MHz

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2549	LDs	BF543	Sie	G	SOT23	n-ch vhf mosfet 300MHz
2550	LEs	BF660	Sie	N	SOT23	BF606A pnp vhf osc fT 800MHz
2551	LGs	BF775A	Sie	N	SOT23	nnp RF fT 5.6GHz for IF amp
2552	LH	BF569R	Tfk	R		BF970 pnp RF
2553	LHs	BF569	Sie	N	SOT23	BF970 pnp RF
2554	LKs	BF799	Sie	N	SOT23	BF959
2555	LKs	BF799W	Sie	N	SOT323	BF959
2556	LKs	BF799	Sie	N	SOT23	BF959
2557	LKs	BF799W	Sie	N	SOT323	BF959
2558	LM	BST120	Phi	T		p-ch DMOSfet 60V 0.3A
2559	LN	BST122	Phi	T		p-ch DMOSfet 50V 0.25A
2560	LOs	BF775	Sie	N	SOT23	BFQ69
2561	LOs	BF775W	Sie	N	SOT323	BFQ69
2562	LRs	BF517	Sie	T	SOT23	BF763 2.5 GHz
2563	LSs	BF770A	Sie	N	SOT23	nnp low noise RF, Ft 6GHz
2564	M	BAR64-02W	Sie	I	SCD80	pin diode
2565	M	BAR65-07	Sie	S	SOT143	dual pin diode
2566	M (blue)	BAR65-03W	Sie	I	SOD323	pin diode
2567	M (white)	BBY55-03W	Sie	I	SOD323	5.4-2.3pF varicap in
2568	M01	BF901	Phi	W	SOT143	N-ch dg mosfet
2569	M02	BF901R	Phi	UQ	SOT143	N-ch dg mosfet
2570	M04	BF904	Phi	W	SOT143B	N-ch dg mosfet
2571	M06	BF904R	Phi	UQ	SOT143	N-ch dg mosfet
2572	M08	PMBFJ308	Phi	F	SOT23	VHF n-ch JFET J308
2573	M09	PMBFJ309	Phi	F	SOT23	VHF n-ch JFET J309
2574	M1	BFR30	Phi	F	SOT23	BFW11 BF245
2575	M10	PMBFJ310	Phi	F	SOT23	VHF n-ch JFET J310
2576	M10	PMBFJ310	Phi	F	SOT23	J310 n-ch jfet
2577	M16	PMBF4416A	Phi	ZC	SOT23	2N4416A n-ch jfet
2578	M1B	MMBT2222L	Mot	N	SOT23	2N2222
2579	M1E	MMBTA43L	Mot	N	SOT23	MPSA43 200V Vce npn
2580	M1F	MMBT5550L	Mot	N	SOT23	2N5550 npn 140V
2581	M1J	MMBT2369L	Mot	N	SOT23	2N2369A
2582	M2	BFR31	Phi	F	SOT23	BFW12 BF245
2583	M26	BF908	Phi	W	SOT143	UHF n-ch dg mosfet
2584	M27	BF908R	Phi	UQ	SOT143	UHF n-ch dg mosfet
2585	M28	BF909	Phi	W	SOT143	UHF n-ch dg mosfet
2586	M29	BF909R	Phi	UQ	SOT143	UHF n-ch dg mosfet
2587	M2B	MMBT2907L	Mot	N	SOT23	2N2907 pnp gp
2588	M2C	MMBTA70L	Mot	N	SOT23	gp pnp MPSA70
2589	M3	BFT46	Phi	F	SOT23	n-ch fet gp low level amp
2590	M3	MMBA812M3	Mot	N		2N5086 hfe 60-120 pnp
2591	M31	BSD20	Phi	XQ		n-ch depl sw mosfet 10V
2592	M32	BSD22	Phi	XQ		n-ch depl sw mosfet 20V
2593	M33	BF861A	Phi	ZC	SOT23	n-ch jfet
2594	M34	BF861B	Phi	ZC	SOT23	n-ch jfet
2595	M35	BF861C	Phi	ZC	SOT23	n-ch jfet
2596	M3A	MMBTH24L	Mot	N	SOT23	nnp VHF amp 400MHz fT 30V
2597	M3B	MMBT918L	Mot	N	SOT23	2N918 UHF amp

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2598	M3J	MMBTH69L	Mot	N	SOT23	pnv VHF amp 2GHz fT 15V
2599	M4	BSR56	Phi	F		2N4856 n-ch fet
2600	M4	MBD110DW	Mot	DL	SOT363	dual UHF schottky
2601	M4A	MMBV109	Mot	C	SOT323	Hyperabrupt varicap
2602	M4B	MMBV432	Mot	B	SOT23	dual cc varicap 45pF/2V
2603	M4C	MMBV3102	Mot	C	SOT23	Hyperabrupt varicap
2604	M4E	MMBV105G	Mot	C	SOT23	Hyperabrupt varicap
2605	M4F	MMBD353	Mot	D	SOT23	dual MBD101 in series
2606	M4G	MMBV2101	Mot	C	SOT23	varicap 6.8pF MV2101
2607	M5	BSR57	Phi	F		2N5457 n-ch fet
2608	M5	MMBA812M5	Mot	N		2N5086 hfe 135-270 pnp
2609	M5	MMBD352W	Mot	Z	SOT323	2x MBD101 in series
2610	M52	BF992R	Phi	UQ	SOT143R	n-ch dg mosfet
2611	M56	BF1100	Phi	W	SOT143	dg mosfet 14V 30mA 0.2W
2612	M57	BF1100R	Phi	UQ	SOT143R	dg mosfet 14V 30mA 0.2W
2613	M5C	MMBD7000	Mot	D	SOT23	100V 2x series sw diodes
2614	M6	BSR58	Phi	F	SOT23	2N4858 n-ch fet
2615	M6	MMBA812M6	Mot	N		2N5086 hfe 200-400 pnp
2616	M6	BSS66	Zet	N		npn 40V 0.1A sw fT 250MHz
2617	M65	BF545A	Phi	ZC	SOT23	VHF n-ch jfet
2618	M66	BF545B	Phi	ZC	SOT23	VHF n-ch jfet
2619	M67	BF545C	Phi	ZC	SOT23	VHF n-ch jfet
2620	M68	PMBFJ210	Phi	ZC	SOT23	n-ch jfet J210
2621	M69	PMBFJ211	Phi	ZC	SOT23	n-ch jfet J211
2622	M6A	MMBF4416	Mot	F	SOT23	2N4416 n-ch rf jfet
2623	M6B	MMBF5484	Mot	F	SOT23	2N5484 n-ch rf jfet
2624	M6C	MMBFU310	Mot	F	SOT23	U310 n-ch rf jfet
2625	M6E	MMBF5460	Mot	F	SOT23	2N5460 n-ch rf jfet
2626	M6H	MMBD354	Mot	A	SOT23	dual MBD101 cc
2627	M7	BSS67	Zet	N		npn 40V 0.1A sw fT 300MHz
2628	M7	MMBA812M7	Mot	N		2N5086 hfe 300-600 pnp
2629	M70	PMBFJ212	Phi	ZC	SOT23	n-ch jfet J212
2630	M74	BSS83	Phi	XQ		n-ch enh sw mosfet
2631	M8	BSS66R	Zet	R		npn 40V 0.1A sw fT 250MHz
2632	M8	BSH103	Phi	M	SOT23	n-ch 50V 0.11A mosfet
2633	M84	BF556A	Phi	ZC	SOT23	VHF n-ch jfet
2634	M85	BF556B	Phi	ZC	SOT23	VHF n-ch jfet
2635	M86	BF556C	Phi	ZC	SOT23	VHF n-ch jfet
2636	M87	BF990A	Phi	W	SOT23	UHF n-ch dg mosfet
2637	M8p	BSN20	Phi	M	SOT23	n-ch 50V 0.11A mosfet
2638	M9	BSS67R	Zet	R		npn 40V 0.1A sw fT 300MHz
2639	M90	BF990	Phi	W		BF980
2640	M91	BF991	Phi	W		BF981
2641	M92	BF992	Phi	W		BF982
2642	M94	BF994	Phi	W		BF964
2643	M96	BF996	Phi	W		BF966
2644	M97	BFR101A				
2645	M98	BFR101B				
2646	MA	M1MA151AT	Mot	E	SOT346	40V 100mA sw diode

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2647	MA	MBT3904DW1	Mot	DN	SOT363	dual 2N3904
2648	MA	M1MA152AT	Mot	E	SOT346	80V 100mA sw diode
2649	MA	BFS17		N	SOT23	BFW92
2650	MAp	BF989	Phi	W	SOT143	n-ch dg mosfet
2651	MB	BF998WR	Phi	UQ	SOT343	n-ch vhf dg mosfet BF988
2652	MB	BF995	Sie	UQ		n-ch vhf dg mosfet BF961
2653	MB	MBT3904DW9	Mot			dual 2N3904
2654	MC	ZVN3306F	Zet	M	SOT23	n-ch mosfet 60V 150mA
2655	MC	BF904WR	Phi	UQ	SOT343R	n-ch uhf dg mosfet
2656	MCs	BFS17P	Sie	N	SOT23	BFW92
2657	MCs	BFS17PW	Sie	N	SOT323	BFW92
2658	MD	BF908WR	Phi	UQ	SOT343R	n-ch uhf dg mosfet
2659	MF	ZVN3310F	Zet	M	SOT23	n-ch mosfet 100V 100mA
2660	MF	BF1100WR	Phi	UQ	SOT343R	n-ch uhf dg mosfet
2661	MG	BF994S	Tfk	W		BF964 n-ch dg vhf mosfet
2662	MGp	BF994S	Phi	W	SOT343	BF964 n-ch dg vhf mosfet
2663	MH	BF996S	Tfk	W		BF966 n-ch dg vhf mosfet
2664	MH	BF996S	Phi	W	SOT343	BF966 n-ch dg vhf mosfet
2665	MH	M1MA141KT	Mot	C	SOT323	40V 100mA sw diode
2666	MH	M1MA151KT	Mot	C	SOT346	40V 100mA sw diode
2667	MI	M1MA142KT	Mot	C	SOT323	80V 100mA sw diode
2668	MI	M1MA152KT	Mot	C	SOT346	80V 100mA sw diode
2669	ML	ZVP3306F	Zet	M	SOT23	p-ch mosfet 60V 90mA
2670	MN	M1MA141WA	Mot	A	SOT323	d diode ca 40V 100mA
2671	MN	M1MA151WA	Mot	A	SOT346	d diode ca 40V 100mA
2672	MO	M1MA142W	Mot	A	SOT323	d diode ca 80V 100mA
2673	MO	M1MA152W	Mot	A	SOT346	d diode ca 80V 100mA
2674	MOp	BF998	Phi	W	SOT143	n-ch vhf dg mosfet BF988
2675	MOp	BF998R	Sie	UQ	SOT143R	n-ch vhf dg mosfet BF988
2676	MOR	BF998R	Tfk	UQ	SOT143R	n-ch vhf dg mosfet BF988
2677	MOs	BF998	Sie	W	SOT143	n-ch vhf dg mosfet BF988
2678	MR	BF998W	Sie	UQ	SOT143R	n-ch vhf dg mosfet BF988
2679	MR	ZVP3310F	Zet	M	SOT23	p-ch mosfet 100V 75mA
2680	MS	CF739	Sie	W		dg GaAsfet 2GHz
2681	MT	M1MA141WK	Mot	B	SOT323	dual diode cc 40V 100mA
2682	MT	M1MA151WK	Mot	B	SOT346	dual diode cc 40V 100mA
2683	MU	M1MA142WK	Mot	B	SOT323	dual diode cc 80V 100mA
2684	MU	M1MA152WK	Mot	B	SOT346	dual diode cc 80V 100mA
2685	MU	ZVN3320F	Zet	M	SOT23	n-ch mosfet 200V 60mA
2686	MX	CF750	Sie	U		biased dg GaAsfet, 3-6V
2687	MY	VN10LF	Zet	M	SOT23	n-ch mosfet 60V 150mA
2688	MY	BF1012	Sie	W		n-ch dg mosfet 1GHz 12V
2689	MZ	ZVN4106F	Zet	M	SOT23	n-ch mosfet 60V 200mA
2690	MZ	BF1005	Sie	W		n-ch dg mosfet 1GHz 5V
2691	N	DAN202K	Roh	B		80V 100mA dual diode
2692	N	BB181	Phi	I	SOD 523	VHF Varicap 1-15pF
2693	N0	TN0200T	Nat	M	SOT23	n-ch mosfet 0.6A Id
2694	N01	DDTC113TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 1k0 0.15W
2695	N01	DDTC113TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 1k0 0.2W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2696	N01	DDTC113TCA	Dio	N	SOT23	dtr npn 50V 0.1A R11k0 0.2W
2697	N01	DDTC113TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 1k0 0.2W
2698	N02	DDTC113ZE	Dio	N	SOT523	dtr npn 50V 0.1A res 1k0/10k 0.15W
2699	N02	DDTC113ZUA	Dio	N	SOT323	dtr npn 50V 0.1A res 1k0/10k 0.2W
2700	N02	DDTC113ZCA	Dio	N	SOT23	dtr npn 50V 0.1A res 1k0/10k 0.2W
2701	N02	DDTC113ZKA	Dio	N	SC59	dtr npn 50V 0.1A res 1k0/10k 0.2W
2702	N03	DDTC123TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 2k2 0.15W
2703	N03	DDTC123TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 2k2 0.2W
2704	N03	DDTC123TCA	Dio	N	SOT23	dtr npn 50V 0.1A R1 2k2 0.2W
2705	N03	DDTC123TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 2k2 0.2W
2706	N04	DDTC123EE	Dio	N	SOT523	dtr npn 50V 0.1A res 2k2/2k2 0.15W
2707	N04	DDTC123EUA	Dio	N	SOT323	dtr npn 50V 0.1A res 2k2/2k2 0.2W
2708	N04	DDTC123ECA	Dio	N	SOT23	dtr npn 50V 0.1A res 2k2/2k2 0.2W
2709	N04	DDTC123EKA	Dio	N	SC59	dtr npn 50V 0.1A res 2k2/2k2 0.2W
2710	N05	SO2484	SGS	N		2N2484
2711	N05	DDTC123YE	Dio	N	SOT523	dtr npn 50V 0.1A res 2k2/10k 0.15W
2712	N05	DDTC123YUA	Dio	N	SOT323	dtr npn 50V 0.1A res 2k2/10k 0.2W
2713	N05	DDTC123YCA	Dio	N	SOT23	dtr npn 50V 0.1A res 2k2/10k 0.2W
2714	N05	DDTC123YKA	Dio	N	SC59	dtr npn 50V 0.1A res 2k2/10k 0.2W
2715	N06	DDTC123JE	Dio	N	SOT523	dtr npn 50V 0.1A res 2k2/47k 0.15W
2716	N06	DDTC123JUA	Dio	N	SOT323	dtr npn 50V 0.1A res 2k2/47k 0.2W
2717	N06	DDTC123JCA	Dio	N	SOT23	dtr npn 50V 0.1A res 2k2/47k 0.2W
2718	N06	DDTC123JKA	Dio	N	SC59	dtr npn 50V 0.1A res 2k2/47k 0.2W
2719	N06	DDC123JU	Dio	DN	SOT363	dual dtr npn 50V 0.1A 2k2/47k
2720	N06	DDC123JK	Dio	DN	SOT26	dual dtr npn 50V 0.1A 2k2/47k
2721	N07	DDTC143TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 4k7 0.15W
2722	N07	DDTC143TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 4k7 0.2W
2723	N07	DDTC143TCA	Dio	N	SOT23	dtr npn 50V 0.1A R1 4k7 0.2W
2724	N07	DDTC143TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 4k7 0.2W
2725	N07	DDC143TU	Dio	DN	SOT363	dual dtr npn 50V 0.1A R1 4k7
2726	N07	DDC143TK	Dio	DN	SOT26	dual dtr npn 50V 0.1A R1 4k7
2727	N08	DDTC143EE	Dio	N	SOT523	dtr npn 50V 0.1A 4k7/4k7 0.15W
2728	N08	DDTC143EUA	Dio	N	SOT323	dtr npn 50V 0.1A 4k7/4k7 0.2W
2729	N08	DDTC143ECA	Dio	N	SOT23	dtr npn 50V 0.1A 4k7/4k7 0.2W
2730	N08	DDTC143EKA	Dio	N	SC59	dtr npn 50V 0.1A 4k7/4k7 0.2W
2731	N08	SO930	SGS	N		2N930
2732	N09	DDTC123XE	Dio	N	SOT523	dtr npn 50V 0.1A res 4k7/10k 0.15W
2733	N09	DDTC123XUA	Dio	N	SOT323	dtr npn 50V 0.1A res 4k7/10k 0.2W
2734	N09	DDTC123XCA	Dio	N	SOT23	dtr npn 50V 0.1A res 4k7/10k 0.2W
2735	N09	DDTC123XKA	Dio	N	SC59	dtr npn 50V 0.1A res 4k7/10k 0.2W
2736	N1	MMBT100	Nat	N		nnp gp sw 500mA
2737	N1	MMBF201N	Mot	M	SOT23	n-ch tmosfet 20V 0.3A Id
2738	N1	MRF571	Mot	N	SOT416	8 GHz 40mA npn RF
2739	N1	TN0201T	Tem	M	SOT23	n-ch mosfet 0.3A Id 0.2W
2740	N10	SO918	SGS	N		2N918
2741	N10	DDTC143FE	Dio	N	SOT523	dtr npn 50V 0.1A 4k7/22k 0.15W
2742	N10	DDTC143FUA	Dio	N	SOT323	dtr npn 50V 0.1A 4k7/22k 0.2W
2743	N10	DDTC143FCA	Dio	N	SOT23	dtr npn 50V 0.1A 4k7/22k 0.2W
2744	N10	DDTC143FKA	Dio	N	SC59	dtr npn 50V 0.1A 4k7/22k 0.2W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2745	N11	DDTC143ZE	Dio	N	SOT523	dtr npn 50V 0.1A 4k7/47k 0.15W
2746	N11	DDTC143ZUA	Dio	N	SOT323	dtr npn 50V 0.1A 4k7/47k 0.2W
2747	N11	DDTC143ZCA	Dio	N	SOT23	dtr npn 50V 0.1A 4k7/47k 0.2W
2748	N11	DDTC143ZKA	Dio	N	SC59	dtr npn 50V 0.1A 4k7/47k 0.2W
2749	N11	SO2369	SGS	N		2N2369
2750	N12	SO2221	SGS	N		2N2221
2751	N12	DDTC114TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 10k 0.15W
2752	N12	DDTC114TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 10k 0.2W
2753	N12	DDTC114TCA	Dio	N	SOT23	dtr npn 50V 0.1A R110k 0.2W
2754	N12	DDTC114TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 10k 0.2W
2755	N12	DDC114TU	Dio	DN	SOT363	dual dtr npn 50V 0.1A R1 10k
2756	N12	DDC114TK	Dio	DN	SOT26	dual dtr npn 50V 0.1A R1 10k
2757	N13	DDTC114EE	Dio	N	SOT523	dtr npn 50V 0.1A 10k/10k 0.15W
2758	N13	DDTC114EUA	Dio	N	SOT323	dtr npn 50V 0.1A 10k/10k 0.2W
2759	N13	DDTC114ECA	Dio	N	SOT23	dtr npn 50V 0.1A 10k/10k 0.2W
2760	N13	DDTC114EKA	Dio	N	SC59	dtr npn 50V 0.1A 10k/10k 0.2W
2761	N13	DDC114EU	Dio	DN	SOT363	dual dtr npn 50V 0.1A 10k/10k
2762	N13	DDC114EK	Dio	DN	SOT26	dual dtr npn 50V 0.1A 10k/10k
2763	N13	SO2222	SGS	N		2N2222
2764	N14	DDTC114YE	Dio	N	SOT523	dtr npn 50V 0.1A 10k/47k 0.15W
2765	N14	DDTC114YUA	Dio	N	SOT323	dtr npn 50V 0.1A 10k/47k 0.2W
2766	N14	DDTC114YCA	Dio	N	SOT23	dtr npn 50V 0.1A 10k/47k 0.2W
2767	N14	DDTC114YKA	Dio	N	SC59	dtr npn 50V 0.1A 10k/47k 0.2W
2768	N14	DDC114YU	Dio	DN	SOT363	dual dtr npn 50V 0.1A 10k/47k
2769	N14	DDC114YK	Dio	DN	SOT26	dual dtr npn 50V 0.1A 10k/47k
2770	N15	DDTC114WE	Dio	N	SOT523	dtr npn 50V 0.1A 10k/47k 0.15W
2771	N15	DDTC114WUA	Dio	N	SOT323	dtr npn 50V 0.1A 10k/47k 0.2W
2772	N15	DDTC114WCA	Dio	N	SOT23	dtr npn 50V 0.1A 10k/47k 0.2W
2773	N15	DDTC114WKA	Dio	N	SC59	dtr npn 50V 0.1A 10k/47k 0.2W
2774	N16	DDTC124TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 22k 0.15W
2775	N16	DDTC124TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 22k 0.2W
2776	N16	DDTC124TCA	Dio	N	SOT23	dtr npn 50V 0.1A R1 22k 0.2W
2777	N16	DDTC124TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 22k 0.2W
2778	N17	DDTC124EE	Dio	DN	SOT523	dtr npn 50V 0.1A 22k/22k 0.15W
2779	N17	DDTC124EUA	Dio	DN	SOT323	dtr npn 50V 0.1A 22k/22k 0.2W
2780	N17	DDTC124ECA	Dio	DN	SOT23	dtr npn 50V 0.1A 22k/22k 0.2W
2781	N17	DDTC124EKA	Dio	DN	SC59	dtr npn 50V 0.1A 22k/22k 0.2W
2782	N17	DDC124EU	Dio	DN	SOT363	dual dtr npn 50V 0.1A 22k/22k
2783	N17	DDC124EK	Dio	DN	SOT26	dual dtr npn 50V 0.1A 22k/22k
2784	N18	SO1711	SGS	N		2N1711
2785	N18	DDTC124XE	Dio	N	SOT523	dtr npn 50V 0.1A 22k/47k 0.15W
2786	N18	DDTC124XUA	Dio	N	SOT323	dtr npn 50V 0.1A 22k/47k 0.2W
2787	N18	DDTC124XCA	Dio	N	SOT23	dtr npn 50V 0.1A 22k/47k 0.2W
2788	N18	DDTC124XKA	Dio	N	SC59	dtr npn 50V 0.1A 22k/47k 0.2W
2789	N19	DDTC144TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 47k 0.15W
2790	N19	DDTC144TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 47k 0.2W
2791	N19	DDTC144TCA	Dio	N	SOT23	dtr npn 50V 0.1A R1 47k 0.2W
2792	N19	DDTC144TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 47k 0.2W
2793	N2	MGSF1N02LT1	Mot	M	SOT23	n-ch mosfet, 20V 85mA

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2794	N2	MMBC1653N2	Mot	N		npn 130V 50mA hfe 50-130
2795	N2	BFS520	Phi	N	SOT323	npn RF 9GHz 70mA
2796	N20	DDTC124EE	Dio	N	SOT523	dtr npn 50V 0.1A 22k/22k 0.15W
2797	N20	DDTC124EUA	Dio	N	SOT323	dtr npn 50V 0.1A 22k/22k 0.2W
2798	N20	DDTC124ECA	Dio	N	SOT23	dtr npn 50V 0.1A 22k/22k 0.2W
2799	N20	DDTC124EKA	Dio	N	SC59	dtr npn 50V 0.1A 22k/22k 0.2W
2800	N20	DDC144EU	Dio	DN	SOT363	dual dtr npn 50V 0.1A 47k/47k
2801	N20	DDC144EK	Dio	DN	SOT26	dual dtr npn 50V 0.1A 47k/47k
2802	N20	SO2222A	SGS	N		2N2222A
2803	N21	DDTC144VE	Dio	N	SOT523	dtr npn 50V 0.1A 47k/10k 0.15W
2804	N21	DDTC144VUA	Dio	N	SOT323	dtr npn 50V 0.1A 47k/10k 0.2W
2805	N21	DDTC144VCA	Dio	N	SOT23	dtr npn 50V 0.1A 47k/10k 0.2W
2806	N21	DDTC144VKA	Dio	N	SC59	dtr npn 50V 0.1A 47k/10k 0.2W
2807	N22	DDTC144WE	Dio	N	SOT523	dtr npn 50V 0.1A 47k/22k 0.15W
2808	N22	DDTC144WUA	Dio	N	SOT323	dtr npn 50V 0.1A 47k/22k 0.2W
2809	N22	DDTC144WCA	Dio	N	SOT23	dtr npn 50V 0.1A 47k/22k 0.2W
2810	N22	DDTC144WKA	Dio	N	SC59	dtr npn 50V 0.1A 47k/22k 0.2W
2811	N23	DDTC115TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 100k 0.15W
2812	N23	DDTC115TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 100k 0.2W
2813	N23	DDTC115TCA	Dio	N	SOT23	dtr npn 50V 0.1A R1 100k 0.2W
2814	N23	DDTC115TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 100k 0.2W
2815	N24	DDTC115EE	Dio	N	SOT523	dtr npn 50V 0.1A 100k/100k 0.15W
2816	N24	DDTC115EUA	Dio	N	SOT323	dtr npn 50V 0.1A 100k/100k 0.2W
2817	N24	DDTC115ECA	Dio	N	SOT23	dtr npn 50V 0.1A 100k/100k 0.2W
2818	N24	DDTC115EKA	Dio	N	SC59	dtr npn 50V 0.1A 100k/100k 0.2W
2819	N25	DDTC125TE	Dio	N	SOT523	dtr npn 50V 0.1A R1 200k 0.15W
2820	N25	DDTC125TUA	Dio	N	SOT323	dtr npn 50V 0.1A R1 200k 0.2W
2821	N25	DDTC125TCA	Dio	N	SOT23	dtr npn 50V 0.1A R1 200k 0.2W
2822	N25	DDTC125TKA	Dio	N	SC59	dtr npn 50V 0.1A R1 200k 0.2W
2823	N26	DDTC114GE	Dio	N	SOT523	dtr npn 50V 0.1A R2 10k 0.15W
2824	N26	DDTC114GUA	Dio	N	SOT323	dtr npn 50V 0.1A R2 10k 0.2W
2825	N26	DDTC114GCA	Dio	N	SOT23	dtr npn 50V 0.1A R2 10k 0.2W
2826	N26	DDTC114GKA	Dio	N	SC59	dtr npn 50V 0.1A R2 10k 0.2W
2827	N27	SO1893	SGS	N		2N1893
2828	N27	DDTC124GE	Dio	N	SOT523	dtr npn 50V 0.1A R2 22k 0.15W
2829	N27	DDTC124GUA	Dio	N	SOT323	dtr npn 50V 0.1A R2 22k 0.2W
2830	N27	DDTC124GCA	Dio	N	SOT23	dtr npn 50V 0.1A R2 22k 0.2W
2831	N27	DDTC124GKA	Dio	N	SC59	dtr npn 50V 0.1A R2 22k 0.2W
2832	N28	BFR520	Phi	N	SOT23	npn RF 9GHz 70mA
2833	N28	DDTC144GE	Dio	N	SOT523	dtr npn 50V 0.1A R2 47k 0.15W
2834	N28	DDTC144GUA	Dio	N	SOT323	dtr npn 50V 0.1A R2 47k 0.2W
2835	N28	DDTC144GCA	Dio	N	SOT23	dtr npn 50V 0.1A R2 47k 0.2W
2836	N28	DDTC144GKA	Dio	N	SC59	dtr npn 50V 0.1A R2 47k 0.2W
2837	N29	BFR540	Phi	N	SOT23	npn RF 9GHz 120mA
2838	N29	DDTC115GE	Dio	N	SOT523	dtr npn 50V 0.1A R2 100k 0.15W
2839	N29	DDTC115GUA	Dio	N	SOT323	dtr npn 50V 0.1A R2 100k 0.2W
2840	N29	DDTC115GCA	Dio	N	SOT23	dtr npn 50V 0.1A R2 100k 0.2W
2841	N29	DDTC115GKA	Dio	N	SC59	dtr npn 50V 0.1A R2 100k 0.2W
2842	N3	MMBC1653N3	Mot	N		npn 130V 50mA hfe 100-220

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2843	N3	MGSF1N03L	Mot	M	SOT23	n-ch TMOS mosfet 30V 0.75A
2844	N30	BFR505	Phi	N	SOT23	npn RF 9GHz 15V 18mA
2845	N33	BFG505	Phi	TQ	SOT143	npn RF 9GHz 15V 18mA
2846	N36	BFG520	Phi	X	SOT143	npn RF 9GHz 70mA
2847	N37	BFG540	Phi	X	SOT143	npn RF 9GHz 120mA
2848	N38	BFG590	Phi	TQ	SOT143	npn RF 5GHz 15V 0.2A
2849	N39	BFG505X	Phi	X		npn RF 9GHz 15V 18mA
2850	N4	MMBC1653N4	Mot	N		npn 130V 50mA hfe 150-330
2851	N44	BFG590X	Phi	X		npn RF 5GHz 15V 0.2A
2852	N5	MMBC1654N5	Mot	N		npn 160V 50mA hfe 50-130
2853	N54	SO2221A	SGS	N		2N2221A
2854	N6	MMBC1653N6	Mot	N		npn 160V 50mA hfe 100-220
2855	N6	BFS25A	Phi	N	SOT323	npn RF 5GHz 6.5mA 32 mW
2856	N7	MMBC1653N7	Mot	N		npn 160V 50mA hfe 150-330
2857	N70	BFG10	Phi	TQ	SOT143	npn 8V 250mA 1.8GHz pwr amp
2858	N71	SO3904	SGS	N		2N3904
2859	N71	BFG10X	Phi	X		8V 250mA 1.8GHz pwr amp
2860	N72	BFG11	Phi	TQ	SOT143	8V 400mA 1.8GHz pwr amp
2861	N72	SO3903	SGS	N		2N3903
2862	N73	BFG11X	Phi	X		8V 400mA 1.8GHz pwr amp
2863	N79	SO5550	SGS	N		2N5550
2864	N80	SO5551	SGS	N		2N5551
2865	N81	SO2369A	SGS	N		2N2369A
2866	N9	DAN222	Mot	B	SOT416	dual cc si diode
2867	N91	SO642	SGS	N		npn Vce 300V
2868	N94	SO517	SGS	N		npn darlington
2869	NA	CFY35-20	Sie	DM		10GHz GaAsfet
2870	NA	BF1105WR	Phi	UQ	SOT343R	uhf n-ch dg mosfet
2871	NAp	BF1105R	Phi	UQ	SOT143R	uhf n-ch dg mosfet
2872	NB	BF1109WR	Phi	UQ	SOT343R	uhf n-ch dg mosfet
2873	NB	CFY35-23	Sie	DM		10GHz GaAsfet
2874	NBp	BF1109R	Phi	UQ	SOT143R	uhf n-ch dg mosfet
2875	NEp	BF1105	Phi	UQ	SOT143	uhf n-ch dg mosfet
2876	NFp	BF1109	Phi	UQ	SOT143	uhf n-ch dg mosfet
2877	NY	BF1012s	Sie	W		n-ch dg mosfet 1GHz 12V
2878	NZ	MGSF1N02L	Mot	M		n-ch TMOS FET
2879	O (white)	BAT14-03W	Sie	I	SOD323	RF Schottky 4V 90mA
2880	O05	SO2484R	SGS	R		2N2484
2881	O08	SO930R	SGS	R		2N930
2882	O10	SO918R	SGS	R		2N918
2883	O12	SO2221R	SGS	R		2N2221
2884	O13	SO2222R	SGS	R		2N2222
2885	O2	BST82	Phi	M	SOT23	n-ch mosfet 80V 175mA
2886	O20	SO2222AR	SGS	R		2N2222A
2887	O27	SO1893R	SGS	R		2N1893
2888	O54	SO2221AR	SGS	R		2N2221A
2889	O79	SO5550R	SGS	R		2N5550
2890	O80	SO5551R	SGS	R		2N5551
2891	O91	SO642R	SGS	R		npn Vce 300V

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2892	P	KV1841E	Tok	I	URD	uhf varicap 7-15pF
2893	P	DAP202K	Roh	A		80V 100mA dual
2894	P (white)	BAT15-03W	Sie	I	SOD323	RF Schottky 4V 100mA
2895	P0	BFP90A	Phi	CX	SOT173	BFG90A
2896	P0	TP0101T	Tem	M	SOT23	p-ch mosfet 0.5A 12V
2897	P0	HSMS-285B	HP	C	SOT323	zero-bias schottky diode uW det
2898	P0	HSMS-2850	HP	C	SOT23	zero-bias schottky diode uW det
2899	p01	PDTA143ET	Phi	N	SOT23	pnp dtr 4k7+4k7
2900	P01	SO2906	SGS	N		2N2906
2901	P01	SST201	Sil	F	SOT23	J201 n-ch fet
2902	P01	DDTA113TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 1k0 0.15W
2903	P01	DDTA113TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 1k0 0.2W
2904	P01	DDTA113TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R11k0 0.2W
2905	P01	DDTA113TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 1k0 0.2W
2906	p02	PDTC143ET	Phi	N	SOT23	nnp 4k7+4k7 bias res
2907	P02	SST202	Sil	F	SOT23	J202 n-ch fet
2908	P02	DDTA113ZE	Dio	N	SOT523	dtr pnp 50V 0.1A res 1k0/10k 0.15W
2909	P02	DDTA113ZUA	Dio	N	SOT323	dtr pnp 50V 0.1A res 1k0/10k 0.2W
2910	P02	DDTA113ZCA	Dio	N	SOT23	dtr pnp 50V 0.1A res 1k0/10k 0.2W
2911	P02	DDTA113ZKA	Dio	N	SC59	dtr pnp 50V 0.1A res 1k0/10k 0.2W
2912	P03	SO2907A	SGS	N		2N2907A
2913	P03	SST203	Sil	F	SOT23	J203 n-ch fet
2914	P03	DDTA123TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 2k2 0.15W
2915	P03	DDTA123TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 2k2 0.2W
2916	P03	DDTA123TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R1 2k2 0.2W
2917	P03	DDTA123TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 2k2 0.2W
2918	P04	SST204	Sil	F	SOT23	J204 n-ch fet
2919	P04	DDTA123EE	Dio	N	SOT523	dtr pnp 50V 0.1A res 2k2/2k2 0.15W
2920	P04	DDTA123EUA	Dio	N	SOT323	dtr pnp 50V 0.1A res 2k2/2k2 0.2W
2921	P04	DDTA123ECA	Dio	N	SOT23	dtr pnp 50V 0.1A res 2k2/2k2 0.2W
2922	P04	DDTA123EKA	Dio	N	SC59	dtr pnp 50V 0.1A res 2k2/2k2 0.2W
2923	P05	SO2907	SGS	N		2N2907
2924	P05	DDTA123YE	Dio	N	SOT523	dtr pnp 50V 0.1A res 2k2/10k 0.15W
2925	P05	DDTA123YUA	Dio	N	SOT323	dtr pnp 50V 0.1A res 2k2/10k 0.2W
2926	P05	DDTA123YCA	Dio	N	SOT23	dtr pnp 50V 0.1A res 2k2/10k 0.2W
2927	P05	DDTA123YKA	Dio	N	SC59	dtr pnp 50V 0.1A res 2k2/10k 0.2W
2928	P06	SO2894	SGS	N		2N2894
2929	P06	DDTA123JE	Dio	N	SOT523	dtr pnp50V 0.1A res 2k2/47k 0.15W
2930	P06	DDTA123JUA	Dio	N	SOT323	dtr pnp 50V 0.1A res 2k2/47k 0.2W
2931	P06	DDTA123JCA	Dio	N	SOT23	dtr pnp 50V 0.1A res 2k2/47k 0.2W
2932	P06	DDTA123JKA	Dio	N	SC59	dtr pnp 50V 0.1A res 2k2/47k 0.2W
2933	P06	DDA123JU	Dio	DO	SOT363	dual dtr pnp 50V 0.1A 2k2/47k
2934	P06	DDA123JK	Dio	DO	SOT26	dual dtr pnp 50V 0.1A 2k2/47k
2935	P07	DDTA143TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 4k7 0.15W
2936	P07	DDTA143TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 4k7 0.2W
2937	P07	DDTA143TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R1 4k7 0.2W
2938	P07	DDTA143TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 4k7 0.2W
2939	P07	DDA143TU	Dio	DO	SOT363	dual dtr pnp 50V 0.1A R1 4k7
2940	P07	DDA143TK	Dio	DO	SOT26	dual dtr pnp 50V 0.1A R1 4k7

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2941	p08	PMBFJ108	Phi	F	SOT23	n-ch jfet J108
2942	P08	DDTA143EE	Dio	N	SOT523	dtr pnp 50V 0.1A 4k7/4k7 0.15W
2943	P08	DDTA143EUA	Dio	N	SOT323	dtr pnp 50V 0.1A 4k7/4k7 0.2W
2944	P08	DDTA143ECA	Dio	N	SOT23	dtr pnp 50V 0.1A 4k7/4k7 0.2W
2945	P08	DDTA143EKA	Dio	N	SC59	dtr pnp 50V 0.1A 4k7/4k7 0.2W
2946	p09	PMBFJ109	Phi	F	SOT23	n-ch jfet J109
2947	P09	DDTA123XE	Dio	N	SOT523	dtr pnp 50V 0.1A res 4k7/10k 0.15W
2948	P09	DDTA123XUA	Dio	N	SOT323	dtr pnp 50V 0.1A res 4k7/10k 0.2W
2949	P09	DDTA123XCA	Dio	N	SOT23	dtr pnp 50V 0.1A res 4k7/10k 0.2W
2950	P09	DDTA123XKA	Dio	N	SC59	dtr pnp 50V 0.1A res 4k7/10k 0.2W
2951	P1	BB131	Phi	I	SOD 323	VHF Varicap 1-15pF
2952	P1	BFP91A	Phi	CX	SOT173	BFG91A
2953	P1	SST201	Tem	F	SOT23	J201 n-ch jfet
2954	P1	BFR92	Phi	N	SOT23	BFR90
2955	p10	PMBFJ110	Phi	F	SOT23	n-ch jfet J110
2956	P10	DDTA143FE	Dio	N	SOT523	dtr pnp 50V 0.1A 4k7/22k 0.15W
2957	P10	DDTA143FUA	Dio	N	SOT323	dtr pnp 50V 0.1A 4k7/22k 0.2W
2958	P10	DDTA143FCA	Dio	N	SOT23	dtr pnp 50V 0.1A 4k7/22k 0.2W
2959	P10	DDTA143FKA	Dio	N	SC59	dtr pnp 50V 0.1A 4k7/22k 0.2W
2960	p11	PDTA114TT	Phi	N	SOT23	pnp dtr
2961	p11	PMBFJ111	Phi	F	SOT23	n-ch jfet J111
2962	P11	DDTA143ZE	Dio	N	SOT523	dtr pnp 50V 0.1A 4k7/47k 0.15W
2963	P11	DDTA143ZUA	Dio	N	SOT323	dtr pnp 50V 0.1A 4k7/47k 0.2W
2964	P11	DDTA143ZCA	Dio	N	SOT23	dtr pnp 50V 0.1A 4k7/47k 0.2W
2965	P11	DDTA143ZKA	Dio	N	SC59	dtr pnp 50V 0.1A 4k7/47k 0.2W
2966	p12	PDTC114TT	Phi	N	SOT23	nnp dtr
2967	p12	PMBFJ112	Phi	F	SOT23	n-ch jfet J112
2968	P12	SO2906A	SGS	N		2N2906A
2969	P12	DDTA114TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 10k 0.15W
2970	P12	DDTA114TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 10k 0.2W
2971	P12	DDTA114TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R110k 0.2W
2972	P12	DDTA114TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 10k 0.2W
2973	P12	DDA114TU	Dio	DO	SOT363	dual dtr pnp 50V 0.1A R1 10k
2974	P12	DDA114TK	Dio	DO	SOT26	dual dtr pnp 50V 0.1A R1 10k
2975	p13	PMBFJ113	Phi	F	SOT23	n-ch jfet J113
2976	P13	DDTA114EE	Dio	N	SOT523	dtr pnp 50V 0.1A 10k/10k 0.15W
2977	P13	DDTA114EUA	Dio	N	SOT323	dtr pnp 50V 0.1A 10k/10k 0.2W
2978	P13	DDTA114ECA	Dio	N	SOT23	dtr pnp 50V 0.1A 10k/10k 0.2W
2979	P13	DDTA114EKA	Dio	N	SC59	dtr pnp 50V 0.1A 10k/10k 0.2W
2980	P13	DDA114EU	Dio	DO	SOT363	dual dtr pnp 50V 0.1A 10k/10k
2981	P13	DDA114EK	Dio	DO	SOT26	dual dtr pnp 50V 0.1A 10k/10k
2982	P14	DDTA114YE	Dio	N	SOT523	dtr pnp 50V 0.1A 10k/47k 0.15W
2983	P14	DDTA114YUA	Dio	N	SOT323	dtr pnp 50V 0.1A 10k/47k 0.2W
2984	P14	DDTA114YCA	Dio	N	SOT23	dtr pnp 50V 0.1A 10k/47k 0.2W
2985	P14	DDTA114YKA	Dio	N	SC59	dtr pnp 50V 0.1A 10k/47k 0.2W
2986	P14	DDA114YU	Dio	DO	SOT363	dual dtr pnp 50V 0.1A 10k/47k
2987	P14	DDA114YK	Dio	DO	SOT26	dual dtr pnp 50V 0.1A 10k/47k
2988	P15	DDTA114WE	Dio	N	SOT523	dtr pnp 50V 0.1A 10k/47k 0.15W
2989	P15	DDTA114WUA	Dio	N	SOT323	dtr pnp 50V 0.1A 10k/47k 0.2W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
2990	P15	DDTA114WCA	Dio	N	SOT23	dtr pnp 50V 0.1A 10k/47k 0.2W
2991	P15	DDTA114WKA	Dio	N	SC59	dtr pnp 50V 0.1A 10k/47k 0.2W
2992	p16	PDTC114ET	Phi	N	SOT23	npn dtr
2993	P16	DDTA124TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 22k 0.15W
2994	P16	DDTA124TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 22k 0.2W
2995	P16	DDTA124TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R1 22k 0.2W
2996	P16	DDTA124TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 22k 0.2W
2997	p17	PDTC124ET	Phi	N	SOT23	npn dtr
2998	P17	DDTA124EE	Dio	DO	SOT523	dtr pnp 50V 0.1A 22k/22k 0.15W
2999	P17	DDTA124EUA	Dio	DO	SOT323	dtr pnp 50V 0.1A 22k/22k 0.2W
3000	P17	DDTA124ECA	Dio	DO	SOT23	dtr pnp 50V 0.1A 22k/22k 0.2W
3001	P17	DDTA124EKA	Dio	DO	SC59	dtr pnp 50V 0.1A 22k/22k 0.2w
3002	P17	DDC124EU	Dio	DO	SOT363	dual dtr pnp 50V 0.1A 22k/22k
3003	P17	DDC124EK	Dio	DO	SOT26	dual dtr pnp 50V 0.1A 22k/22k
3004	p18	PDTC143ZT	Phi	N	SOT23	npn dtr 4k7+47k
3005	P18	DDTA124XE	Dio	N	SOT523	dtr pnp 50V 0.1A 22k/47k 0.15W
3006	P18	DDTA124XUA	Dio	N	SOT323	dtr pnp 50V 0.1A 22k/47k 0.2W
3007	P18	DDTA124XCA	Dio	N	SOT23	dtr pnp 50V 0.1A 22k/47k 0.2W
3008	P18	DDTA124XKA	Dio	N	SC59	dtr pnp 50V 0.1A 22k/47k 0.2W
3009	p19	PDTA143ZT	Phi	N	SOT23	pnp dtr 4k7+47k
3010	P19	DDTA144TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 47k 0.15W
3011	P19	DDTA144TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 47k 0.2W
3012	P19	DDTA144TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R1 47k 0.2W
3013	P19	DDTA144TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 47k 0.2W
3014	p1A	PMMT3904	Phi	N	SOT23	2N3904
3015	p1A	PXT3904	Phi	N	SOT89	2N3904
3016	p1B	PMBT2222	Phi	N	SOT23	2N2222
3017	p1D	PMBTA42	Phi	N	SOT23	MPSA42 300V npn
3018	p1D	PXTA42	Phi	N	SOT89	MPSA42 300V npn
3019	P1D	PZTA42	Mot	P		MPSA42 10mA 300V npn
3020	P1D	PZTA42	Mot	P		MPSA42 300V npn
3021	p1F	PMBT5550	Phi	N	SOT23	2N5550 140V npn
3022	P1F	PZT2222A	Mot	P		2N2222A sw npn
3023	p1G	PMMTA06	Phi	N	SOT23	MPSA06
3024	p1J	PMBT2369	Phi	N	SOT23	2N2369
3025	p1K	PMBT6428	Phi	N	SOT23	MPSA18 50V
3026	p1L	PMBT6429	Phi	N	SOT23	MPSA18 45V
3027	p1M	PXTA13	Phi	N	SOT89	MPSA13 darlington
3028	p1M	PMBTA13	Phi	N	SOT23	MPSA13 darlington
3029	p1N	PMBTA14	Mot	N	SOT23	MPSA14 darlington
3030	p1N	PXTA14	Mot	N	SOT89	MPSA14 darlington
3031	P1N	PZTA14	Mot	P		MPSA14 darlington
3032	P1N	PZTA14	Mot	P		npn darlington MPSA14
3033	p1P	PMBT2222A	Phi	N	SOT23	2N2222A
3034	p1P	PXT2222A	Phi	N	SOT89	2N2222A
3035	p1Q	PMBT5088	Phi	N	SOT23	MPSA18 Vce 30V
3036	P2	BB132	Phi	I	SOD 323	VHF Varicap 2,5-28,8pF
3037	P2	BFR92A	Phi	N	SOT23	BFR90A
3038	P2	HSMSM-285C	HP	D	SOT323	dual series HSMS-285B

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3039	P2	HSMS-2852	HP	D	SOT23	dual series HSMS-285B
3040	P20	DDTA124EE	Dio	N	SOT523	dtr pnp 50V 0.1A 22k/22k 0.15W
3041	P20	DDTA124EUA	Dio	N	SOT323	dtr pnp 50V 0.1A 22k/22k 0.2W
3042	P20	DDTA124ECA	Dio	N	SOT23	dtr pnp 50V 0.1A 22k/22k 0.2W
3043	P20	DDTA124EKA	Dio	N	SC59	dtr pnp 50V 0.1A 22k/22k 0.2W
3044	P20	DDA144EU	Dio	DO	SOT363	dual dtr pnp 50V 0.1A 47k/47k
3045	P20	DDA144EK	Dio	DO	SOT26	dual dtr pnp 50V 0.1A 47k/47k
3046	P21	DDTA144VE	Dio	N	SOT523	dtr pnp 50V 0.1A 47k/10k 0.15W
3047	P21	DDTA144VUA	Dio	N	SOT323	dtr pnp 50V 0.1A 47k/10k 0.2W
3048	P21	DDTA144VCA	Dio	N	SOT23	dtr pnp 50V 0.1A 47k/10k 0.2W
3049	P21	DDTA144VKA	Dio	N	SC59	dtr pnp 50V 0.1A 47k/10k 0.2W
3050	P22	DDTA144WE	Dio	N	SOT523	dtr pnp 50V 0.1A 47k/22k 0.15W
3051	P22	DDTA144WUA	Dio	N	SOT323	dtr pnp 50V 0.1A 47k/22k 0.2W
3052	P22	DDTA144WCA	Dio	N	SOT23	dtr pnp 50V 0.1A 47k/22k 0.2W
3053	P22	DDTA144WKA	Dio	N	SC59	dtr pnp 50V 0.1A 47k/22k 0.2W
3054	P23	DDTA115TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 100k 0.15W
3055	P23	DDTA115TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 100k 0.2W
3056	P23	DDTA115TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R1 100k 0.2W
3057	P23	DDTA115TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 100k 0.2W
3058	P24	DDTA115EE	Dio	N	SOT523	dtr pnp 50V 0.1A 100k/100k 0.15W
3059	P24	DDTA115EUA	Dio	N	SOT323	dtr pnp 50V 0.1A 100k/100k 0.2W
3060	P24	DDTA115ECA	Dio	N	SOT23	dtr pnp 50V 0.1A 100k/100k 0.2W
3061	P24	DDTA115EKA	Dio	N	SC59	dtr pnp 50V 0.1A 100k/100k 0.2W
3062	P25	DDTA125TE	Dio	N	SOT523	dtr pnp 50V 0.1A R1 200k 0.15W
3063	P25	DDTA125TUA	Dio	N	SOT323	dtr pnp 50V 0.1A R1 200k 0.2W
3064	P25	DDTA125TCA	Dio	N	SOT23	dtr pnp 50V 0.1A R1 200k 0.2W
3065	P25	DDTA125TKA	Dio	N	SC59	dtr pnp 50V 0.1A R1 200k 0.2W
3066	P25	SO3906	SGS	N		2N3906
3067	P26	SO3905	SGS	N		2N3905
3068	P26	DDTA114GE	Dio	N	SOT523	dtr pnp 50V 0.1A R2 10k 0.15W
3069	P26	DDTA114GUA	Dio	N	SOT323	dtr pnp 50V 0.1A R2 10k 0.2W
3070	P26	DDTA114GCA	Dio	N	SOT23	dtr pnp 50V 0.1A R2 10k 0.2W
3071	P26	DDTA114GKA	Dio	N	SC59	dtr pnp 50V 0.1A R2 10k 0.2W
3072	P27	DDTA124GE	Dio	N	SOT523	dtr pnp 50V 0.1A R2 22k 0.15W
3073	P27	DDTA124GUA	Dio	N	SOT323	dtr pnp 50V 0.1A R2 22k 0.2W
3074	P27	DDTA124GCA	Dio	N	SOT23	dtr pnp 50V 0.1A R2 22k 0.2W
3075	P27	DDTA124GKA	Dio	N	SC59	dtr pnp 50V 0.1A R2 22k 0.2W
3076	P28	DDTA144GE	Dio	N	SOT523	dtr pnp 50V 0.1A R2 47k 0.15W
3077	P28	DDTA144GUA	Dio	N	SOT323	dtr pnp 50V 0.1A R2 47k 0.2W
3078	P28	DDTA144GCA	Dio	N	SOT23	dtr pnp 50V 0.1A R2 47k 0.2W
3079	P28	DDTA144GKA	Dio	N	SC59	dtr pnp 50V 0.1A R2 47k 0.2W
3080	P29	DDTA115GE	Dio	N	SOT523	dtr pnp 50V 0.1A R2 100k 0.15W
3081	P29	DDTA115GUA	Dio	N	SOT323	dtr pnp 50V 0.1A R2 100k 0.2W
3082	P29	DDTA115GCA	Dio	N	SOT23	dtr pnp 50V 0.1A R2 100k 0.2W
3083	P29	DDTA115GKA	Dio	N	SC59	dtr pnp 50V 0.1A R2 100k 0.2W
3084	p2A	PMBT3906	Phi	N	SOT23	2N3906
3085	p2A	PXT3906	Phi	O	SOT89	2N3906
3086	p2B	PMBT2907	Phi	N	SOT23	2N2907
3087	p2D	PMBTA92	Phi	N	SOT23	MPSA92 pnp Vce 300V

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3088	p2D	PXTA92	Phi	O	SOT89	MPSA92 pnp Vce 300V
3089	P2D	PZTA92	Mot	P		MPSA92 300V pnp
3090	p2F	PMBT2907A	Phi	N	SOT23	2N2907A
3091	p2F	PXT2907A	Phi	O	SOT89	2N2907A
3092	P2F	PZT2907A	Mot	P		2N2907A sw pnp
3093	p2G	PMBTA56	Phi	N	SOT23	MPSA56
3094	p2L	PMBT5401	Phi	N	SOT23	2N5401 pnp 150V
3095	P2p	BFR92AW	Phi	N	SOT323	BFR90A
3096	p2T	PMBT4403	Phi	N	SOT23	2N4403
3097	p2T	PXT4403	Phi	O	SOT89	2N4403
3098	p2V	PXTA64	Phi	O	SOT89	MPSA64 darlington
3099	P2V	PZTA64	Mot	P		MPSA64 darlington
3100	p2X	PMBT4401	Phi	N	SOT23	2N4401
3101	p2X	PxT4401	Phi	O	SOT89	2N4401
3102	P3	BB133	Phi	I	SOD 323	VHF Varicap 2,5-18,5pF
3103	P3	MMBF2202P	Mot	M	SOT23	p-ch TMOSfet 0.3A 20V
3104	P3	TP0202T	Tem	M		p-ch mosfet 0.3A 20V
3105	p31	PDTA143XT	Phi	N	SOT23	pnp dtr 4k7+10k
3106	p32	PDTC143XT	Phi	N	SOT23	pnp dtr 4k7+10k
3107	P32	SO5400	SGS	N		2N5400
3108	P33	SO5401	SGS	N		2N5401
3109	P38	SST4338	Sil	F	SOT23	2N4338
3110	P39	SST4339	Sil	F		2N4339
3111	P39	SO692	SGS			pnp Vce 300V
3112	P4	BFR92R	Phi	R	SOT23R	BFR90
3113	P4	BB134	Phi	I	SOD 323	UHF Varicap 2-12pF
3114	P40	SST4340	Sil	F	SOT23	2N4340
3115	P41	SST4341	Sil	F	SOT23	2N4341
3116	P5	BB135	Phi	I	SOD 323	UHF Varicap 2-12pF
3117	P5	BFR92AR	Phi	R	SOT23R	BFR90A
3118	P5	FMMT2369A	Zet	N		2N2369A
3119	P5	HSMSM-2855	HP	S	SOT143	separate pair HSMS-2850
3120	P57	SST5457	Sil	F	SOT23	2N5457
3091	p2F	PXT2907A	Phi	O	SOT89	2N2907A
3092	P2F	PZT2907A	Mot	P		2N2907A sw pnp
3093	p2G	PMBTA56	Phi	N	SOT23	MPSA56
3094	p2L	PMBT5401	Phi	N	SOT23	2N5401 pnp 150V
3095	P2p	BFR92AW	Phi	N	SOT323	BFR90A
3096	p2T	PMBT4403	Phi	N	SOT23	2N4403
3097	p2T	PXT4403	Phi	O	SOT89	2N4403
3098	p2V	PXTA64	Phi	O	SOT89	MPSA64 darlington
3099	P2V	PZTA64	Mot	P		MPSA64 darlington
3100	p2X	PMBT4401	Phi	N	SOT23	2N4401
3101	p2X	PxT4401	Phi	O	SOT89	2N4401
3102	P3	BB133	Phi	I	SOD 323	VHF Varicap 2,5-18,5pF
3103	P3	MMBF2202P	Mot	M	SOT23	p-ch TMOSfet 0.3A 20V
3104	P3	TP0202T	Tem	M		p-ch mosfet 0.3A 20V
3105	p31	PDTA143XT	Phi	N	SOT23	pnp dtr 4k7+10k
3106	p32	PDTC143XT	Phi	N	SOT23	pnp dtr 4k7+10k

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3107	P32	SO5400	SGS	N		2N5400
3108	P33	SO5401	SGS	N		2N5401
3109	P38	SST4338	Sil	F	SOT23	2N4338
3110	P39	SST4339	Sil	F		2N4339
3111	P39	SO692	SGS			pnP Vce 300V
3112	P4	BFR92R	Phi	R	SOT23R	BFR90
3113	P4	BB134	Phi	I	SOD 323	UHF Varicap 2-12pF
3114	P40	SST4340	Sil	F	SOT23	2N4340
3115	P41	SST4341	Sil	F	SOT23	2N4341
3116	P5	BB135	Phi	I	SOD 323	UHF Varicap 2-12pF
3117	P5	BFR92AR	Phi	R	SOT23R	BFR90A
3118	P5	FMMT2369A	Zet	N		2N2369A
3119	P5	HSMS-2855	HP	S	SOT143	separate pair HSMS-2850
3120	P57	SST5457	Sil	F	SOT23	2N5457
3151	PD	BSS84L	Mot	M	SOT23	p-ch enh tmosfet
3152	PE	BB155	Phi	I	SOD 323	Low Voltage Varicap
3153	PF	BB156	Phi	I	SOD 323	Low Voltage Varicap
3154	PG	BB157	Phi	I	SOD 323	VHF Varicap 2,7-13,7pF
3155	pG3	PMST5551	Phi	N	SOT323	2N5551
3156	PH	BB158	Phi	I	SOD 323	VHF Varicap 2,5-17,5pF
3157	PH2	SST4302	Sil	F	SOT23	2N4302
3158	PH3	SST4303	Sil	F	SOT23	2N4303
3159	PH4	SST4304	Sil	F	SOT23	2N4304
3160	PJ	BB159	Phi	I	SOD 323	UHF Varicap 2-11pF
3161	pJ1	BSH101	Phi	M	SOT23	n-ch 60V 0.7A mosfet
3162	pJ2	BSH102	Phi	M	SOT23	n-ch 30V 1A mosfet
3163	pJ3	BSH103	Phi	M	SOT23	n-ch 30V 0.8A mosfet
3164	PK	BB164	Phi	I	SOD 323	VHF Varicap 3-22,5pF
3165	PL	BB149A	Phi	I	SOD323	2-12pF varicap
3166	PN	BB190	Phi	I	SOD 323	Low Voltage Varicap
3167	POs	BAR64	Sie	C	SOT23	single 200V RF pin
3168	PPs	BAR64-04	Sie	D	SOT23	dual series 200V RF pin
3169	PPs	BAR64-04W	Sie	D	SOT323	dual series 200V RF pin
3170	PRs	BAR64-05	Sie	B	SOT23	dual cc 200V RF pin
3171	PRs	BAR64-05W	Sie	B	SOT323	dual cc 200V RF pin
3172	PSs	BAR64-06	Sie	A	SOT23	dual ca 200V RF pin
3173	PSs	BAR64-06W	Sie	A	SOT323	dual ca 200V RF pin
3174	Q3	MMBC1321Q3	Mot	N		npn VHF amp fT 0.6GHz
3175	Q4	MMBC1321Q4	Mot	N		npn VHF amp fT 0.6GHz
3176	Q5	MMBC1321Q5	Mot	N		npn VHF amp fT 0.6GHz
3177	QQ	2SC4536	Nec	P		npn RF fT 5.7GHz 2W hFE 40-80
3178	QR	2SC4536	Nec	P		npn RF fT 5.7GHz 2W hFE 60-120
3179	QS	2SC4536	Nec	P		npn RF fT 5.7GHz 2W hFE 100-200
3180	R	BA895	Sie	I	SCD80	
3181	R	BA585	Sie	I	SOD123	pin diode 50mA max
3182	R (white)	BA595	Sie	I	SOD323	UHF pin diode 50mA max
3183	R (yellow)	BA597	Sie	I	SOD323	UHF pin diode 100mA max
3184	R1	BFR93	SGS	N	SOT23	BFR91
3185	R1	HSMS-8101	HP	K	SOT23	10-14GHz schottky mixer

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3186	R1	UMT4401	Rho	N	SC70	2N4401
3187	R13	2SC4885	Nec	WQ	SOT143	npn RF FT 3.5GHz
3188	R1A	SST3904	Rho	N	SOT23	2N3904
3189	R1A	UMT3904	Rho	N	SC70	2N3904
3190	R1A	MMST3904	Rho	N	SC59	2N3904
3191	R1G	SSTA06	Rho	N	SOT23	MPSA06
3192	R1G	MMSTA06	Rho	N	SC59	MPSA06
3193	R1H	SSTA05	Rho	N	SOT23	MPSA05
3194	R1J	SST6427	Rho	N	SOT23	
3195	R1K	MMST6428	Rho	N	SC59	
3196	R1M	SSTA13	Rho	N	SOT23	MPSA13
3197	R1M	MMSTA13	Rho	N	SC59	MPSA13
3198	R1N	SSTA14	Rho	N	SOT23	MPSA14
3199	R1N	MMSTA14	Rho	N	SC59	MPSA14
3200	R1O	MMST5088	Rho	N	SC59	2N5088
3201	R1P	SST2222A	Rho	N	SOT23	2N2222A
3202	R1P	UMT2222A	Rho	N	SC70	2N2222A
3203	R1P	MMST2222A	Rho	N	SC59	2N2222A
3204	R2	BFR93A	Phi	N	SOT23	BFR91A
3205	R2	2SC2351P	Nec	N	SOT23	npn RF FT 4.5 GHz hfe 40-120
3206	R2	2SC4225	Nec	N	SOT323	npn RF FT 4GHz hfe 40-120
3207	R22	2SC3356	Nec	N	SOT23	npn RF FT 7GHz 20V 0.2W
3208	R23	2SC3356Q	Nec	N	SOT23	npn RF FT 7GHz hfe 50-100
3209	R23	2SC4226	Nec	N	SOT323	npn RF FT 4.5 GHz hfe 40-80
3210	R24	2SC3356R	Nec	N	SOT23	npn RF FT 7GHz hfe 80-160
3211	R24	2SC4226	Nec	N	SOT323	npn RF FT 4.5 GHz hfe 70-140
3212	R25	2SC3356S	Nec	N	SOT23	npn RF FT 7GHz hfe 125-250
3213	R25	2SC4226	Nec	N	SOT323	npn RF FT 4.5 GHz hfe 125-250
3214	R26	2SC4093Q	Nec	WQ	SOT143	npn RF FT 6.5 GHz hfe 50-100
3215	R26	2SC5011Q	Nec	WQ	SOT343	npn RF FT 6.5 GHz hfe 50-100
3216	R27	2SC4093R	Nec	WQ	SOT143	npn RF FT 6.5 GHz hfe 80-160
3217	R27	2SC5011R	Nec	WQ	SOT343	npn RF FT 6.5 GHz hfe 80-160
3218	R28	2SC4093S	Nec	WQ	SOT143	npn RF FT 6.5 GHz hfe 125-250
3219	R28	2SC5011S	Nec	WQ	SOT343	npn RF FT 6.5 GHz hfe 125-250
3220	R2A	SST3906	Rho	N	SOT23	2N3906
3221	R2A	UMT3906	Rho	N	SC70	2N3906
3222	R2A	MMST3906	Rho	N	SC59	2N3906
3223	R2B	MMST2907	Rho	N	SC59	2N2907
3224	R2F	SST2907A	Rho	N	SOT23	2N2907A
3225	R2F	UMT2907A	Rho	N	SC70	2N2907A
3226	R2F	MMST2907A	Rho	N	SC59	2N2907A
3227	R2G	SSTA56	Rho	N	SOT23	MPSA56
3228	R2G	MMSTA56	Rho	N	SC59	MPSA56
3229	R2K	MMST8598	Rho	N	SC59	
3230	R2O	MMST5087	Rho	N	SC59	
3231	R2P	MMST5086	Rho	N	SC59	
3232	R2T	SST4403	Rho	N	SOT23	2N4403
3233	R2T	UMT4403	Rho	N	SC70	2N4403
3234	R2T	MMST4403	Rho	N	SC59	2N4403

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3235	R2V	MMSTA64	Rho	N	SC59	MPSA64
3236	R2X	SST4401	Rho	N	SCOT23	2N4401
3237	R2X	MMST4401	Rho	N	SC59	2N4401
3238	R3	2SC2351Q	Nec	N	SOT23	npn RF ft 4.5 GHz hfe 100-200
3239	R3	2SC4225	Nec	N	SOT323	npn RF ft 4GHz hfe 100-200
3240	R32	2SC3583	Nec	N	SOT23	npn RF ft 9GHz @ 20mA
3241	R33	2SC3583Q	Nec	N	SOT23	npn RF ft 9GHz hfe 50-100
3242	R33	2SC4227	Nec	N	SOT323	npn RF ft 7 GHz hfe 40-90
3243	R34	2SC3583R	Nec	N	SOT23	npn RF ft 9GHz hfe 80-160
3244	R34	2SC4227	Nec	N	SOT323	npn RF ft 7 GHz hfe 70-150
3245	R35	2SC3583S	Nec	N	SOT23	npn RF ft 9GHz hfe 125-250
3246	R35	2SC4227	Nec	N	SOT323	npn RF ft 7 GHz hfe 110-240
3247	R36	2SC4094Q	Nec	WQ	SOT143	npn RF ft 9GHz hfe 50-100
3248	R36	2SC5012	Nec	WQ	SOT343	npn RF ft 9GHz hfe 50-100
3249	R37	2SC4094R	Nec	WQ	SOT143	npn RF ft 9GHz hfe 80-160
3250	R37	2SC5012	Nec	WQ	SOT343	2SC4094 but min-mold pkg
3251	R38	2SC4094S	Nec	WQ	SOT143	npn RF ft 9GHz hfe 125-250
3252	R38	2SC5012	Nec	WQ	SOT343	npn RF ft 9GHz hfe 125-250
3253	R3B	SST918	Rho	N	SOT23	2N918
3254	R3B	MMST918	Rho	N	SC59	2N918
3255	R4	BFR93R	Tfk	R		BFR91
3256	R4	2SC4092	Nec	WQ	SOT143	npn RF ft 6GHz hfe 40-120
3257	R42	2SC3585	Nec	N	SOT23	npn RF ft 10GHz @ 10mA
3258	R43	2SC3585Q	Nec	N	SOT23	npn RF ft 10GHz hfe 50-100
3259	R43	2SC4228	Nec	N	SOT323	npn RF ft 8.5GHz hfe 50-100
3260	R44	2SC3585R	Nec	N	SOT23	npn RFFT 10GHz hfe 80-160
3261	R44	2SC4228	Nec	N	SOT323	npn RF ft 8.5GHz hfe 80-160
3262	R45	2SC3585S	Nec	N	SOT23	npn RF ft 10GHz hfe 125-250
3263	R45	2SC4228	Nec	N	SOT323	npn RF ft 8.5GHz hfe 125-250
3264	R46	2SC4095Q	Nec	WQ	SOT143	npn ft10GHz
3265	R46	2SC5013Q	Nec	WQ	SOT343	npn ft10GHz
3266	R47	2SC4095R	Nec	WQ	SOT143	npn ft10GHz
3267	R47	2SC5013R	Nec	WQ	SOT343	npn ft10GHz
3268	R48	2SC4095S	Nec	WQ	SOT143	npn ft10GHz
3269	R48	2SC5013S	Nec	WQ	SOT343	npn ft10GHz
3270	R5	HSMS-8205	HP	S	SOT143	separate pair HSMS-8101
3271	R5	BFR93AR	SGS	R	SOT23R	BFR91A
3272	R5	2SC4092	Nec	WQ	SOT143	npn RF ft 6GHz hfe 100-200
3273	R62	2SC3663	Nec	N	SOT23	npn RF ft 4GHz @1mA
3274	R64	2SC4091	Nec	?WQ		?npn RF ft 4GHz @1mA
3275	R66	2SC4091Q	Nec	?WQ	SOT143	?npn RF ft 4GHz hfe 50-100
3276	R67	2SC4091R	Nec	?WQ	SOT143	?npn RF ft 4GHz hfe 80-160
3277	R68	2SC4091S	Nec	?WQ	SOT143	?npn RF ft 4GHz hfe 125-250
3278	R6A	2SC4187	Nec	N	SOT323	npn RF ft 4GHz hfe 50-100
3279	R6B	2SC4187	Nec	N	SOT323	npn RF ft 4GHz hfe 80-160
3280	R6C	2SC4187	Nec	N	SOT323	npn RF ft 4GHz hfe 125-250
3281	R7	HSMS-8207	HP	RQ	SOT145	HSMS-8101 ring quad mixer
3282	R7	BFR106	Phi	N	SOT23	BFR96S
3283	R8	BFG93A	Sie	TQ	SOT143	BFG90

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3284	R97	SSTIS97	Rho	N	SOT23	TIS97
3285	RA	BFQ81	Sie	N	SOT23	BFQ69 npn fT 5.8GHz
3286	RAs	BF772	Sie	X	SOT143	nnp RF TV tuners
3287	RAT	SSTA28	Rho	N	SOT23	MPSA28
3288	RAT	MMSTA28	Rho	N	SC59	MPSA28
3289	RAV	MMST8908	Rho	N	SC59	
3290	RB	MSC1621	Mot	H		nnp sw 20V 200MHz
3291	RBR	SST6838	Rho	N	SOT23	
3292	RBs	BF771	Sie	N	SOT23	nnp RF fT 8GHz
3293	RBs	BF771W	Sie	N	SOT323	nnp RF fT 8GHz
3294	RCs	BFP193	Sie	X	SOT143	BFQ82 npn fT 8GHz
3295	RCs	BFP193W	Sie	WQ	SOT343	BFQ82 npn fT 8GHz
3296	RCs	BFR193	Sie	N	SOT23	BFQ82 npn fT 8GHz
3297	RCs	BFR193T	Sie	N	SC75	BFQ82 npn fT 8GHz
3298	RDs	BFP180	Sie	X	SOT143	nnp RF 8V 4mA fT 7GHz
3299	RDs	BFP180W	Sie	WQ	SOT343	nnp RF 8V 4mA fT 7GHz
3300	RDs	BFR180	Sie	N	SOT23	nnp RF 8V 4mA fT 7GHz
3301	RDs	BFR180W	Sie	N	SOT323	nnp RF 8V 4mA fT 7GHz
3302	RE	2SC3357	Nec	P	SOT89	nnp RF 1.2W fT 6.5GHz
3303	REs	BFS480	Sie	DJ	SOT363	dual RF npn fT 7GHz
3304	REs	BFR280	Sie	N	SOT23	nnp RF 8V 8mA fT 7.5GHz
3305	REs	BFR280W	Sie	N	SOT323	nnp RF 8V 8mA fT 7.5GHz
3306	REs	BFP280	Sie	X	SOT143	nnp RF 8V 8mA fT 7.5GHz
3307	REs	BFP280W	Sie	WQ	SOT343	nnp RF 8V 8mA fT 7.5GHz
3308	RF	2SC3357	Nec	P	SOT89	nnp RF 1.2W fT 6.5GHz
3309	RFQ	SST6839	Rho	N	SOT23	
3310	RFs	BFR181	Sie	N	SOT23	nnp RF 12V 20mA fT 8GHz
3311	RFs	BFP181	Sie	X	SOT143	nnp RF 12V 20mA fT 8GHz
3312	RFs	BFP181W	Sie	WQ	SOT343	nnp RF 12V 20mA fT 8GHz
3313	RFs	BFS481	Sie	DJ	SOT363	Dual BFR181
3314	RGs	BFR182	Sie	N	SOT23	nnp RF12V 35mA fT 8GHz
3315	RGs	BFR182W	Sie	N	SOT323	nnp RF12V 35mA fT 8GHz
3316	RGs	BFP182	Sie	X	SOT143	nnp RF12V 35mA fT 8GHz
3317	RGs	BFP182W	Sie	WQ	SOT343	nnp RF12V 35mA fT 8GHz
3318	RGs	BFR182T	Sie	N	SC75	nnp RF12V 35mA fT 8GHz
3319	RGs	BFS482	Sie	DJ	SOT363	Dual BFR182
3320	RH	2SC3357	Nec	P	SOT89	nnp RF 1.2W fT 6.5GHz
3321	RHs	BFR183	Sie	N	SOT23	nnp RF 12V 65mA fT 8GHz
3322	RHs	BFR183W	Sie	N	SOT323	nnp RF 12V 65mA fT 8GHz
3323	RHs	BFR183T	Sie	N	SC75	nnp RF 12V 65mA fT 8GHz
3324	RHs	BFP183	Sie	X	SOT143	nnp RF 12V 65mA fT 8GHz
3325	RHs	BFP183W	Sie	WQ	SOT343	nnp RF 12V 65mA fT 8GHz
3326	RHs	BFS483	Sie	DJ	SOT363	Dual BFR183 npn RF
3327	RIIs	BFP196	Sie	X	SOT143	pnp RF 12V 100mA Ft 7.5GHz
3328	RK	2SC3357	Nec	P	SOT89	nnp RF 1.2W fT 6.5GHz
3329	RKM	RK7002	Rho		SOT23	
3330	RKs	BFP194	Sie	X	SOT143	pnp RF 15V 100mA Ft 5GHz
3331	RKs	BFR194	Sie	N	SOT233	pnp RF 15V 100mA Ft 5GHz
3332	RR	BBY59-02V	Inf	I	SC79	hyperabrupt varicap 7-28pF

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3333	RR	BFR93P	Sie	N	SOT23	BFR91
3334	RVZ	MMST4126	Rho	N	SC59	2N4126
3335	RW	BFR194	Sie	N		pnp RF amp 1.5GHz
3336	RZC	SST4124	Rho	N	SOT23	2N4124
3337	RZC	MMST4124	Rho	N	SC59	2N4124
3338	S	BAP64-02	Phi	I	SOD523	3GHz pin diode
3339	S	BB515	Sie	I	SOD123	varicap 17.7pf @ 1V 30V max
3340	S (blue)	BA592	Sie	I	SOD323	BA282
3341	S (red)	BB640	Sie	I	SOD323	70-3pF varicap
3342	S (white)	BB535	Sie	I	SOD323	18-2pF varicap
3343	S (yellow)	BB639	Sie	I	SOD323	39-2.7pF varicap
3344	S0	HSMP-3880	HP	C	SOT23	pin sw diode
3345	S1	HSMP-3881	HP	K	SOT23	pin sw diode
3346	S1	BBY31	Phi	C	SOT23	BB405
3347	S12	BBY39	Phi	B	SOT23	2x BBY31
3348	S14	SST5114	Sil	F	SOT23	2N5114
3349	S15	SST5115	Sil	F	SOT23	2N5115
3350	S16	SST5116	Sil	F	SOT23	2N5116
3351	S16	ZHCS1006	Zet	E	SOT23	60V 1A schottky diode
3352	S1A	S1A	Fch	I	DO214	1N4001
3353	S1B	S1B	Fch	I	DO214	1N4002
3354	S1D	S1D	Fch	I	DO214	1N4003
3355	S1G	S1G	Fch	I	DO214	1N4004
3356	S1J	S1J	Fch	I	DO214	1N4005
3357	S2	BBY40	Phi	C	SOT23	BB809
3358	S2	BFQ31	Zet	N		npn vhf 15V 0.1A
3359	S3	BFQ31R	Zet	R		npn vhf 15V 0.1A
3360	S3	BBY51	Sie	B	SOT23	dual cc varicap
3361	S4	BFQ31A	Zet	N		npn vhf 15V 0.1A
3362	S5	BFQ31AR	Zet	R		npn vhf 15V 0.1A
3363	S5	BBY52	Sie	B	SOT23	dual cc varicap
3364	S5	BAT15-099	Sie	NQ	SOT143	Dual BAT15 schottky
3365	S56	ZHCS506	Zet	E	SOT23	60V 0.5A schottky diode
3366	S6	BAT15-099R	Sie	DQ		Ring quad BAT15 schottky
3367	S6	BF510	Phi	G		BF410A
3368	S7	BF511	Phi	G		BF410B
3369	S7	SST177	Tem	F	SOT23	J177 p-ch analog sw jfet
3370	S7	BAT114-099	Sie	NQ	SOT143	Dual schottky
3371	S70	SST270	Sil	F	SOT23	J270 p-ch jfet
3372	S71	SST271	Sil	F	SOT23	J271 p-ch jfet
3373	S74	SST174	Sil	F	SOT23	J174 p-ch fet
3374	S75	SST175	Sil	F	SOT23	J175 p-ch fet
3375	S76	SST176	Sil	F	SOT23	J176 p-ch fet
3376	S76	ZHCS756	Zet	E	SOT23	60V 0.75A schottky diode
3377	S77	SST177	Sil	F	SOT23	J177 p-ch fet
3378	S7s	BBY53-05	Sie	B	SOT23	dual cc varicap
3379	S7s	BBY53-05W	Sie	B	SOT323	dual cc varicap
3380	S8	BF512	Phi	G		BF410C
3381	S8	BAT14-099	Sie	NQ	SOT143	Dual schottky

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3382	S9	BAT14-099R	Sie	DQ		Quad crossover ring schottky
3383	S9	BF513	Phi	G		BF410D
3384	SA	BSS123	Sie	M	SOT23	n-ch mosfet 100V 0.17A
3385	SBp	BB200	Phi	B	SOT 23	Low Voltage Varicap dual
3386	SCp	BB201	Phi	b	SOT 223	Low Voltage Varicap dual
3387	SD	BSS284	Sie	M	SOT23	p-ch mosfet 50V 0.13A
3388	SE	2SC4703	Nec	P		npn RF 1.8W fT 6GHz
3389	SF	2SC4703	Nec	P		npn RF 1.8W fT 6GHz
3390	SF2	BB804W	Phi	B	SOT 23	VHF Varicap dual
3391	SF5	BB804	Phi	B	SOT 23	VHF Varicap dual
3392	SFs	BB804	Sie	A	SOT23	dual 45-26pF cc VHF varicap
3393	SH	2SC4703	Nec	P		npn RF 1.8W fT 6GHz
3394	SH2	BB814	Sie	A	SOT23	dual 45-20pF cc varicap
3395	SM	BB914	Sie	B	SOT23	dual varicap for FM radio
3396	SP	BSS84	Sie	M	SOT23	p-ch mosfet 50V 0.13A
3397	SR	BSS131	Sie	M	SOT23	n-ch mosfet 240V 0.1A
3398	SS	BSS138	Sie	M	SOT23	n-ch mosfet 50V 0.22A
3399	sSG	SN7002	Sie	M	SOT23	n-ch mosfet 60V 0.19A
3400	ST	BSS139	Sie	M	SOT23	n-ch dep mosfet 250V 0.04A
3401	T	BAR67-02W	Sie	I	SCD80	
3402	T	BB811	Sie	I	SOD123	9.8pF @ 1V 30V max
3403	T0	TP0601T	Tem	M		p-ch mosfet 60V 0.12A
3404	T0	HSMS-2860	HP	C	SOT23	zero bias schottky diode
3405	T0	HSMS-286B	HP	C	SOT323	zero bias schottky diode
3406	t01	PDTA143ET	Phi	N	SOT23	npn dtr 4k7+4k7
3407	t02	PDTC143ET	Phi	N	SOT23	npn 4k7+4k7 bias res
3408	t04	PMBS3904	Phi	N	SOT23	2N3904
3409	t06	PMBS3906	Phi	N	SOT23	2N3906
3410	T1	BCX17	Phi	N	SOT23	BC327
3411	T1	IMT1A	Roh	DA		2 x 2SA1037AK npn
3412	T1	BSS63	Mot	N	SOT23	npn 100V 0.1A
3413	t11	PDTA114TT	Phi	N	SOT23	npn dtr
3414	t12	PDTC114TT	Phi	N	SOT23	npn dtr
3415	t16	PDTC114EU	Phi	N	SOT323	npn dtr
3416	t17	PDTC124EU	Phi	N	SOT323	npn dtr
3417	t18	PDTC143ZT	Phi	N	SOT23	npn dtr 4k7+47k
3418	t19	PDTA143ZT	Phi	N	SOT23	npn dtr 4k7+47k
3419	t1A	PMMT3904	Phi	N	SOT23	2N3904
3420	t1A	PMST3904	Phi	N	SOT323	2N3904
3421	t1B	PMBT2222	Phi	N	SOT23	2N2222
3422	t1B	PMST2222	Phi	N	SOT233	2N2222
3423	t1D	PMBTA42	Phi	N	SOT23	MPSA42 300V npn
3424	t1D	PMSTA42	Phi	N	SOT323	MPSA42 300V npn
3425	t1E	PMBTA43	Mot	N	SOT23	MPSA43 200V npn
3426	t1E	PMSTA43	Mot	N	SOT323	MPSA43 200V npn
3427	t1F	PMBT5550	Phi	N	SOT23	2N5550 140V npn
3428	t1F	PMST5550	Phi	N	SOT323	2N5550 140V npn
3429	t1G	PMMTA06	Phi	N	SOT23	MPSA06
3430	t1G	PMMTA06	Phi	N	SOT323	MPSA06

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3431	t1H	MMBTA05	Phi	N	SOT323	MPSA05
3432	t1J	PMBT2369	Phi	N	SOT23	2N2369
3433	t1J	PMBT2369	Phi	N	SOT323	2N2369
3434	t1K	PMBT6428	Phi	N	SOT23	MPSA18 50V
3435	t1K	PMBT6428	Phi	N	SOT323	MPSA18 50V
3436	t1L	PMBT6429	Phi	N	SOT23	MPSA18 45V
3437	t1L	PMBT6429	Phi	N	SOT323	MPSA18 45V
3438	t1M	PMBTA13	Phi	N	SOT23	MPSA13 darlington
3439	t1N	PMBTA14	Mot	N	SOT23	MPSA14 darlington
3440	t1P	PMBT2222A	Phi	N	SOT23	2N2222A
3441	t1P	PMST2222A	Phi	N	SOT323	2N2222A
3442	T1p	BCX17	Phi	N	SOT23	BC327
3443	t1Q	PMBT5088	Phi	N	SOT23	MPSA18 Vce 30V
3444	t1Q	PMST5088	Phi	N	SOT323	MPSA18 Vce 30V
3445	t1R	PMST5089	Phi	N	SOT323	MPSA18 Vce 25V
3446	T1t	BCX17	Phi	N	SOT23	BC327
3447	T2	BCX18	Phi	N	SOT23	BC328
3448	T2	IMT2A	Roh	DB		2 x 2SA1037AK pnp
3449	T2	HSMS-286C	HP	D	SOT323	dual series HSMS-286B
3450	T2	HSMS-2862	HP	D	SOT23	dual series HSMS-286B
3451	t23	PDTA114TU	Phi	N	SOT323	pnp dtr R1 10k
3452	t24	PDTC114TU	Phi	N	SOT323	npn dtr R1 10k
3453	t2A	PMBT3906	Phi	N	SOT23	2N3906
3454	t2A	PMST3906	Phi	N	SOT323	2N3906
3455	t2B	PMBT2907	Phi	N	SOT23	2N2907
3456	t2D	PMBTA92	Phi	N	SOT23	MPSA92 pnp Vce 300V
3457	t2D	PMSTA92	Phi	N	SOT323	MPSA92 pnp Vce 300V
3458	t2E	PMBTA93	Phi	N	SOT23	MPSA93 pnp Vce 200V
3459	t2E	PMSTA93	Phi	N	SOT323	MPSA93 pnp Vce 200V
3460	t2F	PMBT2907A	Phi	N	SOT23	2N2907A
3461	t2F	PMBT2907A	Phi	N	SOT323	2N2907A
3462	t2G	PMBTA56	Phi	N	SOT23	MPSA56
3463	t2G	PMSTA56	Phi	N	SOT323	MPSA56
3464	t2H	PMBTA55	Phi	N	SOT23	MPSA55
3465	t2H	PMSTA55	Phi	N	SOT323	MPSA55
3466	t2L	PMBT5401	Phi	N	SOT23	2N5401 pnp 150V
3467	t2L	PMST5401	Phi	N	SOT323	2N5401 pnp 150V
3468	T2p	BCX18	Phi	N	SOT23	BC328
3469	t2T	PMBT4403	Phi	N	SOT23	2N4403
3470	t2T	PMST4403	Phi	N	SOT323	2N4403
3471	T2t	BCX18	Phi	N	SOT23	BC328
3472	t2U	PMBTA63	Phi	N	SOT23	MPSA63 darlington
3473	t2V	PMBTA64	Phi	H	SOT23	MPSA64 darlington
3474	t2X	PMBT4401	Phi	N	SOT23	2N4401
3475	t2X	PMST4401	Phi	N	SOT323	2N4401
3476	T3	BSS63	Phi	N	SOT23	BSS68
3477	T3	HSMS-286E	HP	A	SOT323	ca dual HSMS-286B
3478	T3	HSMS-2863	HP	A	SOT23	ca dual HSMS-286B
3479	t31	PDTA143XT	Phi	N	SOT23	pnp dtr4k7+10k

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3480	t32	PDTC143XT	Phi	N	SOT23	pnp dtr 4k7+10ks
3481	T32	2SC4182	Nec	N	SOT23	npn RF FT 1.1GHz @3V hfe 60-105
3482	T33	2SC4182	Nec	N	SOT23	npn RF FT 1.1GHz @3V hfe 85-150
3483	T34	2SC4182	Nec	N	SOT23	npn RF FT 1.1GHz @3V hfe 120-220
3484	T4	BCX17R	Phi	R	SOT23R	BC327
3485	T4	HSMS-286F	HP	B	SOT323	cc dual HSMS-286B
3486	T4	HSMS-2864	HP	B	SOT23	cc dual HSMS-286B
3487	T4	MBD330DW	Mot	DL	SOT363	dual UHF schottky diode
3488	T42	2SC3545P	Nec	N		npn RF FT 2GHz hfe 50-100
3489	T42	2SC4184	Nec	N	SOT323	npn RF FT1.8GHz hfe 40-80
3490	T43	2SC3545Q	Nec	N		UHF osc/mix FT 2GHz hfe 70-140
3491	T43	2SC4184	Nec	N	SOT323	npn FT1.8GHz hfe 60-120
3492	T44	2SC3545R	Nec	N		npn RF FT 2GHz hfe 120-250
3493	T44	2SC4184	Nec	N	SOT323	npn RF FT1.8GHz hfe 100-200
3494	T5	HSMS-2865	HP	S	SOT143	separate dual HSMS-286B
3495	T5	BCX18R	Phi	R	SOT23R	BC328
3496	T6	BSS63R	Phi	R	SOT23R	BSS68
3497	T62	2SC3841P	Nec	N	SOT23	npn RF FT 4GHz hfe 40-80
3498	T62	2SC4186	Nec	N	SOT323	npn RF FT 4GHz hfe 40-80
3499	T63	2SC3841Q	Nec	N	SOT23	npn RF FT 4GHz hfe 60-120
3500	T63	2SC4186	Nec	N	SOT323	npn RF FT 4GHz hfe 60-120
3501	T64	2SC3841R	Nec	N	SOT23	npn RF FT 4GHz hfe 100-200
3502	T64	2SC4186	Nec	N	SOT323	npn RF FT 4GHz hfe 100-200
3503	T7	BSR15	SGS	N	SOT23	2N2907
3504	T71	BSR15R	SGS	R	SOT23R	2N2907
3505	T72	2SC4568	Nec	N	SOT23	npn RF ft 5.5GHz hfe 40-80
3506	T72	2SC4570	Nec	N	SOT323	npn RF ft 5.5GHz hfe 40-80
3507	T73	2SC4568	Nec	N	SOT23	npn RF ft 5.5GHz hfe 60-120
3508	T73	2SC4570	Nec	N	SOT323	npn RF ft 5.5GHz hfe 60-120
3509	T74	2SC4568	Nec	N	SOT23	npn RF ft 5.5GHz hfe 100-200
3510	T74	2SC4570	Nec	N	SOT323	npn RF ft 5.5GHz hfe 100-200
3511	T75	2SC4569	Nec	N	SOT23	npn RF FT 5GHz hfe 40-80
3512	T75	2SC4571	Nec	N	SOT323	npn RF FT 5GHz hfe 40-80
3513	T76	2SC4569	Nec	N	SOT23	npn RF FT 5GHz hfe 60-120
3514	T76	2SC4571	Nec	N	SOT323	npn RF FT 5GHz hfe 60-120
3515	T76	2SC4571	Nec	N	SOT323	npn RF FT 5GHz hfe 100-200
3516	T77	2SC4569	Nec	N	SOT23	npn RF FT 5GHz hfe 100-200
3517	T78	2SC5507	Nec	WQ	SOT343	npn RF FT 25GHz 3V 10mA
3518	T79	2SC5508	Nec	WQ	SOT343	npn RF FT 25GHz 3V 30mA
3519	T7p	BSR15	Phi	N	SOT23	2N2907
3520	T7t	BSR15	Phi	N	SOT23	2N2907
3521	T8	BSR16	SGS	N	SOT23	2N2907A
3522	T80	2SC5507	Nec	WQ	SOT343	npn RF FT 17GHz 3V 90mA
3523	T81	BSR16R	SGS	R	SOT23R	2N2907A
3524	T82	2SC4954	Nec	N	SOT23	npn RF FT12GHz @3V 5mA
3525	T82	2SC4956	Nec	WQ	SOT143	npn RF FT 12GHz @3V 5mA
3526	T82	2SC4958	Nec	N	SOT323	npn RF FT 12GHz @3V 5mA
3527	T82	2SC5014	Nec	WQ	SOT343	npn RF FT 12GHz @3V 5mA
3528	T83	2SC4955	Nec	N	SOT23	npn RF FT 12GHz @3V 10mA

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3529	T83	2SC4957	Nec	WQ	SOT143	npn RF FT 12GHz @3V 10mA
3530	T83	2SC4959	Nec	N	SOT323	npn RF FT 12GHz @3V 10mA
3531	T83	2SC5015	Nec	WQ	SOT343	npn RF FT 12GHz @3V 10mA
3532	T84	2SC5177	Nec	N	SOT23	npn RF FT 13GHz @2V 7mA
3533	T84	2SC5179	Nec	N	SOT323	npn RF FT 13GHz @2V 7mA
3534	T84	2SC5178	Nec	WQ	SOT143	npn RF FT 13GHz @2V 7mA
3535	T84	2SC5180	Nec	WQ	SOT343	npn RF FT 13GHz @2V 7mA
3536	T86	2SC5182	Nec	N	SOT23	npn RF FT 12GHz @2V 20mA
3537	T86	2SC5183	Nec	WQ	SOT143	npn RF FT 12GHz @2V 20mA
3538	T86	2SC5184	Nec	N	SOT323	npn RF FT 12GHz @2V 20mA
3539	T86	2SC5183	Nec	WQ	SOT343	npn RF FT 12GHz @2V 20mA
3540	T88	2SC5191	Nec	N	SOT23	npn RF FT 8.5GHz @3V 20mA
3541	T88	2SC5192	Nec	WQ	SOT143	npn RF FT 8.5GHz @3V 20mA
3542	T88	2SC5193	Nec	N	SOT323	npn RF FT 8.5GHz @3V 20mA
3543	T88	2SC5193	Nec	WQ	SOT343	npn RF FT 8.5GHz @3V 20mA
3544	T89	2SC5288	Nec	WQ	SOT143	npn RF
3545	T8p	BSR16	Phi	N	SOT23	2N2907A
3546	T8t	BSR16	Phi	N	SOT23	2N2907A
3547	T90	2SC5289	Nec	WQ	SOT143	npn RF
3548	T92	BSR18A	Fch	N	SOT23	2N3904
3549	T92	2SA1977	Nec	N	SOT23	pnp RF FT 8.5GHz
3550	T92P	BSR18A	Phi	N	SOT23	2N3904
3551	T93	2SA1978	Nec	N	SOT23	pnp RF FT 8.5GHz
3552	TA	2SC5431EB	Nec	N	SC59	npn RF FT 4.3GHz 12V 60mA
3553	TB	2SC5431FB	Nec	N	SC59	npn RF FT 4.3GHz 12V 60mA
3554	TC	2SC5432EB	Nec	N	SC59	npn RF FT 4.5GHz 12V 100mA
3555	TD	2SC5432FB	Nec	N	SC59	npn RF FT 4.5GHz 12V 100mA
3556	TE	2SC5433EB	Nec	N	SC59	npn RF FT 7GHz 10V 65mA
3557	TF	2SC5433FB	Nec	N	SC59	npn RF FT 7GHz 10V 65mA
3558	TFX	BAL99	Mot	V	SOT23	switching diode
3559	tG1	PMBT5551	Phi	N	SOT23	2N5551 npn Vce 140V
3560	tG1	PMST5551	Phi	N	SOT323	2N5551 npn Vce 140V
3561	TH	2SC5434EB	Nec	N	SC59	npn RF FT 8GHz 10V 35mA
3562	TJ	2SC5434FB	Nec	N	SC59	npn RF FT 8GHz 10V 35mA
3563	TK	2SC5435EB	Nec	N	SC59	npn RF FT 12GHz 9V 30mA
3564	TL	2SC5435FB	Nec	N	SC59	npn RF FT 12GHz 9V 30mA
3565	TN	2SC5436EB	Nec	N	SC59	npn RF FT 14GHz 5V 30mA
3566	TP	2SC5436FB	Nec	N	SC59	npn RF FT 14GHz 5V 30mA
3567	TS	2SC5437EB	Nec	N	SC59	npn RF FT 9.5GHz 9V 50mA
3568	TT	2SC5437FB	Nec	N	SC59	npn RF FT 9.5GHz 9V 50mA
3569	TV	2SC5599	Nec	N	SC-70	npn RF FT 5GHz 5.5V 5mA
3570	TV	2SC5600	Nec	N	SC-59	npn RF FT 5GHz 5.5V 15mA
3571	TV	MMBF112L	Mot	F	SOT23	RF jfet
3572	TW	2SC5602	Nec	N	SC-70	npn RF FT 13.5GHz 6V 5mA
3573	TW	2SC5603	Nec	N	SC-59	npn RF FT 13.5GHz 6V 15mA
3574	U	BB545	Sie	I	SOD323	20-2pF varicap
3575	U	BB145	Phi	I	SOD 523	Low Voltage Varicap
3576	U1	BCX19	Mot	N	SOT23	BC337
3577	U1	BGX50A	Sie	BQ	SOT143	quad ring Si sw diodes

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3578	U16	2SC4183	Nec	N		npn RF 5V fT1GHz hFE 60-120
3579	U17	2SC4183	Nec	N		npn RF 5V fT1GHz hFE 90-180
3580	U18	2SC4183	Nec	N		npn RF 5V fT1GHz hFE 120-240
3581	U1A	3SK230A	Nec	UQ	SOT143	dg RF mosfet
3582	U1B	3SK230B	Nec	UQ	SOT143	dg RF mosfet
3583	U1C	3SK231C	Nec	UQ	SOT143	dg RF mosfet
3584	U1D	3SK231D	Nec	UQ	SOT143	dg RF mosfet
3585	U1E	3SK252E	Nec	UQ	SOT143	dg RF mosfet
3586	U1E	3SK254E	Nec	UQ	SOT343	dg RF mosfet
3587	U1G	3SK253G	Nec	UQ	SOT143	dg RF mosfet
3588	U1G	3SK255G	Nec	UQ	SOT343	dg RF mosfet
3589	U1p	BCX19	Phi	N	SOT23	BC337
3590	U1t	BCX19	Phi	N	SOT23	BC337
3591	U2	BCX20	Phi	N	SOT23	BC338
3592	U21	2SC4185	Nec	N		npn RF 10V fT2.4GHz hFE 40-80
3593	U22	2SC4185	Nec	N		npn RF 10V fT2.4GHz hFE 60-120
3594	U23	2SC4185	Nec	N		npn RF 10V fT2.4GHz hFE 90-180
3595	U2t	BCX20	Phi	N	SOT23	BC338
3596	U3	BSS64	Phi	N	SOT23	120V 0.25A 0.2W
3597	U4	BCX19R	Phi	R	SOT23R	BC337
3598	U5	BCX20R	Phi	R	SOT23R	BC338
3599	U55	3SK134B	Nec	UQ	SOT143	dg mosfet
3600	U55	3SK245	Nec	UQ	SOT343	dg mosfet
3601	U56	3SK134B	Nec	UQ	SOT143	dg mosfet
3602	U56	3SK245	Nec	UQ	SOT343	dg mosfet
3603	U6	BSS64R	Phi	R	SOT23R	120V 0.25A 0.2W
3604	U65	3SK135A	Nec	UQ	SOT143	dg mosfet
3605	U66	3SK135A	Nec	UQ	SOT143	dg mosfet
3606	U7	BSR13	SGS	N	SOT23	2N2222
3607	U71	BSR13R	SGS	R	SOT23R	2N2222
3608	U71	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss 5-15mA
3609	U71	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 5-15mA
3610	U72	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss10-25mA
3611	U72	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 10-25mA
3612	U73	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss 20-35mA
3613	U73	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 20-35mA
3614	U74	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss 30-40mA
3615	U74	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 30-40mA
3616	U76	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 10-25mA
3617	U77	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 20-35mA
3618	U78	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 30-50mA
3619	U79	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 45-80mA
3620	U7p	BSR13	Phi	N	SOT23	2N2222
3621	U7t	BSR13	Phi	N	SOT23	2N2222
3622	U8	BSR14	SGS	N	SOT23	2N2222A
3623	U81	BSR14R	SGS	R	SOT23R	2N2222A
3624	U87	3SK176A	Nec	UQ	SOT143	dg mosfet
3625	U88	3SK176A	Nec	UQ	SOT143	dg mosfet
3626	U8p	BSR14	Phi	N	SOT23	2N2222A

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3627	U8t	BSR14	Phi	N	SOT23	2N2222A
3628	U90	3SK223	Nec	UQ	SOT143	dg mosfet
3629	U90	3SK243	Nec	UQ	SOT343	dg mosfet
3630	U91	3SK223	Nec	UQ	SOT143	dg mosfet
3631	U91	3SK243	Nec	UQ	SOT143	dg mosfet
3632	U92	BSR17A	Fch	N	SOT23	2N3904
3633	U92p	BSR17A	Phi	N	SOT23	2N3904
3634	U94	3SK224D	Nec	UQ	SOT143	dg mosfet
3635	U94	3SK244D	Nec	UQ	SOT343	dg mosfet
3636	U95	3SK224E	Nec	UQ	SOT143	dg mosfet
3637	U95	3SK244E	Nec	UQ	SOT143	dg mosfet
3638	UB	2SB852K	Roh	N		pnnp darlington comp 2SD1383K
3639	UC	MSC2404-C	Mot	H		nnp RF 450MHz ft 20V
3640	V01	VN50300T	Sil	M		n-ch enh mosfet 500V 22mA
3641	V02	VN0605T	Sil	M		n-ch enh mosfet 60V/0.18A
3642	V04	VN45350T	Sil	M		n-ch enh mosfet 450V 20mA
3643	V1	MRF959	Mot	N	SC75	nnp RF ft 9GHz
3644	V1	DZ23C2V7	Dio	A	SOT23	dual cc zener 2.7V 0.3W
3645	V10	DZ23C6V2	Dio	A	SOT23	dual cc zener 6.2V 0.3W
3646	V11	3SK131	Nec	UQ	SOT143	dg VHF mosfet
3647	V11	3SK242	Nec	UQ	SOT343	dg VHF mosfet
3648	V11	DZZ23C6V8	Dio	A	SOT23	dual cc zener 6.8V 0.3W
3649	V12	DZZ23C7V5	Dio	A	SOT23	dual cc zener 7.5V 0.3W
3650	V12	3SK131	Nec	UQ	SOT143	dg VHF mosfet
3651	V12	3SK242	Nec	UQ	SOT343	dg VHF mosfet
3652	V13	3SK131	Nec	UQ	SOT143	dg VHF mosfet
3653	V13	ZC932	Zet	C	SOT23	5 - 17pF hyperabrupt varicap
3654	V13	3SK242	Nec	UQ	SOT343	dg VHF mosfet
3655	V13	DZZ23C8V2	Dio	A	SOT23	dual cc zener 8.2V 0.3W
3656	V14	ZC931	Zet	C	SOT23	4 - 13.5pF hyperabrupt varicap
3657	V14	DZZ23C9V1	Dio	A	SOT23	dual cc zener 9.1V 0.3W
3658	V15	ZC930	Zet	C	SOT23	3 - 9pF hyperabrupt varicap
3659	V15	DZZ23C10	Dio	A	SOT23	dual cc zener 10V 0.2W
3660	V16	ZC934	Zet	C	SOT23	25 - 95pF hyperabrupt varicap
3661	V16	DZZ23C11	Dio	A	SOT23	dual cc zener 11V 0.3W
3662	V17	ZC933	Zet	C	SOT23	12 - 42pF hyperabrupt varicap
3663	V17	DZZ23C12	Dio	A	SOT23	dual cc zener 12V 0.3W
3664	V18	DZZ23C13	Dio	A	SOT23	dual cc zener 13V 0.3W
3665	V19	DZZ23C15	Dio	A	SOT23	dual cc zener 15V 0.3W
3666	V1p	BFT25	Phi	N	SOT23	nnp RF 5V 6.5mA 2.3GHz
3667	V2	BFQ67	Tfk	N		nnp RF ft 7.5 GHz 50mA
3668	V2	DZ23C3V0	Dio	A	SOT23	dual cc zener 3.0V 0.3W
3669	V20	DZZ23C16	Dio	A	SOT23	dual cc zener 16V 0.3W
3670	V21	3SK222	Nec	UQ	SOT143	dg VHF mosfet
3671	V21	3SK246	Nec	UQ	SOT343	dg VHF mosfet
3672	V21	DZZ23C18	Dio	A	SOT23	dual cc zener 18V 0.3W
3673	V22	3SK222	Nec	UQ	SOT143	dg VHF mosfet
3674	V22	3SK246	Nec	UQ	SOT343	dg VHF mosfet
3675	V22	DZZ23C22	Dio	A	SOT23	dual cc zener 22V 0.3W

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3676	V23	DZZ23C22	Dio	A	SOT23	dual cc zener 22V 0.3W
3677	V24	DZZ23C24	Dio	A	SOT23	dual cc zener 24V 0.3W
3678	V25	DZZ23C27	Dio	A	SOT23	dual cc zener 27V 0.3W
3679	V26	DZZ23C30	Dio	A	SOT23	dual cc zener 30V 0.3W
3680	V27	DZZ23C33	Dio	A	SOT23	dual cc zener 33V 0.3W
3681	V28	DZZ23C36	Dio	A	SOT23	dual cc zener 36V 0.3W
3682	V29	DZZ23C39	Dio	A	SOT23	dual cc zener 39V 0.3W
3683	V3	BFG67	Phi	X	SOT143	npn RF FT 8GHz 50mA
3684	V3	DZ23C3V3	Dio	A	SOT23	dual cc zener 3.3V 0.3W
3685	V30	DZZ23C43	Dio	A	SOT23	dual cc zener 43V 0.3W
3686	V31	DZZ23C47	Dio	A	SOT23	dual cc zener 47V 0.3W
3687	V32	DZZ23C51	Dio	A	SOT23	dual cc zener 51V 0.3W
3688	V4	DZ23C3V6	Dio	A	SOT23	dual cc zener 3.6V 0.3W
3689	V5	BFG197	Phi	X	SOT143	npn RF 7.5GHz 100mA
3690	V5	DZ23C3V9	Dio	A	SOT23	dual cc zener 3.9V 0.3W
3691	V50	VP0610T	Sil	M		p-ch enh mosfet -60V 120mA
3692	V6	DZ23C4V3	Dio	A	SOT23	dual cc zener 4.3V 0.3W
3693	V7	DZ23C4V7	Dio	A	SOT23	dual cc zener 4.7V 0.3W
3694	V8	DZ23C5V1	Dio	A	SOT23	dual cc zener 5.1V 0.3W
3695	V9	DZ23C5V6	Dio	A	SOT23	dual cc zener 5.6V 0.3W
3696	VB	MSC2295-B	Mot	H		npn RF 150MHz FT 20V
3697	VC	MSC2295-C	Mot	H		npn RF 150MHz FT 20V
3698	W0F	TSDF1205RW	Tfk	WQ	SOT343	12GHz npn 5mA 4V
3699	W18	BFP181TW	Tfk	X		npn RF FT 7.8GHz 10V 20mA
3700	W18	BFP181TRW	Tfk	WQ		npn RF FT 7.8GHz 10V 20mA
3701	W1s	BFT92	Sie	N	SOT23	BFQ51/BFQ76
3702	W1s	BCR10PN	Sie	DP	SOT363	pnp/npn dig 0.1A 10k+10k
3703	W2	TSDF1220RW	Tfk	WQ	SOT343	12GHz npn 6V 20mA
3704	W22	S822TW	Tfk	X		npn rf FT 5.2 GHz 6V 8mA
3705	W22	S822TRW	Tfk	WQ		npn rf FT 5.2 GHz 6V 8mA
3706	W28	BFP280TRW	Tfk	WQ		npn rf FT 7 GHz 8V 10mA
3707	W28	BFP280TW	Tfk	X		npn rf FT 7 GHz 8V 10mA
3708	W3	BZX84-C2V4	Phi	C	SOT23	0.3W zener 2.4V5%
3709	W4	BZX84-C2V7	Phi	C	SOT23	0.3W zener 2.7V5%
3710	W5	BZX84-C3V0	Phi	C	SOT23	0.3W zener 3.0V5%
3711	W52	S852TW	Tfk	X		npn rf FT 5.2 GHz 6V 8mA
3712	W6	BZX84-C3V3	Phi	C	SOT23	0.3W zener 3.3V5%
3713	W67	BFP67W	Tfk	X		npn rf FT 7.5 GHz 10V 50mA
3714	W7	BZX84-C3V6	Phi	C	SOT23	0.3W zener 3.6V5%
3715	W8	BZX84-C3V9	Phi	C	SOT23	0.3W zener 3.9V5%
3716	W8	BZV49C3V9	Zet	O	SOT89	1W zener 3.9V5%
3717	W82	BFP182TRW	Tfk	WQ		npn rf FT 7.5 GHz 10V 35mA
3718	W82	BFP182TW	Tfk	X		npn rf FT 7.5 GHz 10V 35mA
3719	W83	BFP183TRW	Tfk	WQ		npn rf FT 7.4 GHz 10V 65mA
3720	W83	BFP183T	Tfk	X		npn rf FT 7.4 GHz 10V 65mA
3721	W9	BZX84-C4V3	Phi	C	SOT23	0.3W zener 4.3V5%
3722	W9	BZV49C4V3	Zet	O	SOT89	1W zener 4.3V5%
3723	W92	BFP92AW	Tfk	X	SOT343	npn rf FT 6 GHz 15V 30mA
3724	WB	2SD1383K	Roh	N		npn darlington comp 2SB852K

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3725	WCs	BCR133	Sie	N	SOT23	npn dig 50V 0.1A 10k+10k
3726	WCs	BCR133T	Sie	N	SC75	npn dig 50V 0.1A 10k+10k
3727	WCs	BCR133U	Sie	N	SOT457	npn dig 50V 0.1A 10k+10k
3728	WCs	BCR133W	Sie	N	SOT323	npn dig 50V 0.1A 10k+10k
3729	WCs	BCR133S	Sie	DN	SOT363	dual BCR133
3730	WDs	BCR141	Sie	N	SOT23	npn 50V 0.1A dig 22k +22k
3731	WDs	BCR141T	Sie	N	SC75	npn 50V 0.1A dig 22k +22k
3732	WDs	BCR141W	Sie	N	SOT323	npn 50V 0.1A dig 22k +22k
3733	WDs	BCR141S	Sie	DN	SOT363	dual BCR141
3734	WE1	BFS17W	Tfk	N		npn rf FT 2.1GHz SOT-323
3735	WE2	BFS17AW	Tfk	N		npn rf FT 3.2GHz SOT-323
3736	WEs	BCR148	Sie	N	SOT23	npn 50V 0.1A dig 47k +47k
3737	WEs	BCR148T	Sie	N	SC75	npn 50V 0.1A dig 47k +47k
3738	WEs	BCR148U	Sie	N	SOT457	npn 50V 0.1A dig 47k +47k
3739	WEs	BCR148W	Sie	N	SOT323	npn 50V 0.1A dig 47k +47k
3740	WEs	BCR148S	Sie	DN	SOT363	dual BCR148
3741	WF0	TSDF1205W	Tfk	X	SOT343	12 GHz npn 5mA 4V
3742	WF2	TSDF1220W	Tfk	X	SOT343	12GHz npn 6V 20mA
3743	WFE	BFP93A	Tfk	X	SOT343	BFP93A (FE) in 6GHz npn
3744	WFs	BCR08PN	Sie	DP	SOT363	pnp/npn dig 0.1A 2k2+47k
3745	WFs	BCR112	Sie	N	SOT23	npn dig 50V 0.1A 4k7+4k7
3746	WGs	BCR116	Sie	N	SOT23	npn dig 50V 0.1A 4k7+47k
3747	WGs	BCR116W	Sie	N	SOT323	npn dig 50V 0.1A 4k7+47k
3748	WHs	BCR108	Sie	N	SOT23	npn dig 50V 0.1A 2k2+47k
3749	WHs	BCR108T	Sie	N	SC75	npn dig 50V 0.1A 2k2+47k
3750	WHs	BCR108W	Sie	N	SOT323	npn dig 50V 0.1A 2k2+47k
3751	WHs	BCR108S	Sie	DN	SOT363	dual BCR108
3752	WIs	BCR158	Sie	N	SOT23	pnp dig 50V 0.1A 2k2+47k
3753	WIs	BCR158T	Sie	N	SC75	pnp dig 50V 0.1A 2k2+47k
3754	WIs	BCR158W	Sie	N	SOT323	pnp dig 50V 0.1A 2k2+47k
3755	WJs	BCR135	Sie	N	SOT23	npn dig 50V 0.1A 10k+47k
3756	WJs	BCR135T	Sie	N	SC75	npn dig 50V 0.1A 10k+47k
3757	WJs	BCR135W	Sie	N	SOT323	npn dig 50V 0.1A 10k+47k
3758	WJs	BCR135S	Sie	DN	SOT363	dual BCR135
3759	WKs	BCR119	Sie	N	SOT23	npn dig 50V 0.1A 4k7
3760	WKs	BCR119S	Sie	DN	SOT363	npn dig 50V 0.1A 4k7
3761	WKs	BCR119W	Sie	N	SOT323	npn dig 50V 0.1A 4k7
3762	WLs	BCR146	Sie	N	SOT23	dual npn dig 50V 47k+22k
3763	WLs	BCR146W	Sie	N	SOT323	dual npn dig 50V 47k+22k
3764	WMO	BF998RW	Tfk	UQ	SOT343R	vhf dg mosfet BF988
3765	WMs	BCR183	Sie	N	SOT23	pnp dig 50V 10k+10k
3766	WMs	BCR183W	Sie	N	SOT323	pnp dig 50V 10k+10k
3767	WMs	BCR183T	Sie	N	SC75	pnp dig 50V 10k+10k
3768	WMs	BCR183U	Sie	N	SOT457	pnp dig 50V 10k+10k
3769	WMs	BCR183S	Sie	DO	SOT363	dual pnp dig 50V 10k+10k
3770	WNs	BCR185	Sie	N	SOT23	pnp dig 50V 0.1A 10k+47k
3771	WNs	BCR185U	Sie	N	SOT457	pnp dig 50V 0.1A 10k+47k
3772	WNs	BCR185W	Sie	N	SOT323	pnp dig 50V 0.1A 10k+47k
3773	WNs	BCR185S	Sie	DO	SOT363	dual BCR185

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3774	WO	BZX284-B2V4	Phi	I	SOD110	0.4W zener 2.4V E24 2%
3775	WOs	BCR191	Sie	N	SOT23	pnnp dig 50V 0.1A 22k+22k
3776	WOs	BCR191W	Sie	N	SOT323	pnnp dig 50V 0.1A 22k+22k
3777	WOs	BCR191S	Sie	DO	SOT363	dual BCR191
3778	WP	BZX284-B2V7	Phi	I	SOD110	0.4W zener 2.7V E24 2%
3779	WP2	BFR92A	Tfk	N	SOT23	BRF90A
3780	WPs	BCR192	Sie	N	SOT23	pnnp dig 50V 0.1A 22k+47k
3781	WPs	BCR192T	Sie	N	SC75	pnnp dig 50V 0.1A 22k+47k
3782	WPs	BCR192W	Sie	N	SOT323	pnnp dig 50V 0.1A 22k+47k
3783	WPs	BCR22PN	Sie	DP	SOT363	pnnp/npn dig 0.1A 22k+22k
3784	WQ	BZX284-B3V0	Phi	I	SOD110	0.4W zener 3.0V E24 2%
3785	WR	MSD602R	Mot	N	SOT346	npn gp 25V 150mA
3786	WR	BZX284-B3V3	Phi	I	SOD110	0.4W zener 3.3V E24 2%
3787	WR2	BFR93AW	Tfk	N		BRF91A
3788	WRE	BFR280TW	Tfk	N		npn RF ft 7.5GHz
3789	WRF	BFR181TW	Tfk	N		npn RF ft 7.8GHz
3790	WRG	BFR182TW	Tfk	N		npn RF ft 7GHz
3791	WRH	BFR183TW	Tfk	N		npn RF ft 7.4GHz
3792	WRs	BCR198	Sie	N	SOT23	pnnp dig 50V 0.1A 47k+47k
3793	WRs	BCR198W	Sie	NN	SOT323	pnnp dig 50V 0.1A 47k+47k
3794	WRs	BCR198S	Sie	D	SOT363	dual BCR198
3795	WS	BCR169	Sie	N	SOT23	pnnp dig 50V 0.1A 4k7
3796	WS	BCR169W	Sie	N	SOT323	pnnp dig 50V 0.1A 4k7
3797	WS	BCR169S	Sie	DO	SOT363	dual BC169
3798	WS	BZX284-B3V6	Phi	I	SOD110	0.4W zener 3.6V E24 2%
3799	WT	BCR166	Sie	N	SOT23	pnnp dig 50V 0.1A 4k7+47k
3800	WT	BCR166W	Sie	N	SOT323	pnnp dig 50V 0.1A 4k7+47k
3801	WT	BCR48PN	Sie	DP	SOT363	pnnp/npn dig npn 2x47k pnp 2k2+47k
3802	WT	BZX284-B3V9	Phi	I	SOD110	0.4W zener 3.9V E24 2%
3803	WU	BCR162	Sie	N	SOT23	pnnp dig 50V 0.1A 4k7+4k7
3804	WU	BCR162T	Sie	N	SC75	pnnp dig 50V 0.1A 4k7+4k7
3805	WU	BCR35PN	Sie	DP	SOT363	pnnp/npn dig 0.1A 10k+47k
3806	WU	BZX284-B4V3	Phi	I	SOD110	0.4W zener 4.3V E24 2%
3807	WU	MRF2947A	Mot	DG	SOT363	dual MRF941 npn RF 9GHz
3808	X	BB187	Phi	I	SOD 523	VHF Varicap 2,7-13,7pF
3809	X (white)	BB833	Sie	I	SOT323	9.3-0.75pF varicap
3810	X (yellow)	BB835	Sie	I	SOT323	9.1-0.6pF varicap
3811	X1	BFT93	Sie	N	SOT23	BFQ23 BFQ75
3812	X1	IMX1	Roh	DC		dual 2SC2412K npn
3813	X1	BZX84-C27	Phi	C	SOT23	0.3W zener 27V5%
3814	X1p	BFT93	Phi	N	SOT23	BFQ23 BFQ75
3815	X2	IMX2	Roh	DD		dual 2SC2412K npn
3816	X2	BZX99-C13	Phi	C	SOT23	13V 0.3W zener 5%
3817	X2	BZX84-C30	Zet	C	SOT23	0.3W zener 30V5%
3818	X2	BZV49C30	Zet	O	SOT89	1W zener 30V5%
3819	X3	BZX99-C15	Phi	C	SOT23	15V 0.3W zener 5%
3820	X3	BZX84-C33	Zet	C	SOT23	0.3W zener 33V5%
3821	X4	BFT93R	Sie	R	SOT23R	BFQ23 BFQ75
3822	X4	BZX84-C36	Zet	C	SOT23	0.3W zener 36V5%

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3823	X5	BZV49C39	Zet	O	SOT89	1W zener 39V5%
3824	X5	MMBV409G	Mot	C	SOT23	Hyperabrupt varicap
3825	X6	BZV49C43	Zet	O	SOT89	1W zener 43V5%
3826	X6	BZX84-C43	Zet	C	SOT23	0.3W zener 43V5%
3827	X7	BZX84-C47	Zet	C	SOT23	0.3W zener 47V5%
3828	XA	BZX284-B7V5	Phi	I	SOD110	0.4W zener 7.5V E24 2%
3829	XA	BZX99-C4V7	Phi	C	SOT23	4.7V 0.3W zener
3830	XAs	BCR503	Sie	N	SOT23	npn dtr 50V 0.5A 2k2 +2k2
3831	XB	BZX284-B8V2	Phi	I	SOD110	0.4W zener 8.2V E24 2%
3832	XB	BZX99-C5V1	Phi	C	SOT23	5.1V 0.3W zener
3833	XBs	BCR553	Sie	N	SOT23	pnp dtr 50V 0.5A 2k2 +2k2
3834	XC	BZX284-B9V1	Phi	I	SOD110	0.4W zener 9.1V E24 2%
3835	XC	BZX99-C5V6	Phi	C	SOT23	5.6V 0.3W zener
3836	XCs	BCR533	Sie	N	SOT23	npn dtr 50V 0.5A 10k + 10k
3837	XD	BZX284-B10	Phi	I	SOD110	0.4W zener 10V E24 2%
3838	XD	BZX99-C6V2	Phi	C	SOT23	6.2V 0.3W zener
3839	XDs	BCR555	Sie	N	SOT23	pnp dtr 50V 0.5A 2k2 +10k
3840	XE	BZX284-B11	Phi	I	SOD110	0.4W zener 11V E24 2%
3841	XE	BZX99-C6V8	Phi	C	SOT23	6.8V 0.3W zener
3842	XF	BZX284-B12	Phi	I	SOD110	0.4W zener 12V E24 2%
3843	XF _s	BCR512	Sie	N	SOT23	npn dtr 50V 0.5A 4k7+ 4k7
3844	XG	BZX284-B13	Phi	I	SOD110	0.4W zener 13V E24 2% S
3845	XGs	BCR523	Sie	N	SOT23	npn dtr 50V 0.5A 1k0 +10k
3846	XH	BZX284-B15	Phi	I	SOD110	0.4W zener 15V E24 2%
3847	XH	MMSD701	Mot	I	SOD123	MMBD701
3848	XH _s	BCR573	Sie	N	SOT23	pnp dtr 50V 0.5A 1k0 +10k
3849	XI	BZX284-B16	Phi	I	SOD110	0.4W zener 16V E24 2%
3850	XJ	BZX284-B18	Phi	I	SOD110	0.4W zener 18V E24 2%
3851	XK	BZX284-B20	Phi	I	SOD110	0.4W zener 20V E24 2%
3852	XK _s	BCR519	Sie	N	SOT23	npn dtr 50V 0.5A R1 4k7
3853	XL	BZX284-B22	Phi	I	SOD110	0.4W zener 22V E24 2%
3854	XL	BZX99-C2V4	Phi	C	SOT23	2.4V 0.3W zener
3855	XL _s	BCR569	Sie	N	SOT23	pnp dtr 50V 0.5A R1 4k7
3856	XM	BZX284-B24	Phi	I	SOD110	0.4W zener 24V E24 2%
3857	XM	BZX99-C2V7	Phi	C	SOT23	2.7V 0.3W zener
3858	XM _s	BCR583	Sie	N	SOT23	pnp dtr 50V 0.5A 10k +10k
3859	XN	BZX284-B27	Phi	I	SOD110	0.4W zener 27V E24 2%
3860	XN	BZX99-C3V0	Phi	C	SOT23	3.0V 0.3W zener
3861	XO	BZX284-B30	Phi	I	SOD110	0.4W zener 30V E24 2%
3862	XP	MMBD3000	Mot	C	SOT346	Si diode 30V 0.2A
3863	XP	BZX284-B33	Phi	I	SOD110	0.4W zener 33V E24 2%
3864	XP	BZX99-C3V3	Phi	C	SOT23	3.3V 0.3W zener
3865	XQ	MMBD3005	Mot	A	SOT346	dual ca MMBD3000
3866	XQ	BZX284-B36	Phi	I	SOD110	0.4W zener 36V E24 2%
3867	XQ	2PD602AQ	Phi	N	SOT346	gp npn hfe 85-170
3868	XR	BZX284-B39	Phi	I	SOD110	0.4W zener 39V E24 2%
3869	XR	BZX99-C3V6	Phi	C	SOT23	3.6V 0.3W zener
3870	XR	MRF2947RA	Mot	DH	SOT363	dual MRF941 npn RF 9GHz
3871	XR	2PD602AR	Phi	N	SOT346	gp npn hfe 120-240

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3872	XS	MMBD3010	Mot	B	SOT346	dual cc MMBD3000
3873	XS	BZX284-B43	Phi	I	SOD110	0.4W zener 43V E24 2%
3874	XS	BZX99-C3V9	Phi	C	SOT23	3.9V 0.3W zener
3875	XS	2PD602AS	Phi	N	SOT346	gp npn hfe 170-340
3876	XT	BZX284-B47	Phi	I	SOD110	0.4W zener 47V E24 2%
3877	XT	MMSD301	Mot	I	SOD123	MBD301
3878	XT	BZX99-C4V3	Phi	C	SOT23	4.3V 0.3W zener
3879	XU	BZX284-B51	Phi	I	SOD110	0.4W zener 51V E24 2%
3880	XU	MRF2947RA	Mot	DH		dual MRF941 npn RF 9GHz
3881	XU	BZX99-C7V5	Phi	C	SOT23	7.5V 0.3W zener
3882	XUs	BCR562	Sie	N	SOT23	pnp dtr 50V 0.5A 4k7+ 4k7
3883	XV	BZX284-B56	Phi	I	SOD110	0.4W zener 56V E24 2%
3884	XV	BZX99-C8V2	Phi	C	SOT23	8.2V 0.3W zener
3885	XVs	BCR521	Sie	N	SOT23	nnp dtr 50V 0.5A 1k0 +1k0
3886	XW	BZX284-B62	Phi	I	SOD110	0.4W zener 62V E24 2%
3887	XW	BZX99-C9V1	Phi	C	SOT23	9.1V 0.3W zener
3888	XWs	BCR505	Sie	N	SOT23	nnp dtr 50V 0.5A 2k2 +10k
3889	XX	BZX284-B68	Phi	I	SOD110	0.4W zener 68V E24 2%
3890	XX	BZX99-C10	Phi	C	SOT23	10V 0.3W zener
3891	XXs	BCR571	Sie	N	SOT23	pnp dtr 50V 0.5A 1k0 +1k0
3892	XY	BZX99-C11	Phi	C	SOT23	11V 0.3W zener
3893	XY	BZX284-B75	Phi	I	SOD110	0.4W zener 75V E24 2%
3894	XZ	BZX99-C12	Phi	C	SOT23	12V 0.3W zener
3895	Y	BB182B	Phi	I	SOD 523	VHF Varicap
3896	Y0s	CGY121B	Sie			GaAs MMIC
3897	Y1	BZX84-C11	Phi	C	SOT23	0.3W zener 11V5%
3898	Y1	BZV49C11	Zet	O	SOT89	1W zener 11V 5%
3899	Y10	BZX84-C27	Phi	C	SOT23	0.3W zener 27V5%
3900	Y11	BZX84-C30	Phi	C	SOT23	0.3W zener 30V5%
3871	XR	2PD602AR	Phi	N	SOT346	gp npn hfe 120-240
3872	XS	MMBD3010	Mot	B	SOT346	dual cc MMBD3000
3873	XS	BZX284-B43	Phi	I	SOD110	0.4W zener 43V E24 2%
3874	XS	BZX99-C3V9	Phi	C	SOT23	3.9V 0.3W zener
3875	XS	2PD602AS	Phi	N	SOT346	gp npn hfe 170-340
3876	XT	BZX284-B47	Phi	I	SOD110	0.4W zener 47V E24 2%
3877	XT	MMSD301	Mot	I	SOD123	MBD301
3878	XT	BZX99-C4V3	Phi	C	SOT23	4.3V 0.3W zener
3879	XU	BZX284-B51	Phi	I	SOD110	0.4W zener 51V E24 2%
3880	XU	MRF2947RA	Mot	DH		dual MRF941 npn RF 9GHz
3881	XU	BZX99-C7V5	Phi	C	SOT23	7.5V 0.3W zener
3882	XUs	BCR562	Sie	N	SOT23	pnp dtr 50V 0.5A 4k7+ 4k7
3883	XV	BZX284-B56	Phi	I	SOD110	0.4W zener 56V E24 2%
3884	XV	BZX99-C8V2	Phi	C	SOT23	8.2V 0.3W zener
3885	XVs	BCR521	Sie	N	SOT23	nnp dtr 50V 0.5A 1k0 +1k0
3886	XW	BZX284-B62	Phi	I	SOD110	0.4W zener 62V E24 2%
3887	XW	BZX99-C9V1	Phi	C	SOT23	9.1V 0.3W zener
3888	XWs	BCR505	Sie	N	SOT23	nnp dtr 50V 0.5A 2k2 +10k
3889	XX	BZX284-B68	Phi	I	SOD110	0.4W zener 68V E24 2%
3890	XX	BZX99-C10	Phi	C	SOT23	10V 0.3W zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3891	XXs	BCR571	Sie	N	SOT23	pnp dtr 50V 0.5A 1k0 +1k0
3892	XY	BZX99-C11	Phi	C	SOT23	11V 0.3W zener
3893	XY	BZX284-B75	Phi	I	SOD110	0.4W zener 75V E24 2%
3894	XZ	BZX99-C12	Phi	C	SOT23	12V 0.3W zener
3895	Y	BB182B	Phi	I	SOD 523	VHF Varicap
3896	Y0s	CGY121B	Sie			GaAs MMIC
3897	Y1	BZX84-C11	Phi	C	SOT23	0.3W zener 11V5%
3898	Y1	BZV49C11	Zet	O	SOT89	1W zener 11V 5%
3899	Y10	BZX84-C27	Phi	C	SOT23	0.3W zener 27V5%
3900	Y11	BZX84-C30	Phi	C	SOT23	0.3W zener 30V5%
3931	Y6	BZX84-C18	Phi	C	SOT23	0.3W zener 18V5%
3932	Y60	BZX84-A6V2	Phi	C	SOT23	0.3W zener 6.2V 1%
3933	Y61	BZX84-A6V8	Phi	C	SOT23	0.3W zener 6.8V 1%
3934	Y62	BZX84-A7V5	Phi	C	SOT23	0.3W zener 7.5V 1%
3935	Y63	BZX84-A8V2	Phi	C	SOT23	0.3W zener 8.2V 1%
3936	Y64	BZX84-A9V1	Phi	C	SOT23	0.3W zener 9.1V 1%
3937	Y65	BZX84-A10	Phi	C	SOT23	0.3W zener 10V 1%
3938	Y66	BZX84-A11	Phi	C	SOT23	0.3W zener 11V 1%
3939	Y67	BZX84-A12	Phi	C	SOT23	0.3W zener 12V 1%
3940	Y68	BZX84-A13	Phi	C	SOT23	0.3W zener 13V 1%
3941	Y69	BZX84-A15	Phi	C	SOT23	0.3W zener 15V 1%
3942	Y6s	CGY62	Sie	DS	MW6	GaAs MMIC
3943	Y7	CGY60	Sie	DS	MW6	GaAs preamp MMIC 1.8GHz
3944	Y7	BZX84-C20	Phi	C	SOT23	0.3W zener 20V5%
3945	Y70	BZX84-A16	Phi	C	SOT23	0.3W zener 16V 1%
3946	Y71	BZX84-A18	Phi	C	SOT23	0.3W zener 18V 1%
3947	Y72	BZX84-A20	Phi	C	SOT23	0.3W zener 20V 1%
3948	Y73	BZX84-A22	Phi	C	SOT23	0.3W zener 22V 1%
3949	Y74	BZX84-A24	Phi	C	SOT23	0.3W zener 24V 1%
3950	Y75	BZX84-A27	Phi	C	SOT23	0.3W zener 27V 1%
3951	Y76	BZX84-A30	Phi	C	SOT23	0.3W zener 30V 1%
3952	Y77	BZX84-A33	Phi	C	SOT23	0.3W zener 33V 1%
3953	Y78	BZX84-A36	Phi	C	SOT23	0.3W zener 36V 1%
3954	Y79	BZX84-A39	Phi	C	SOT23	0.3W zener 39V 1%
3955	Y8	CGY120	Sie		MW6	GaAs MMIC
3956	Y8	BZX84-C22	Phi	C	SOT23	0.3W zener 22V5%
3957	Y8	BZV49C22	Zet	O	SOT89	1W zener 22V 5%
3958	Y80	BZX84-A43	Phi	C	SOT23	0.3W zener 43V 1%
3959	Y81	BZX84-A47	Phi	C	SOT23	0.3W zener 47V 1%
3960	Y82	BZX84-A51	Phi	C	SOT23	0.3W zener 51V 1%
3961	Y83	BZX84-A56	Phi	C	SOT23	0.3W zener 56V 1%
3962	Y84	BZX84-A62	Phi	C	SOT23	0.3W zener 62V 1%
3963	Y85	BZX84-A68	Phi	C	SOT23	0.3W zener 68V 1%
3964	Y86	BZX84-A75	Phi	C	SOT23	0.3W zener 75V 1%
3965	Y9	BZX84-C24	Phi	C	SOT23	0.3W zener 24V5%
3966	Y9	BZV49C24	Zet	O	SOT89	1W zener 124V 5%
3967	Y9s	CGY121A	Sie		MW6	GaAs MMIC
3968	YBs	BSS84	Inf	M	SOT23	p-ch mosfet 50V 0.13A
3969	YO	BZX284-C2V4	Phi	I	SOD110	0.4W zener 2.4V E12 5%

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
3970	YP	BZX284-C2V7	Phi	I	SOD110	0.4W zener 2.7V E12 5%
3971	YQ	BZX284-C3V0	Phi	I	SOD110	0.4W zener 3.0V E12 5%
3972	YR	MSD601R	Mot	N	SOT346	npn gp 25V
3973	YR	BZX284-C3V3	Phi	I	SOD110	0.4W zener 3.3V E12 5%
3974	YS	MSD601S	Mot	N	SOT346	npn gp 25V
3975	YS	BZX284-C3V6	Phi	I	SOD110	0.4W zener 3.6V E12 5%
3976	YT	BZX284-C3V9	Phi	I	SOD110	0.4W zener 3.9V E12 5%
3977	YU	BZX284-C4V3	Phi	I	SOD110	0.4W zener 4.3V E12 5%
3978	YV	BZX284-C4V7	Phi	I	SOD110	0.4W zener 4.7V E12 5%
3979	YW	BZX284-C5V1	Phi	I	SOD110	0.4W zener 5.1V E12 5%
3980	YX	BZX284-C5V6	Phi	I	SOD110	0.4W zener 5.6V E12 5%
3981	YY	BZX284-C6V2	Phi	I	SOD110	0.4W zener 6.2V E12 5%
3982	YZ	BZX284-C6V8	Phi	I	SOD110	0.4W zener 6.8V E12 5%
3983	Z	BB145B	Phi	I	SOD 523	Low Voltage Varicap
3984	Z0	SST310	Tem	F	SOT23	J310 n-ch jfet
3985	Z0	PDZ2.4B	Phi	I	SOD323	2.4V 0.4W zener
3986	Z08	SST308	Sil	F	SOT23	J308 n-ch jfet
3987	Z09	SST309	Sil	F	SOT23	J309 n-ch jfet
3988	Z1	BB145B-01	Phi	I	SOD 723	Low Voltage Varicap
3989	Z1	BZX84-C4V7	Phi	C	SOT23	0.3W zener 4.7V
3990	Z1	SSTJ211	Sil	F	SOT23	J211 n-ch jfet
3991	Z1	PDZ2.7B	Phi	I	SOD323	2.7V 0.4W zener
3992	Z1	IMZ1A	Roh	DE		2SC2414 npn,2SA1037AK pnp
3993	Z1	BZV49C4V7	Zet	O	SOT89	1W 5% zener 4.7V
3994	Z1	BZV49C10	Zet	O	SOT89	1W 5% zener 10V
3995	Z10	SST310	Sil	F	SOT23	J310 n-ch jfet
3996	Z10	SST310	Sil	F	SOT23	J310 n-ch jfet
3997	Z11	BZX84-C2V4	Phi	C	SOT23	0.3W zener 2.4V 5%
3998	Z12	BZX84-C2V7	Phi	C	SOT23	0.3W zener 2.7V 5%
3999	Z13	BZX84-C3V0	Phi	C	SOT23	0.3W zener 3.0V 5%
4000	Z14	BZX84-C3V3	Phi	C	SOT23	0.3W zener 3.3V 5%
4001	Z15	BZX84-C3V6	Phi	C	SOT23	0.3W zener 3.6V 5%
4002	Z16	BZX84-C3V9	Phi	C	SOT23	0.3W zener 3.9V 5%
4003	Z17	BZX84-C4V3	Phi	C	SOT23	0.3W zener 4.3V 5%
4004	Z2	BZX84-C5V1	Phi	C	SOT23	0.3W zener 4.7V
4005	Z2	SSTJ212	Sil	F	SOT23	J212 n-ch jfet
4006	Z2	IMZ2A	Roh	DF		2SC2414 npn,2SA1037AK pnp
4007	Z2	PDZ3.0B	Phi	I	SOD323	3.0V 0.4W zener
4008	Z2	BZV49C5V1	Zet	O	SOT89	1W 5% zener 5.1V
4009	Z21	DTC113ZE	Rho	N	EMT3	npn dtr 1k0 + 10k 50V 100mA
4010	Z21	DTC113ZUA	Rho	N	SC70	npn dtr 1k0 + 10k 50V 100mA
4011	Z21	DTC113ZKA	Rho	N	SC59	npn dtr 1k0 + 10k 50V 100mA
4012	Z2U	FMMTA63	Zet	N	SOT23	MPSA63
4013	Z2V	FMMTA64	Zet	N	SOT23	MPSA64
4014	Z3	BZX84-C5V6	Phi	C	SOT23	0.3W zener 5.6V
4015	Z3	PDZ3.3B	Phi	I	SOD323	3.3V 0.4W zener
4016	Z3	2SK1078	Tos	T	SOT89	n-ch mosfet 60V 0.8A
4017	Z3	BZV49C5V6	Zet	O	SOT89	1W 5% zener 5.6V
4018	Z4	BZX84-C6V2	Phi	C	SOT23	0.3W zener 6.2V

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
4019	Z4	PDZ3.6B	Phi	I	SOD323	3.6V 0.4W zener
4020	Z4	2SK1079	Tos	T	SOT89	n-ch mosfet 100V 0.6A
4021	Z4	BZV49C6V2	Zet	O	SOT89	1W 5% zener 6.2V
4022	Z5	BZX84-C6V8	Phi	C	SOT23	0.3W zener 6.8V
4023	Z5	PDZ3.9B	Phi	I	SOD323	3.9V 0.4W zener
4024	Z5	2SK1717	Tos	T	SOT89	n-ch mosfet 60V 2A
4025	Z5	BZV49C6V8	Zet	O	SOT89	1W 5% zener 6.8V
4026	Z50	BZX84-B2V4	Phi	C	SOT23	0.3W zener 2.4V 2%
4027	Z51	BZX84-B2V7	Phi	C	SOT23	0.3W zener 2.7V 2%
4028	Z52	BZX84-B3V0	Phi	C	SOT23	0.3W zener 3.0V 2%
4029	Z53	BZX84-B3V3	Phi	C	SOT23	0.3W zener 3.3V 2%
4030	Z54	BZX84-B3V6	Phi	C	SOT23	0.3W zener 3.6V 2%
4031	Z55	BZX84-B3V9	Phi	C	SOT23	0.3W zener 3.9V 2%
4032	Z56	BZX84-B4V3	Phi	C	SOT23	0.3W zener 4.3V 2%
4033	Z57	BZX84-B4V7	Phi	C	SOT23	0.3W zener 4.7V 2%
4034	Z58	BZX84-B5V1	Phi	C	SOT23	0.3W zener 5.1V 2%
4035	Z59	BZX84-B5V6	Phi	C	SOT23	0.3W zener 5.6V 2%
4036	Z6	BZX84-C7V5	Phi	C	SOT23	0.3W zener 7.5V
4037	Z6	PDZ4.3B	Phi	I	SOD323	4.3V 0.4W zener
4038	Z6	2SJ238	Tos	T	SOT89	p-ch mosfet 60V 1A
4039	Z6	BZV49C7V5	Zet	O	SOT89	1W 5% zener 7.5V
4040	Z60	BZX84-B6V2	Phi	C	SOT23	0.3W zener 6.2V 2%
4041	Z61	BZX84-B6V8	Phi	C	SOT23	0.3W zener 6.8V 2%
4042	Z62	BZX84-B7V5	Phi	C	SOT23	0.3W zener 7.5V 2%
4043	Z63	BZX84-B8V2	Phi	C	SOT23	0.3W zener 8.2V 2%
4044	Z64	BZX84-B9V1	Phi	C	SOT23	0.3W zener 9.1V 2%
4045	Z65	BZX84-B10	Phi	C	SOT23	0.3W zener 10V 2%
4046	Z66	BZX84-B11	Phi	C	SOT23	0.3W zener 11V 2%
4047	Z67	BZX84-B12	Phi	C	SOT23	0.3W zener 12V 2%
4048	Z68	BZX84-B13	Phi	C	SOT23	0.3W zener 13V 2%
4049	Z69	BZX84-B15	Phi	C	SOT23	0.3W zener 15V 2%
4050	Z7	BZX84-C8V2	Phi	C	SOT23	0.3W zener 8.2V
4051	Z7	PDZ4.7B	Phi	I	SOD323	4.7V 0.4W zener
4052	Z7	BZV49C8V2	Zet	O	SOT89	1W 5% zener 8.2V
4053	Z70	BZX84-B16	Phi	C	SOT23	0.3W zener 16V 2%
4054	Z71	BZX84-B18	Phi	C	SOT23	0.3W zener 18V 2%
4055	Z72	BZX84-B20	Phi	C	SOT23	0.3W zener 20V 2%
4056	Z73	BZX84-B22	Phi	C	SOT23	0.3W zener 22V 2%
4057	Z74	BZX84-B24	Phi	C	SOT23	0.3W zener 24V 2%
4058	Z75	BZX84-B27	Phi	C	SOT23	0.3W zener 27V 2%
4059	Z76	BZX84-B30	Phi	C	SOT23	0.3W zener 30V 2%
4060	Z77	BZX84-B33	Phi	C	SOT23	0.3W zener 33V 2%
4061	Z78	BZX84-B36	Phi	C	SOT23	0.3W zener 36V 2%
4062	Z79	BZX84-B39	Phi	C	SOT23	0.3W zener 39V 2%
4063	Z8	BZX84-C9V1	Phi	C	SOT23	0.3W zener 9.1V
4064	Z8	PDZ5.1B	Phi	I	SOD323	5.1V 0.4W zener
4065	Z8	BZV49C9V1	Zet	O	SOT89	1W 5% zener 9.1V
4066	Z80	BZX84-B43	Phi	C	SOT23	0.3W zener 43V 2%
4067	Z81	BZX84-B47	Phi	C	SOT23	0.3W zener 47V 2%

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
4068	Z82	BZX84-B51	Phi	C	SOT23	0.3W zener 51V 2%
4069	Z83	BZX84-B56	Phi	C	SOT23	0.3W zener 56V 2%
4070	Z84	BZX84-B62	Phi	C	SOT23	0.3W zener 62V 2%
4071	Z85	BZX84-B68	Phi	C	SOT23	0.3W zener 68V 2%
4072	Z86	BZX84-B75	Phi	C	SOT23	0.3W zener 75V 2%
4073	Z9	BZX84-C10	Phi	C	SOT23	0.3W zener 10V
4074	Z9	PDZ5.6B	Phi	I	SOD323	5.6V 0.4W zener
4075	ZA	BZX284-C7V5	Phi	I	SOD110	0.4W zener 7.5V 5%
4076	ZA	PDZ6.2B	Phi	I	SOD323	6.2V 0.4W zener
4077	ZB	FMMT4123	Zet	N	SOT23	2N4123
4078	ZB	PDZ6.8B	Phi	I	SOD323	6.8V 0.4W zener
4079	ZB	BZX284-C8V2	Phi	I	SOD110	0.4W zener 8.2V 5%
4080	ZC	FMMT4124	Zet	N	SOT23	2N4124
4081	ZC	BZX284-C9V1	Phi	I	SOD110	0.4W zener 9.1V 5%
4082	ZC	PDZ7.5B	Phi	I	SOD323	7.5V 0.4W zener
4083	ZD	FMMT4125	Zet	N	SOT23	2N4125
4084	ZD	MMBT4125	Mot	N	SOT23	2N4125
4085	ZD	BZX284-C10	Phi	I	SOD110	0.4W zener 10V 5%
4086	ZD	PDZ8.2B	Phi	I	SOD323	8.2V 0.4W zener
4087	ZE	FMMT4126	Zet	N	SOT23	2N4126
4088	ZE	MMBT4123	Nat	N	SOT23	2N4123
4089	ZE	BZX284-C11	Phi	I	SOD110	0.4W zener 11V 5%
4090	ZE	PDZ9.1B	Phi	I	SOD323	9.1V 0.4W zener
4091	ZF	BZX284-C12	Phi	I	SOD110	0.4W zener 12V 5%
4092	ZF	PDZ10B	Phi	I	SOD323	10V 0.4W zener
4093	ZG	BZX284-C13	Phi	I	SOD110	0.4W zener 13V 5%
4094	ZG	PDZ11B	Phi	I	SOD323	11V 0.4W zener
4095	ZH	BZX284-C15	Phi	I	SOD110	0.4W zener 15V 5%
4096	ZH	PDZ12B	Phi	I	SOD323	12V 0.4W zener
4097	ZHK	SM2Z5V1	STM	I	2W SMD	5.1V 2W zener
4098	ZHL	SM2Z5V6	STM	I	2W SMD	5.6V 2W zener
4099	ZHW	SM2Z12	STM	I	2W SMD	12V 2W zener
4100	ZI	BZX284-C16	Phi	I	SOD110	0.4W zener 16V 5%
4101	ZJ	BZX284-C18	Phi	I	SOD110	0.4W zener 18V 5%
4102	ZJ	PDZ13B	Phi	I	SOD323	13V 0.4W zener
4103	ZJF	SM2Z18	STM	I	2W SMD	18V 2W zener
4104	ZJQ	SM2Z30	STM	I	2W SMD	30V 2W zener
4105	ZK	BZX284-C20	Phi	I	SOD110	0.4W zener 20V 5%
4106	ZK	PDZ15B	Phi	I	SOD323	15V 0.4W zener
4107	ZKR	SM2Z150	STM	I	2W SMD	150V 2W zener
4108	ZL	BZX284-C22	Phi	I	SOD110	0.4W zener 22V 5%
4109	ZL	PDZ16B	Phi	I	SOD323	16V 0.4W zener
4110	ZM	BZX284-C24	Phi	I	SOD110	0.4W zener 24V 5%
4111	ZM	PDZ18B	Phi	I	SOD323	18V 0.4W zener
4112	ZN	BZX284-C27	Phi	I	SOD110	0.4W zener 27V 5%
4113	ZN	PDZ20B	Phi	I	SOD323	20V 0.4W zener
4114	ZO	BZX284-C30	Phi	I	SOD110	0.4W zener 30V 5%
4115	ZP	BZX284-C33	Phi	I	SOD100	0.4W zener 33V 5%
4116	ZP	PDZ22B	Phi	I	SOD323	22V 0.4W zener

贴片三极管印字对照

编号	印字	型号	厂家	类型	封装	备注
4117	ZQ	BZX284-C36	Phi	I	SOD110	0.4W zener 36V 5%
4118	ZQ	PDZ24B	Phi	I	SOD323	24V 0.4W zener
4119	Z-Q	2PC4081Q	Phi	N	SOT323	gp npn hfe 120-270
4120	ZR	MSD1819A	Mot	N	SOT323	npn gp 50V
4121	ZR	BZX284-C39	Phi	I	SOD110	0.4W zener 39V 5%
4122	ZR	PDZ27B	Phi	I	SOD323	27V 0.4W zener
4123	Z-R	2PC4081R	Phi	N	SOT323	gp npn hfe 180-390
4124	ZS	BZX284-C43	Phi	I	SOD110	0.4W zener 43V 5%
4125	ZS	PDZ30B	Phi	I	SOD323	30V 0.4W zener
4126	Z-S	2PC4081S	Phi	N	SOT323	gp npn hfe 270-560
4127	ZS1	ZHCS1000	Zet	E	SOT23	30V 1A schottky diode
4128	ZS1	ZHCS1000	Zet	C	SOT23	schottky 1A 30V
4129	ZS5	ZHCS500	Zet	E	SOT23	40V 0.5A schottky diode
4130	ZS7	ZHCS750	Zet	E	SOT23	30V 0.75A schottky diode
4131	ZS7	ZHCS750	Zet	C	SOT23	schottky 0.75A 30V
4132	ZT	BZX284-C47	Phi	I	SOD110	0.4W zener 47V 5%
4133	ZT	PDZ33B	Phi	I	SOD323	33V 0.4W zener
4134	ZtQ	2PC4081Q	Phi	N	SOT323	gp npn hfe 120-270
4135	ZtR	2PC4081R	Phi	N	SOT323	gp npn hfe 180-390
4136	ZtS	2PC4081S	Phi	N	SOT323	gp npn hfe 270-560
4137	ZU	BZX284-C51	Phi	I	SOD110	0.4W zener 51V 5%
4138	ZU	PDZ36B	Phi	I	SOD323	36V 0.4W zener
4139	ZV	BZX284-C56	Phi	I	SOD110	0.4W zener 56V 5%
4140	ZW	BZX284-C62	Phi	I	SOD110	0.4W zener 62V 5%
4141	ZX	BZX284-C68	Phi	I	SOD110	0.4W zener 68V 5%
4142	ZY	BZX284-C75	Phi	I	SOD110	0.4W zener 75V 5%